Published in final edited form as:

Biosens Bioelectron. 2011 October 15; 28(1): 239–242. doi:10.1016/j.bios.2011.07.025.

Multiplexed SOI BioFETs

Aleksandar Vacic¹, Jason M Criscione², Eric Stern³, Nitin K Rajan⁴, Tarek Fahmy^{2,5}, and Mark A. Reed^{1,4}

¹Department of Electrical, Yale University, 15 Prospect St., New Haven, CT 06511, USA

²Department of Biomedical, Yale University, 15 Prospect St., New Haven, CT 06511, USA

³Nanoterra, Inc., Cambridge, MA 02139, USA

⁴Department of Applied Physics, Yale University, 15 Prospect St., New Haven, CT 06511, USA

⁵Department of Chemical Engineering, Yale University, 15 Prospect St., New Haven, CT 06511, USA

Abstract

Nanoscale Field Effect Transistors have emerged as a promising technology for ultrasensitive, unlabeled diagnostic applications. However, their use as quantitative sensors has been problematic because of the need for individual sensor calibration. In this work we demonstrate an internal calibration scheme for multiplexed nanoribbon field effect sensors by utilizing the initial current rates rather than end point detection. A linear response is observed consistent with initial binding kinetics. Moreover, we are able to show that top-down fabrication techniques yield reproducible device results with minimal fluctuations, enabling internal calibration.

1. Introduction

Nanowire Field Effect Transistor (FET) sensor technology has demonstrated tremendous potential for point-of-care (POC) applications and has been successfully used for detection of proteins (Cui et al. 2001), oligonucleotide sequences (Zhang et al. 2008), cellular function (Stern et al. 2008), virus detection (Patolsky et al. 2004) and enzymatic activity (Stern et al. 2010a). Electronic label-free detection is based on nanosensor surface modification with specific receptors capable of recognizing and binding the desired target molecules. Upon binding, the nanosensor surface potential is changed due to the electric charge present on the bound molecule, which modulates the nanosensor surface potential and thus causes an increase or decrease of carriers and device current (Bergveld 1981).

While several qualitative studies have demonstrated the true power of this detection method, the lack of quantitative results diminishes the competitiveness of the bioFET technology with the existing state-of-the-art techniques. A number of previous experiments have been performed on “bottom-up” or chemical vapour deposition (CVD) grown nanowires, but this method suffers from large device-to-device variation in electrical parameters such as threshold voltage, mobility and transconductance (Ishikawa et al. 2009). Given these

© 2011 Elsevier B.V. All rights reserved.

Publisher's Disclaimer: This is a PDF file of an unedited manuscript that has been accepted for publication. As a service to our customers we are providing this early version of the manuscript. The manuscript will undergo copyediting, typesetting, and review of the resulting proof before it is published in its final citable form. Please note that during the production process errors may be discovered which could affect the content, and all legal disclaimers that apply to the journal pertain.

fluctuations, individual device calibration is thus required for quantitative analysis, thus eliminating one of the primary advantages of a microfabrication approach i.e. multiplexing.

In order to minimize the variations of sensor electrical properties and sensing signal, two different approaches are used. One of them, uses device solution transconductance, $g_{m,sol}$ to normalize the total current change, ΔI , (Ishikawa et al. 2009; Stern et al. 2010a) caused by analyte binding, while the other applies a normalization by device baseline current level, I_0 , established prior to analyte addition (Bunimovitch et al. 2006). However, all these methods use bottom-up grown nanowire which are problematic because of their nonuniform characteristics (Stern et al. 2005).

In this work we demonstrate multiplexed sensing of cancer antigens and calibration of Silicon-On-Insulator (SOI) nanoribbon bioFETs fabricated using traditional lithographic methods. The top-down method accounts for the uniformity of device electrical characteristics which gives sensing repeatability and reproducibility. This aspect enables multiplexing, which allows for simultaneous data acquisition with better statistical analysis. The nanosensor surface is modified with capture antibodies which allow specific recognition of target biomarkers. Instead of using end-point detection to quantify device response, we instead measured initial rate, which has been shown using surface plasmon resonance (SPR) for antigen-antibody interactions to be linearly dependent on the analyte concentration (Homola 2003). Furthermore, we show that initial current rate scales linearly with both device baseline current and solution transconductance, supporting the claim of using device electrical parameters for sensor calibration and suppression of device-to-device variation. Using the proposed method, we demonstrated universal calibration curve for device response, for a given biomarker. We conclude by presenting a blind test measurement performed to demonstrate the validity of the internal calibration standard.

2. Materials and Methods

Silicon nanoribbon devices are fabricated from Silicon-on-Insulator (SOI) wafers in a process similar to the one previously described (Stern et al. 2010b). Nanosensor mesas were defined by chlorine reactive ion etching of 4" (100) SOI wafers with 25–35nm of active Si layer (resistivity 1–10 Ωcm) and 145nm of buried oxide and silicon handle used as a backgate. Following the backgate etch and BF_2^+ implantation (Core Systems, Inc., dose $5 \times 10^{15} \text{cm}^{-2}$, energy 8keV, tilt 7°), devices were annealed using a Rapid Thermal Processor (RTP) at 1000°C for 30 seconds for dopant activation. Metal contacts were formed by electron beam deposition of Ti/Al stack (5nm/145nm) and ohmic contacts were formed by an RTP annealing at 450°C for 1 minute with N_2 purge. Devices were protected using hard baked S1813 photoresist. A schematic of a device is shown in Figure 1a. Dies (5 mm $\times$ 5 mm) were packaged using 28-pin ceramic headers (Spectrum Semiconductor Materials, Inc., model CSB02892). Multiplexed I–V and DC time measurements were done using custom made system using a National Instruments Data Acquisition Card and Keithley 2636 Dual Source Measure Unit.

Prior to protection layer deposition, devices were functionalized with 3-aminopropyltriethoxy silane (APTES) functionalization by immersing in 5% (v/v) solution of APTES in toluene in an inert atmosphere for 2 hours. The devices were then baked in a vacuum oven for 4 hours at 180°C .

Antibody functionalization was performed after I–V screening. Prostate specific (PSA) and breast cancer antigens (CA15.3) were chosen for multiplexed detection and calibration. Receptors, anti-PSA and anti-CA15.3 were bound to the nanoribbon surface using *N*-hydroxysulfosuccinimide/1-ethyl-3-(3-dimethylaminopropyl)carbodiimide hydrochloride

(NHS/EDC) chemistry in 1X phosphate buffer saline (PBS, Sigma) at pH 7.4 for 2 hours (Selo et al. 1996). Samples were then washed with 1 x PBS and a blocking step was performed with 10% fetal bovine serum (FBS) for 30 minutes, followed by washing with sensing buffer (1mM bicarbonate buffer at pH 9).

Sensing experiments were done in direct current (DC) regime with gate-source and drain-source voltages being $V_{gs}=-3V$ and $V_{ds}=0.2V$, respectively, reference Ag/AgCl electrode grounded and a sampling time of $t_s=0.5s$ between DC current measurements. In each sensing experiment devices were first measured in 5 μ l of buffer solution to confirm a stable baseline current, followed by the addition of 5 μ l of analyte solution, upon which the current was observed and recorded.

3. Results and Discussion

Device characteristics were assessed by simultaneous measurement of up to 8 devices on a given die. Fig 1b shows the $I_{DS}-V_{GS}$ characteristics of a representative p-type accumulation mode device. Devices show relatively narrow threshold voltage distribution, with average $V_T=-2.3V$, standard deviation of 0.15V and standard error of the mean of 0.014V for sample of 106 devices. The distribution in threshold voltages is dominated by the nonuniform thickness of the active silicon layer ($70\pm10(3\sigma)$ nm) and variations in the thickness of the thinning dry oxide (up to 5%). Figure 1c shows the variation of threshold voltage for a series of dies, and the corresponding wafer map. Even with the variations of threshold voltage across the entire wafer, we demonstrate results with less than 10% error (see below). In regions with minimal thickness fluctuations (wafer center), we obtain threshold voltage variations of 8mV, standard error of the mean. The off current of dry devices is measured to be on the order 1fA to 100fA which yields good on/off current ratios of approximately 5–6 orders of magnitude. The average subthreshold swing is (630 ± 60) mV/dec which is the consequence of 145nm thick buried oxide layer between the active silicon layer and the backgate. The average drift mobility obtained from peak transconductance is calculated to be (93 ± 17) cm²/Vs which is in agreement with previously obtained values measured on fully depleted SOI RIE defined devices (Habicht et al. 2010).

Bonded chips integrated with a fluidic mixing chamber (Stern et al. 2007) were functionalized with CA15.3 and PSA specific antibodies (anti-CA15.3 and anti-PSA, respectively) using NHS/EDC chemistry. Prior to analyte addition (CA15.3 or PSA), 5 μ l of sensing buffer was left in the mixing chamber and a baseline current I_0 was measured. This was followed by the addition of 5 μ l of analyte solution upon which the current I_{ds} was recorded as a function of time. Current rate was calculated numerically from recorded data after data acquisition. Next we measured initial current rates which are directly proportional to the analyte concentration. Fig 2 shows normalized simultaneous responses of 5 devices on the same chip upon addition of 5 μ l solution of 9.5U/ml CA15.3. Device signals were normalized using their baseline currents established prior to analyte injection. Figure 3 shows that initial current rates are, as expected, linearly proportional to device electrical parameters i.e. baseline current, therefore confirming the validity of our method.

FET current and transconductance are given by

$$i_{ds} = \begin{cases} k(v_g - v_T)v_{ds}, & \text{linear region} \\ \frac{k}{2}(v_g - v_T)^2, & \text{saturation region} \end{cases}$$

and

$$g_m = \frac{\partial i_d}{\partial v_{gs}} = \begin{cases} kv_{ds}, \text{lin.reg.} \\ k(v_{gs} - v_T), \text{sat.reg.} \end{cases},$$

respectively, where v_g is the reference gate potential and v_T is the device pre-sensing threshold voltage. The baseline current i_{ds0} and transconductance g_{m0} prior to analyte addition are linearly related by

$$i_{ds0} = \alpha(v_g - v_T)g_{m0},$$

where $\alpha = \begin{cases} 1, \text{lin.reg.} \\ \frac{1}{2}, \text{sat.reg.} \end{cases}$, which implies that normalizations by device baseline current i_{ds0} and by transconductance g_{m0} would yield the same results if the term $v_g - v_T$ does not change significantly between devices. In prior work (Ishikawa et al. 2009) it was found that the scaling was better for transconductance normalization versus baseline current normalization.

This is because the initial current normalization is given by $\frac{\Delta I}{I_{ds}} = \frac{\Delta v_T}{v_{gs} - v_T}$, where ΔI is the current change caused by the equivalent gating potential Δv of the absorbed biomolecules, and v_T is the threshold voltage of the device. Similarly, the transconductance scaling is given

by $\frac{\Delta I}{\frac{dI_{ds}}{dv_g}} = \Delta v_T$. In the approach presented here the variation of v_T is insignificant (14mV SEM with $|v_T| = 2.3V$, or $< 1\%$), and thus initial current rate or transconductance scaling gives equivalent results.

Measurements were repeated multiple times on different dies using different dilutions of the 9.5U/ml stock solution. A similar procedure was repeated for PSA detection using the serial dilutions of 10ng/ml. Applying the described normalizing method for the three analyte concentrations one can plot calibrations curves, as shown in Fig 4a and 4b for PSA and CA15.3 respectively. The device response is linear in the clinically relevant concentration range (1–10 ng/ml for PSA, 1–10U/ml for CA15.3) (Vizcarra et al. 1996; Wu et al. 2001). Even though the absolute errors of the stock solution concentrations, as determined by ELISA, were relatively large (15–20% for PSA and 40% for CA15.3), the variation of device responses was less than 10% (in terms of the standard error of the mean, SEM). Each data point represents an average over multiple (7 to 10) devices. Both fits have correlation coefficients $R > 0.98$. Table 1 summarizes the calibration results obtained for PSA and CA15.3 and demonstrates the relative standard error of the mean to be less than 10%.

In addition, we tested the calibration method using a blind measurement on a single device and a different measurement setup (red circle, Fig 4a) and compared it to the calibrated data. Upon introducing a concentration of (0.4 ± 0.08) ng/ml of PSA (determined by conventional ELISA) we measured a normalized current rate of $1.0054 \cdot 10^{-4} \text{ s}^{-1}$. Using the calibration curve shown in Fig 4a we calculated the expected value to be (0.46 ± 0.06) ng/ml. This measurement deviates from the concentration obtained by using conventional ELISA by approximately 15%.

4. Conclusion

Here we demonstrate a novel method for internal calibration of nanoscale FETs and use it for quantification of clinically relevant analytes i.e. cancer biomarkers PSA and CA15.3.

This approach is enabled by the ability of the CMOS-compatible fabrication approach we have developed to produce devices with very similar transport characteristics. We use initial kinetic rates, which are directly proportional to the analyte concentrations (assuming an initial unused sensor¹) rather than the endpoint detection. Measured calibration curves show a linear response in the relevant concentration ranges as well as good agreement with a blind measurement. In addition, we demonstrate that calibration by baseline current normalization is equivalent to that obtained by transconductance normalization. Our results demonstrate that nanosensors fabricated by conventional CMOS compatible processes yield reproducible results traceable to a calibration standard. We believe that this approach will make nanoscale FET sensor technology a step closer to commercial point-of-care applications.

Acknowledgments

The authors would like to thank Jason Park for the ELISA tests. This work was partially supported by the National Institutes of Health (NIH R01EB008260), DTRA (HDTRA1-10-1-0037), and the Canadian Institute for Advanced Research (CIFAR).

References

- Bergveld P. *Sensors and Actuators*. 1981; (1):17–29.
- Bunimovitch YL, Shin YS, Yeo W-S, Amori M, Kwong G, Heath JR. *J Am Chem Soc*. 2006; (128): 16323–16331. [PubMed: 17165787]
- Cui Y, Wei Q, Park H, Lieber CM. *Science*. 2001; 293:1289–1292. [PubMed: 11509722]
- Habicht, S.; Feste, SF.; Zhao, QT.; Mantl, S. Solid-State Device Research Conference (ESSDERC). Sevilla: 2010. p. 372-375.
- Homola J. *Anal Bioanal Chem*. 2003; 377:528–539. [PubMed: 12879189]
- Ishikawa FN, Curreli M, Chang H-K, Chen P-C, Zhang R, Cote RJ, Thompson ME, Zhou C. *ACS Nano*. 2009; 3(12):3969–3976. [PubMed: 19921812]
- Patolsky F, Zheng G, Hayden O, Lakadamyali M, Zhuang Z, Lieber CM. *Proceedings of the National Academy of Sciences*. 2004; 101(39):14017–14022.
- Selo I, Negroni L, Creminon C, Wal JM. *Journal of Immunological Methods*. 1996; 199:127–138. [PubMed: 8982354]
- Stern E, Cheng G, Cimpoiu E, Klie R, Guthrie G, Klemic J, Kretzschmar I, Steinlauf E, Turner-Evans DB, Broomfield E, Hyland J, Koudelka R, Boone T, Young M, Sanders A, Munden R, Lee T, Routenberg DA, Reed MA. *Nanotechnology*. 2005; 16.
- Stern E, Klemic JF, Routenberg DA, Wyrembak PN, Turner-Evans DB, Hamilton AD, LaVan DA, Fahmy TM, Reed MA. *Nature*. 2007; 445:519–522. [PubMed: 17268465]
- Stern E, Steenblock ER, Reed MA, Fahmy TM. *Nano Letters*. 2008; 8(10):3310–3314. [PubMed: 18763834]
- Stern E, Vacic A, Li C, Ishikawa FN, Zhou C, Reed MA, Fahmy TM. *Small*. 2010a; 6(2):232–238. [PubMed: 19882688]
- Stern E, Vacic A, Rajan NK, Criscione JM, Park J, Ilic BR, Mooney DJ, Reed MA, Fahmy TM. *Nature Nanotechnology*. 2010b; (5):138–142.
- Vizcarra E, Llunch A, Cibrian R, Jarque F, Alberola V, Belloch V, Garcia-Conde J. *Breast Cancer Res Treat*. 1996; 3(37):209–216. [PubMed: 8825132]
- Wu G, Datar RHKM, Thundat T, Cote RJ, Majumdar A. *Nature Biotechnology*. 2001; 19:856–860.
- Zhang G-J, Zhang G, Chua JH, Chee R-E, Wong EH, Agarwal A, Buddharaju KD, Singh N, Gao Z, Balasubramanian N. *Nano Letters*. 2008; 8(4):1066–1070. [PubMed: 18311939]

¹An interesting case is when the dissociation rate k_{off} is much larger than the product of analyte concentration and the association constant k_{on} . In this case the linear response regime may be very short in time (from $t=0$) and may be difficult to resolve.

Figure 1.

a) Device schematic b) Electrical characteristics, I_{ds} - V_{gs} , and g_m - V_{gs} , of a typical nanoribbon device, c) threshold voltage distribution of nanoribbon devices across a 4" wafer. Each data point is a 5×5 mm die containing up to 8 devices. The inset shows approximate die positions on the wafer. Notation a) and b) in the die label refers to the lower and the upper half of a 10 × 5 mm die. (10,3) is a center column die.

Figure 2.

Normalized current response of 5 functionalized devices on the same chip upon addition of CA15.3, measured simultaneously. I_0 is the baseline current for a given device prior to analyte addition. The arrow indicates injection of the analyte solution. Time traces are intentionally offset by 0.05 along the y-axis for visual clarity.

Figure 3.

Initial current rate of five devices shown in Fig 2 as a function of both baseline currents and device solution transconductances at $V_{\text{backgate}} = -3\text{V}$ and $V_{\text{sol}} = 0\text{V}$. Error bars are approximately the size of the data points. The relative standard deviations for initial current rates, baseline currents and transconductances are 0.7%, 0.3% and 0.6%, respectively. Both fits are linear ($y=kx$), shown on a log-log scale for clarity.

Figure 4. Calibration curves for (a) PSA and (b) CA15.3 show linear device response in the clinically relevant range of analytes. Red data point represents a blind measurement.

Table 1

Calibration points for PSA and CA15.3 obtained on multiple devices demonstrating the relative standard error of the mean to be below 10%

PSA concentration [ng/ml]	Number of devices	Normalized device signal, average [s ⁻¹]	Standard error of the mean [s ⁻¹]	% error
3.3 ± 0.7	7	3.225 10 ⁻⁴	2.9 10 ⁻⁵	8.8
5.0 ± 1.0	10	5.179 10 ⁻⁴	5.1 10 ⁻⁵	9.9
0.22 ± 0.04	8	7.869 10 ⁻⁵	7.5 10 ⁻⁶	9.6
CA 15.3 concentration[U/ml]				
4.75± 1.8	7	1.32 10 ⁻³	5 10 ⁻⁵	3.8
3.2± 1.2	8	8.6 10 ⁻⁴	5 10 ⁻⁵	5.8
0.5± 0.2	9	1.65 10 ⁻⁴	1 10 ⁻⁵	6