Reconstruction of Electroencephalogram Brain Maps by Incorporating the Blind Source Separation Concept

S. Sanei and Ong Sim Heng

Electroencephalogram (EEG) brain maps provide useful and reliable neurodiagnostic information. Accurate reconstruction of the data requires an efficient separation of the electrode signals. Although autoregressive (AR) spectrum estimation highly refines the signals, it cannot remove the effect of adjacent electrode signals. This report describes an efficient blind signal separation (BSS) method. The algorithm identifies the coefficients of an adaptive FIR filter by minimization of a cost function in terms of the corresponding fourth-order cumulants. Applying this method, the quality of the results is far superior to the traditional methods.

Copyright © 2000 by W.B. Saunders Company

PSEUDO-COLORED REAL-TIME brain maps (neuro-images) are two-dimensional images reconstructed from one-dimensional electroencephalogram (EEG) signals.¹ Rhythmic (and some arrhythmic) functional, as well as anatomical abnormalities can be observed in these images. Accurate reconstruction of the images requires an efficient restoration of the signals, as well as variable positioning of the EEG electrodes. Application of an efficient blind signal separation (BSS) technique² not only removes the noise, but also separates each electrode signal from the combination of multisource signals. In addition, the method adjusts the filter coefficients to enable maximum separation. This is achieved when an optimum electrode positioning is obtained.

BSS is a new era in signal processing, and is widely demanded for separation of source signals from their mixture without any priori knowledge about the sources and their combination. A mature approach exploits higher order statistics⁴ in order to extract each signal from the mixture. Here, a novel iterative algorithm based on minimization of fourth-

order contrast function defined as:

$$\phi_4[y] \triangleq \sum_{ijkl} (C_{ijkl}[y] - C_{ijkl}[s])^2$$

has been developed. In this relationship, $C_{ijkl}[y]$ and $C_{ijkl}[s]$ are fourth-order cumulants of the estimated output signal and mixed (electrode) signal samples, respectively. $C_{ijkl}[y] = \text{Cum}[y_i, y_j, y_k, y_l]$ and $C_{ijkl}[s] = k_i \delta_{ijkl}$. In the later formula, δ is the Kronecker symbol⁴ and the kurtosis k_i is defined as $k_i = C_{iiii}[s] = E s_i^4 - 3E^2 s_i^2$. The function should be primarily minimized for each electrode signal. In the above calculation it is assumed that the estimated EEG signals are independent and their combination is convolutive. The approach not only enables real-time reconstruction of the maps, but also inquires repositioning the electrodes in order to meet a minima for the minimum values of ϕ . The procedure highly decreases the effects of adjacent electrodes, as well as any other disturbing interference.

RECONSTRUCTION OF IMAGES

Four images for four frequency sub-bands are then reconstructed. Delta band includes the frequency range $f < 4$ Hz. The tetra band falls within 4 to 8 Hz, the alpha band contains the components $8 < f < 14$ Hz, and the beta band consists of $f > 14$ Hz. The spectrum of each EEG signal is estimated using autoregressive (AR) criterion. In comparison to the Fourier transform method, AR-based spectrum estimation removes idle signal effects more efficiently and further decorrelates various signals. Energy of each signal, as well as its peak value for each sub-band, is measured and assigned to the corresponding electrode positions. Bicubic extrapolation criterion is then exploited to provide a two-dimensional image. Four-color images are then produced by pseudo-hot coloring those images. Cold and hot colors represent less and high activity regions of the brain, respectively.

THE EXPERIMENT AND RESULTS

A set of long-term EEG records was used for the experiment. Only 8-pin EEG was used. Brain damage and tumors (anatomical abnormalities) and

From the Electronic and Communication Department, Singapore Polytechnic; and the Department of Electrical Engineering, National University of Singapore, Singapore.

Address reprint requests to S. Sanei, PhD, Electronic and Communication Department, Singapore Polytechnic, 500 Dover Rd, Singapore 139651. E-mail: ssanei@sp.edu.sg.

Copyright © 2000 by W.B. Saunders Company

0897-1889/00/1302-1063\$10.00/0

doi:10.1053/jdim.2000.6909

Fig 1. Normal condition using AR.

Fig 4. CJD patient using AR and BSS.

Fig 2. Normal condition using AR and BSS.

Fig 5. Patient with tumor using AR.

Fig 3. CJD patient using AR.

Fig 6. Patient with tumor using AR and BSS.

rhythmic abnormalities such as CJD (functional abnormalities) can be easily detected by browsing these images. Frequent arrhythmic problems give rise to the overall spectrum energy, which can also be detected. The images reconstructed using the above method are very informative and provide a comprehensive visualization for physicians and neurodiagnostic specialists. Figures 1 and 2 show normal cases for the traditional method and when BSS is used, respectively. Figures 3 and 4 illustrate a patient with CJD using the same methods.

Finally, Figs 5 and 6 highlight a tumor in the front-lateral part of the brain. An extreme enhancement of the results can be easily seen when the proposed method is applied.

REFERENCES

1. Speekman EJ (ed): *Electroencephalography*. Wiley, 1994
2. Pope KJ, Bogner RE: Blind signal separation 1 & 2. *J DSP* 6:5-28, 1996
3. Nikias CL, Petropulu AP: *Higher-Order Spectra Analysis*. New York, NY, Academic, 1993