Published in final edited form as:

IEEE Trans Ultrason Ferroelectr Freq Control. 2011 December ; 58(12): 2596–2607. doi:10.1109/

TUFEFC.2011.2122

Optimizing Circular Ring Arrays for Forward-Looking IVUS Imaging

Coskun Tekes [Member, IEEE],

Department of Electronics Engineering, Isik University, Istanbul, Turkey and currently with G. W. Woodruff School of Mechanical Engineering, Georgia Institute of Technology, Atlanta, GA. (phone: 404-385-7071)

Mustafa Karaman [Member, IEEE], and

Department of Electronics Engineering, Isik University, Istanbul, Turkey. (phone: +90 216 528-7125)

F. Levent Degertekin [Senior Member, IEEE]

G. W. Woodruff School of Mechanical Engineering, Georgia Institute of Technology, Atlanta, GA. (phone: 404-385-1357)

Coskun Tekes: coskun.tekes@me.gatech.edu; Mustafa Karaman: karaman@isikun.edu.tr; F. Levent Degertekin: levent.degertekin@me.gatech.edu

Abstract

Forward-looking (FL) catheter-based imaging systems are highly desirable for guiding interventions in intravascular ultrasound (IVUS) applications. One of the main challenges of array based FL-IVUS systems is the large channel count which results in increased system complexity. Synthetic phased array processing with reduced firing count simplifies the front-end and hence can enable 3-D real-time imaging. Recently, we have investigated dual-ring arrays suitable for IVUS imaging, where the two concentric circular arrays are used separately as transmit (Tx) and receive (Rx) arrays. In this study, we present different optimized array designs based on dual and single circular rings that are suitable for synthetic phased array processing with reduced number of firings. To obtain optimal firing set that produces low side lobes in the wide-band response, we use simulated annealing algorithm. In the simulations we use 1.2 mm diameter array configurations with 64 Tx and 58 Rx elements, center frequency of 20 MHz and fractional bandwidth of 50% and 80%. The results show that optimized dual ring arrays provide 8 dB improvements in peak near side lobe level with no widening in main lobe width when compared with full and other sparse coarrays.

Index Terms

Ultrasonic imaging; circular array; Forward-Looking; IVUS; simulated annealing; coarray

I. Introduction

Intravascular ultrasound (IVUS) is a useful tool for diagnosing arterial diseases, guiding interventions such as stent deployment and monitoring ablation procedures. IVUS systems are catheter based and provide 2-D cross-sectional images as well as 3-D volumetric images [1–4]. Side-looking (SL) catheter probes with mechanically rotating single transducers provide cross-sectional images of the vessel [5, 6]. Solid-state SL probes use circumferential arrays mounted around the catheter to enable electronic scanning of the cross-sectional area [7–9]. These probes provide high image resolution and are free of mechanical artifacts caused by rotating transducers. A significant shortcoming of these SL probes is the lack of forward-looking (FL) capability to provide true volumetric images in front of the catheter.

These images are highly desirable in guiding interventions especially in the case of chronic total occlusions. Although single transducer based systems where the transducer is mounted on a rotating cam assembly have been realized for FL-IVUS, these systems require a complex, bulky mechanism and complicated beam alignment and calibration protocols [10–12]. Some more recent single element systems either do not provide true volumetric images or still suffer from motion artifacts [13, 14]. Therefore, a solid state miniature transducer array emerges as a key component of a FL-IVUS system for imaging in coronary arteries imaging system. A ring shaped array is a suitable configuration for FL-IVUS where a central opening for a guide wire is required. The CMUT technology is promising for FL-IVUS imaging since it offers high bandwidth, good sensitivity and flexibility to fabricate arrays of different shapes and sizes [15, 16]. In addition, it enables monolithic or flip-chip-bonding integration of front-end electronics [17–19]. By taking advantage of the flexibility offered by CMUT technology, it is possible to utilize the area around the guide wire efficiently by implementing multiplexing arrays for FL-IVUS imaging (Fig. 1). We have demonstrated several successful studies on implementing single and dual ring CMUT arrays for FL-IVUS [20–23].

One of the main challenges in array based FL-IVUS systems is the large channel count which results in increased front-end complexity. Synthetic phased array processing with reduced firing count simplifies the front-end and hence can enable 3-D real-time imaging [24]. To reduce the number of channels and/or firing count, an optimized set of transmit-receive element combinations is essential. For array optimization, various studies have been presented in the literature for both 2-D planar arrays and circular arrays. Most of these studies try to find sparse array layouts with optimized weighting schemes to reduce side lobes and suppress grating lobes in the beam pattern. Smith *et al.* have used different transmit and receive arrays where grating lobes are suppressed by nulling transmit array response with receive array response [25]. Lockwood *et al.* have introduced vernier interpolation with periodic but different transmit-receive arrays [26–28]. Austeng *et al.* have proposed several sparse array designs with symmetric and asymmetric periodic and diagonal array configurations [29]. Johnson *et al.* have investigated volumetric imaging using a small number of firings of phased subarrays over 2-D planar arrays. More recently a set of reduced redundancy 2-D rectangular array configurations have been explored for 3-D ultrasonic imaging [30–32]. Holm *et al.* have proposed optimized array distribution by using linear programming and simulated annealing algorithm for continuous wave far field approximation [33–35]. Later, Trucco has extended this work for wideband 2-D arrays with applying both thinning and weighting by using simulated annealing and genetic algorithms [36–38]. All these approaches use full disk aperture and rectangular planar arrays. For the optimization of FL-IVUS single ring array, Wang *et al.* have proposed an optimal subset of all transmit-receive combinations by using element separation and interleaved arrangement strategy [39]. Most of optimization studies attempt to improve the beam performance using an optimal aperture weighting scheme. This is not desirable in FL-IVUS, because low SNR caused by the small element size and synthetic phased array processing. In this study, we propose optimized array designs for both single and dual ring arrays. The optimization here aims to determine a suitable firing subset which eliminates redundant spatial frequencies in the coarray (effective aperture) and produces low side lobes in the wide-band point spread function (PSF). For this purpose, we used two different coarray sampling schemes and simulated annealing based optimization.

II. Circular Ring Array Processing

A circular ring array best fits on the front surface of a catheter and thus is a preferred array structure for FL-IVUS. Due to the circular symmetry and spatial diversity on the coarray, it produces lower side lobes when compared with periodic rectangular arrays. In addition,

circular ring arrays enable 3-D volumetric imaging by scanning conical volume in front of the array plane. Single or multiple ring arrays can be implemented.

Single ring arrays are formed by coaxial array of elements located around the probe in an equally spaced circumferential manner. The array elements are used in both transmit and receive operation. The viability of FL-IVUS imaging using a single ring array has been demonstrated by several studies in literature [16, 21, 39]. We have recently proposed a CMUT based array configuration consisting of two circular rings (dual rings) with separate transmit and receive functionality which is a particular case of multiple ring array configuration [22, 23]. The main advantages of dual ring array configuration are eliminating transmit-receive switching circuitry and separate optimization of transmit and receive element geometry or biasing schemes [40]. Moreover, dual ring configuration provides nearly identical resolution as compared to single ring array without losing active area.

The theoretical far field continuous wave two-way PSF of a dual ring array is given by:

$$P(r) = J_0(kar/z) \cdot J_0(kbr/z), \quad (1)$$

where $J_0(\cdot)$ is the zero-order Bessel function, $k=2\pi/\lambda$, λ is the wavelength, z is the range r is the radial distance, a and b are the radius of transmit and receive arrays (see Fig. 2). Similarly, the PSF of single ring array can be determined by defining the radii of transmit and receive arrays as equal. The circular ring arrays, as expected, produce higher side lobes when compared with the full disk aperture (with radius b) which has a PSF in the form of the first order Bessel function $J_1(kbr/z)$ [41, 42].

Optimizing an array should suppress side lobes while reducing the number of firings to produce high frame rate with reduced motion artifacts. Because of the complexity of the optimization process, analytical methods are not used in optimized array design. Synthesizing ring arrays is more cumbersome due to the circular geometry when compared with the 2-D rectangular arrays. Therefore, we use coarray concept to simplify the 2-D optimization problem by reducing it to the 1-D case. The objective of the optimization is to obtain an optimal firing set consisting of a predefined number of transmit-receive element combinations through elimination of redundant spatial frequencies in the coarray while producing low side lobe levels.

A. Coarray Concept

In array design the coarray concept can be used as a guiding tool for synthesizing appropriate transmit and receive array configurations. The coarray corresponds to the convolution of transmit and receive arrays and represents the two-way aperture function, equivalently the spatial frequency response. Each transmit-receive element pair contributes to a specific bin of the coarray, representing a specific lateral spatial frequency. The location of the bin corresponds to the sum of the position vectors of transmit and receive elements. The overall coarray kernel extends to the sum of the sizes of transmit and receive apertures. The goal in array design is to form a uniform coarray function, where amplitude of each coarray element must be controllable independently.

The coarray kernel for ring arrays fills a circular area with a boundary radius of $R_{max} = R_{tr} + R_{rc}$, where R_{tr} and R_{rc} represent the radius of transmit and receive ring arrays respectively. The full set of all transmit-receive combinations produces many redundant spatial frequencies (firings) since it has $N_{tr} \times N_{rc}$ elements. Since the number of firings must be minimized for real time imaging, the goal is to form a coarray function with minimal redundancy in spatial frequency content, while the beam pattern has reduced low side lobe level. In general, a suitable weighting function is used to suppress the side lobes in beam

patterns, but this approach results in degraded SNR. Therefore we propose two sampling schemes to obtain reduced firing sets and to suppress side lobes through adjusting the element densities of the coarray rings in radial and angular directions.

B. Uniform Coarray Sampling

The spatial frequency components near the center of the coarray kernel correspond to spatial DC and have no contribution in image quality [39, 43]. Therefore, a central hole in coarray kernel with a radius of R_{min} is excluded, and thus the resulting coarray is in the form of a donut shape. To form a uniformly sampled control kernel, the coarray space between R_{min} and R_{max} is sampled at equal radial and equal angular distances to obtain a desired number (N_d) of firings (coarray elements). Each sample is an equal area patch shown in Fig. 3. To obtain a uniform distribution, we choose the nearest neighbor elements to the control coarray elements from the full-set coarray elements. Other elements apart from this nearest element are discarded. Using this approach, we choose a subset of N_d elements from the full set to form a fully non-redundant coarray, the uniformly sampled control kernel, and determined the corresponding transmit-receive pairs.

C. Non-Uniform Coarray Sampling

To eliminate periodicity on coarray pattern which suppresses possible grating lobes, we use a non-uniform sampling scheme: We sample the coarray kernel to adjust the element density distributed in a decreasing manner from inner ring to outer ring by increasing inter-element distance of the rings radially to fit a given apodization function. This method suppresses both the grating lobes and the side lobes. The procedure to obtain the non-redundant coarray subset is the same as that for the uniformly sampled coarray [44].

D. Simulated Annealing

Uniform and non-uniform coarray sampling gives completely heuristic solutions to the array optimization problem. To obtain a coarray pattern with a desired PSF performance one should search all the N_d -element subsets of the full set coarray. This is a non-deterministic polynomial time (NP-complete) problem. Therefore algorithms producing near optimal solutions in reasonable time have received a lot of attention. In this study we use simulated annealing based array optimization which results in near optimal solutions.

The simulated annealing algorithm was first introduced by Kirkpatrick [45] and widely used in array optimization, circuit design and image processing. The algorithm is based on an energy (cost) function defined for the system, which reduces with improved performance of the system. During each iteration of the algorithm, a small random perturbation is induced in the state. If the new state causes the energy function to reduce, it is accepted. Otherwise the state is accepted with a probability dependent on the temperature of the system, in accordance with the Boltzmann distribution given as,

$$p(\Delta E) = e^{-\frac{\Delta E}{T}}, \quad (2)$$

where E is the energy and T is the temperature of the system. The temperature T is gradually lowered by a temperature function of the iteration number. As the system cools off, the probability for accepting a poor solution is reduced, and eventually the system converges on the final solution which, if the optimization parameters are chosen well, may be close to the optimal solution.

To implement the optimization algorithm, we first calculated the PSF, $H(\cdot)$, using the simplified Rayleigh-Sommerfeld diffraction expressed as

$$H(r, \theta, \phi) = \sum_n w_n \cdot \sum_k w_k \cdot s\left(\frac{2r}{c} - t_n - t_k - \tau_n - \tau_k\right), \quad (3)$$

where (r, θ, ϕ) are the spherical coordinates; n and k represents the transmit and receive indices respectively; w_i is the apodization weight; $s(\cdot)$ is the excitation pulse; c is the speed of sound; t_i is the flight time; τ_i is the focusing delay time [46]. In this study we consider uniform weighting (no apodization): $w_i=1$ for all i . For the sake of computational complexity, we ignore the element factor, obliquity factor and the attenuation effects. The PSF geometry showing the array and spherical coordinate system is shown in Fig. 2.

The initial step in the optimization is to calculate the PSF including all transmit-receive firing combinations for all the sampled azimuth and elevation angles. These data are recorded to be used further in the iterations to eliminate repeating PSF calculations for each perturbation state. To find an optimized subset with a desired number of elements from the full set coarray, one can define an energy function $f(v_i)$, where v_i is the coarray element position vector and i is the current iteration index. To minimize the side lobe level the energy function should be defined as,

$$f(v_i) = \max_{\theta \geq \theta_i} |H(r, \theta, \phi)|^2, \quad (4)$$

where θ_i is the angle of main lobe to side lobe transition. The objective of the optimization is to minimize the energy function for peak side lobe level. Another energy function can be defined to minimize the integrated side lobe energy and the expression is given as

$$f(v_i) = \int_{\theta_i - \frac{\pi}{2}}^{\frac{\pi}{2}} \int_{\frac{\pi}{2}}^{\frac{\pi}{2}} |H(r, \theta, \phi)|^2 d\phi d\theta, \quad (5)$$

Due to the symmetric array geometry, the PSF is also symmetric. Therefore considering the spherical coordinates, the range of angles $(0 \leq \theta \leq \pi/2, -\pi/2 \leq \phi \leq \pi/2)$ is sufficient to represent the PSF characteristic and reduce computational time.

The flow chart of the optimization procedure is shown in Fig. 4. In this procedure we first determine suitable temperature function and number of iteration and perturbation parameters. The initial temperature is chosen high enough so that the first perturbations are almost always accepted which results in sharp variations on the energy function. A randomly chosen element set from the full set determines the initial energy state value and after that the iterations start. In every iteration step, predetermined number of perturbations on the current subset vector is performed. In every perturbation, a randomly chosen single element replaces with a randomly chosen non-used element. If this new state decreases the energy function it is accepted, if not, then it is accepted with the defined probability function. The new state (element set) is updated if it is decided to be accepted. This procedure is repeated until all the predefined number iterations and perturbations are completed. At the end of the procedure, the variation on the energy function decreases to a predefined reasonable level which yields an optimal element set.

III. Simulation Results

To test the imaging performance of the optimized array configurations with dual and single ring arrays, we performed custom numerical simulations. For test arrays, we considered a 64-element single ring array and a dual ring array with 64 transmit and 58 receive elements.

The diameter of the single ring array is 1200 μm , whereas the diameters of transmit and receive arrays of the dual-ring array are 1200 μm and 1080 μm , respectively.

To analyze the coarray patterns we first obtained the full set coarray of the corresponding array configurations. The full set has 3712 and 4096 firing combinations for dual and single ring arrays, respectively. Due to different transmit and receive array radii and number of array elements, all the firing combinations have uniform amplitude, in other words there is no overlap on the coarray space. However, the same transmit-receive pairs results in an identical point on the coarray space and hence single ring array has some redundancy. When we eliminate this redundancy, we may consider 2049 firing elements that have uniform amplitude.

For dual ring array configuration we consider two test cases with 512 and 256 firings (desired coarray element counts) which correspond to a reduction of nearly 1/7 and 1/14 of the full set. These firing counts are suitable for real time IVUS imaging. To compare coarray distributions we obtained uniformly and non-uniformly sampled coarrays as well as the optimized coarray. For uniformly sampled coarray we determined 13 rings and 9 rings with inter-element distance of nearly 1.2λ and 1.7λ for 512 and 256 element designs, respectively. For non-uniformly sampled coarray we used Kaiser-Bessel apodization function to fit the radial inter-element distance. The Kaiser-Bessel function is expressed as,

$$\Delta r(m) = \frac{I_0(\alpha \sqrt{1 - (\frac{2m}{N} - 1)^2})}{I_0(\alpha)} \quad (6)$$

where Δr is the inter-element distance of rings, m is the ring index, I_0 is the zero-order modified Bessel function of the first kind, α is an arbitrary parameter and N is the total number of rings. To obtain a desired element number of 512, we determined a minimum and maximum inter-element distance of 0.8λ and 1.34λ respectively, whereas for 256-element case these numbers are 1.2λ and 2.0λ . The number of rings is identical with uniformly sampled case. For both uniformly and non-uniformly sampled cases the coarray subsets are determined by the nearest neighbor technique. In optimization we used the following parameters: 400 iterations, 4000 perturbations and the initial temperature of 3×10^4 . For the temperature function we used

$$T(i) = T_0 \beta^i, \quad (7)$$

where T_0 is the initial temperature, i is the iteration index and β is a parameter chosen as 0.97. We performed the simulations for the energy functions using both minimizing the peak side lobe and the integrated side lobe energy techniques. Although they produce similar results, the former yields better results. To obtain a circularly symmetric coarray and PSF distribution, when choosing elements we used a quarter of the coarray space and extended the solution to the other quarters symmetrically. This also results in symmetric transmit-receive firing pairs. Another advantage of this method is that the optimization is performed on a small search space which reduces computational time to reach an optimum solution. The coarrays produced by all transmit-receive element pairs (full-set), uniformly sampled, non-uniformly sampled and optimized cases are shown in Fig. 5–7 (top). In these figures, the coarray elements are represented by binary values: black (not used) and white (used element).

We considered two sets of wide-band PSF simulations using a 20-MHz Gaussian pulse with 50% and 80% fractional bandwidths. The speed of sound is $c=1540$ m/s and the sampling

frequency is 2 GHz. To display 2-D PSFs, we used constant- r surface ($\theta\phi$ -surface) and $r\theta$ -plane (in spherical coordinates as depicted in Fig. 2), which correspond to the C-scan and B-scan displays, respectively. Each image in these figures is normalized to its own maximum and log compressed to 40 dB dynamic range. Here the target is located on the array normal (on axis) at $f/4$, and hence these PSFs represent non-steered beam patterns. The C-scan and B-scan PSFs are shown in Fig. 5–7 (middle, bottom). For ease of comparison, we also obtained averaged 1-D lateral cross-sections of the PSFs shown in Fig. 5–7, where the averaging was performed by the 1-D cross-sections across the entire ϕ -range and the r -range, respectively.

When the 2-D PSF responses of dual ring array are examined, we observe that optimized coarray configuration has narrower 6-dB main lobe width when compared with uniformly and non-uniformly sampled cases. The non-uniformly sampled coarray, as expected, has a lower first side lobe level than the uniformly sampled coarray. On the other hand, the optimized coarray produces considerably better performance than the other two. Although the average side lobe levels of the uniform and non-uniform coarrays decrease below -40 dB level around 10° angle, a relative rise to the -35 dB in the far side lobe region is observed. For the optimized coarrays with 512 and 256 elements, there is a slightly flat side lobe level near -40 dB. Especially in the 512-element case the far side lobe level of the optimized coarray remains below -40 dB at almost every angle. We also simulated PSFs for FBW of 80% for both 512 and 256 element sets. The results for 512-element case are shown in Fig. 7. The optimized coarray produces the best results as it is seen in the results for FBW of 50% case. The main difference in FBW of 80% is on the non-uniform coarray case where there is a widening beneath the main lobe region and a rise on the far side level. This is consistent because as the FBW is increased, large inter-element distances on outer rings of the coarray result in a rise in side lobe levels. The measurements on simulation results in terms of beam width, peak first side lobe level and far side lobe levels are outlined in Table 1. We also reconstructed the steered PSFs for 512-element case (shown in Fig. 9), where the steering angle is θ is 30° ($\phi=0^\circ$). The steered PSFs showed that the optimized coarray has significant near side lobe reduction compared with full-set and similar performance with uniformly and non-uniformly sampled coarrays.

For the PSF simulations of single ring array, we used a Gaussian pulse with a center frequency of 10 MHz which is the value that Wang *et al.* used in their study [39]. The coarrays produced by all transmit-receive element pairs (full-set), non-uniformly sampled and optimized coarrays are shown in Fig. 8 (top). The coarray for Wang's approach is also given as a reference for the comparison of single ring array design. We also produced 2-D PSFs of the corresponding coarrays along with the 1-D averaged cross-sections (Fig. 8).

The simulation results showed that the optimized and non-uniformly sampled coarray have narrower 6-dB main lobe width. Wang's coarray and non-uniformly sampled coarray perform similar in terms of the first and far side lobe levels, while the optimized design has nearly 8-dB improvement for the first side lobe level.

IV. Summary and Conclusion

In this study, we presented different optimized array designs based on circular single and dual rings that are suitable for synthetic phased array processing with reduced number of firings. To obtain optimal firing set we used simulated annealing algorithm and together with the wide-band pulse-echo response of the array system. The simulation results demonstrated that the annealing algorithm can be used to reduce the number of firings and control side lobe performance for circular ring arrays. For dual ring array design, we explored the coarrays of two test cases with 512 and 256 firing elements. They both

produced near side lobe level below -30 dB and far side lobe level of nearly -40 dB without compromising the main lobe width. For 20-MHz operating frequency and 10 mm imaging depth, the test configuration with 256 firings form an image frame in 3.3ms which results in nearly 300 frames/sec when only a single active channel is available. The low susceptibility to tissue-transducer motion is as vital as the high frame rate in synthetic phased array processing. The 256-firings/frame corresponds to a maximum phase error of $T_0/10$ caused by tissue-transducer motion less than or equal to 1.14 mm/sec. The motion susceptibility can be scaled down by using a number of parallel active channels. For example an IVUS system with 4 active channels can tolerate tissue-transducer motion up to 4.56 mm/sec with a maximum $T_0/10$ phase error [47].

Although proposed optimal designs with synthetic phased array processing increase frame rate and reduce motion susceptibility, SNR should also be considered due to decrease in number of firings. The theoretical image SNR produced by synthetic phased array beam forming is proportional to the square root of number of firings ($\sqrt{N_f}$) [24, 30]. Therefore, for our two test cases with 512 and 256 firing elements, optimized coarray sets produce an expected image SNR of 47 dB and 44 dB, respectively, where an average SNR of 20 dB is assumed for a single pulse-echo scan. These indicate 8 dB and 11 dB SNR loss relative to the full set with 3712 elements. In general SNR performance above 40 dB is considered to be sufficient for IVUS applications.

In optimizing single ring arrays, Wang *et al.* had chosen the reduced set using predefined spatial offsets between transmit and receive elements' locations (i.e., indexes). This approach has also been used by Yeh *et al.* [16] for forward-looking intravascular/intracardiac imaging using a single-ring CMUT array. It seems that Wang's approach and ours generate reduced firing sets with different sampling of the coarray kernel: the former involves non-uniform sampling with density decreasing as the distance from the coarray center increases, whereas the latter produces nearly uniform sampling and non-uniformly distributed coarray elements density to fit an apodization function. These two coarray formation approaches for single-ring arrays can yield similar image quality, as long as the coarray size and the number of transmit-receive pairs are identical. Because of the limitation in finding a proper set of offsets between the elements of the concentric rings with different element counts, the coarray synthesis using predefined offsets is not suitable for the dual-ring or multiple-ring array configurations, where each ring has a different number of array elements and/or inter-element separation. Therefore we used simulated annealing algorithm to obtain optimal coarray sets in both dual ring and single array designs. The optimized sets for single ring array produce considerably better results than other coarray sampling approaches.

Acknowledgments

This work was supported by Award Number R01EB010070 from the National Institute of Biomedical Imaging and Bioengineering, and Award Number R01HL082811 from the National Heart, Lung and Blood Institute. The content is solely the responsibility of the authors and does not necessarily represent the official views of the National Institutes of Health.

References

1. Courtney BK, et al. Innovations in imaging for chronic total occlusions: a glimpse into the future of angiography's blind-spot. *Eur Heart J.* 2008; 29(5):583–93. [PubMed: 18238930]
2. Cuneo A, Tebbe U. The management of chronic total coronary occlusions. *Minerva Cardioangiol.* 2008; 56(5):527–41. [PubMed: 18813187]
3. van der Steen A, Baldewsing RA, Degertekin FL, Emelianov S, Frijlink M, Furukawa Y, Goertz D, Karaman M, Khuri-Yakub P, Kim K, Mastik F, Moriya T, Oralkan O, Saijo Y, Schaar J, Serruys

- PW, Sethuraman S, Tanaka A, Vos HJ, Witte R, O'Donnell M. IVUS beyond the horizon. *Euro Intervention*. 2006; 2:132–42. [PubMed: 19755250]
4. van den Steen, A.; Saijo, Y. *Vascular ultrasound*. Tokyo: Springer-Verlag; 2003.
5. Bom N, ten Hoff H, Lancee CT, Gussenhoven WJ, Bosch JG. Early and recent intraluminal ultrasound devices. *Int J Card Imag*. 1989; 4:79–88.
6. Yock PG, Linker DT. Intravascular ultrasound: Looking below the surface of vascular disease. *Circulation*. 1990; 81:1715–18. [PubMed: 2184950]
7. O'Donnell M, Thomas LJ. Efficient synthetic aperture imaging from a circular aperture with possible application to catheter-based imaging. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 1992; 39:366–80.
8. O'Donnell M, Shapo BM, Eberle MJ, Stephens DN. Experimental studies of an efficient catheter array imaging system. *Ultrason Imaging*. 1995; 17:83–94. [PubMed: 7571209]
9. O'Donnell M, Eberle MJ, Stephens DN, Litzza JL, San Vicente K, Shapo BM. Synthetic phased arrays for intraluminal imaging of coronary arteries. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 1997; 44:714–721.
10. Evans JL, Ng KH, et al. Arterial imaging with a new forward-viewing intravascular ultrasound catheter, I. Initial studies. *Circulation*. 1994; 89:712–717. [PubMed: 8313559]
11. Ng KH, Evans JL, et al. Arterial imaging with a new forward-viewing intravascular ultrasound catheter, II. Three-dimensional reconstruction and display of data. *Circulation*. 1994; 89:718–723. [PubMed: 8313560]
12. Liang DH, Hu BS. A forward-viewing intravascular ultrasound catheter for intracoronary use. *Biomed Instr Technol*. 1997; 31:45–53.
13. Rogers JH. Forward-Looking IVUS in Chronic Total Occlusions: A new approach to an old problem. *Cardiac Interventions Today*. Jun-Jul;2009
14. Courtney, B.; Munce, NR.; Thind, AS.; Yang, VXD.; Forster, FS. Scanning mechanisms for imaging probe. US Patent. 2008/0177138. Jul 24. 2008
15. Wang Y, Stephens DN, O'Donnell M. A forward viewing ring-annular ultrasound array for intravascular imaging. *Proc IEEE Ultrason Symp*. 2001:1573–76.
16. Yeh DT, et al. 3-D ultrasound imaging using a forward-looking CMUT ring array for intravascular/intracardiac applications. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 2006; 53(6):1202–11.
17. Ergun AS, et al. Capacitive micro machined ultrasonic transducers: fabrication technology. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 2005; 52(12):2242–58.
18. Knight J, McLean J, Degertekin FL. Low temperature fabrication of immersion capacitive micromachined ultrasonic transducers on silicon and dielectric substrates. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 2004; 51:1324–33.
19. Zahorian J, Guldiken R, Gurun G, Qureshi MS, Balantekin M, Hasler P, Degertekin FL. Single chip CMUT arrays with integrated CMOS electronics: Fabrication Process Development and Experimental Results. *Proc IEEE Ultrason Symp*. 2008:386–89.
20. Demirci U, et al. Forward-viewing CMUT arrays for medical imaging. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 2004; 51(7):887–95.
21. Degertekin FL, Guldiken RO, Karaman M. Annular-ring CMUT arrays for forward-looking IVUS: transducer characterization and imaging. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 2006; 53(2):474–82.
22. Guldiken RO, Zahorian J, Balantekin M, Degertekin FL, Tekes C, Sisman A, Karaman M. Dual-Annular-Ring CMUT Array for Forward Looking IVUS Imaging. *Proc IEEE Ultrason Symp*. 2006:698–701.
23. Guldiken RO, Zahorian J, Gurun G, Qureshi MS, Balantekin M, Tekes C, Hasler P, Karaman M, Carlier S, Degertekin FL. Forward-Looking IVUS Imaging Using a Dual-Annular Ring CMUT Array: Experimental Results. *Proc IEEE Ultrason Symp*. 2007:1247–50.
24. Karaman M, Li PC, O'Donnell M. Synthetic aperture imaging for small scale systems. *IEEE Trans Ultrason, Ferroelect, Freq Contr*. 1995; 42(3):429–442.

25. Smith SW, Pavy HG, von Ramm OT. High-speed ultrasound volumetric imaging system-Part I: Transducer design and beam steering. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 1991; 38:100–108.
26. Lockwood GR, Foster FS. Optimizing sparse two-dimensional arrays using an effective aperture approach. *Proc IEEE Ultrason Symp.* 1994:1497–1501.
27. Lockwood GR, Foster FS. Optimizing the radiation pattern of sparse periodic two-dimensional arrays. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 1996; 43(1):15–19.
28. Brunke SS, Lockwood GR. Broad-bandwidth radiation patterns of sparse two-dimensional vernier arrays. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 1997; 44(5):1101–1109.
29. Austeng A, Holm S, Weber PK, Aakvaag N, Iranpour K. 1d and 2d algorithmically optimized sparse arrays. *Proc IEEE Ultrason Symp.* 1997; 2:1683–1686.
30. Johnson JA, Karaman M, Khuri-Yakub BT. Coherent Array Imaging Using Phased Subarrays—Part I: Basic Principles. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 2005; 52(1):37–50.
31. Johnson JA, Oralkan O, Ergun AS, Demirci U, Karaman M, Khuri-Yakub BT. Coherent Array Imaging Using Phased Subarrays—Part II: simulation and experimental results. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 2005; 52(1):51–64.
32. Karaman M, Wygant IO, Oralkan O, Khuri-Yakub PT. Minimally redundant 2-D array designs for 3-D medical ultrasound imaging. *IEEE Trans Medical Imaging.* 2009; 28(7):1051–1061.
33. Holm S. Minimum sidelobe energy versus minimum peak sidelobe level for sparse array optimization. *PTOC IEEE Nordic Signal Processing Symp.* 1996:227–230.
34. Holm S, Elgetun B, Dahl G. Properties of the beam pattern of weight- and layout-optimized sparse array. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 1997; 44(5):983–991.
35. Holm S, Elgetun B, Dahl G. Weight- and layout-optimized sparse arrays. *Proc Int Workshop on Sampling Theory Appl.* 1997:97–102.
36. Trucco A, Repetto F. A Stochastic Approach to Optimizing the Aperture and the Number of Elements of an Aperiodic Array. *Oceans.* 1996; 96:1510–1515.
37. Trucco A. Thinning and weighting of large planar arrays by simulated annealing. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 1999; 46(2):347–355.
38. Caorsi S, Trucco A. Planar Antenna Array Design with a Multi-Purpose GA-Based Procedure. *Microwave and Optical Technology Letters.* 2002; 35(6)
39. Wang Y, Stephens DN, O'Donnell M. Optimizing the beam pattern of a forward-viewing ring-annular ultrasound array for intravascular imaging. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 2002; 49(12):1652–1664.
40. Zahorian, J.; Hochman, M.; Xu, T.; Gurun, G.; Degertekin, L. Bias optimization of dual ring CMUT arrays for forward looking IVUS applications. presented at the IEEE Ultrasonics Symposium; San Diego, CA. 2010.
41. Norton SJ. Synthetic aperture imaging with arrays of arbitrary shape—Part I: General case. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 2002; 49(9):399–403.
42. Norton SJ. Synthetic aperture imaging with arrays of arbitrary shape—Part II: The annular array. *IEEE Trans Ultrason, Ferroelect, Freq Contr.* 2002; 49(9):404–408.
43. Steinberg, BD. *Principles of Aperture and Array System Design.* New York: Wiley; 1976.
44. Tekes C, Karaman M, Degertekin FL. Co-array Optimization of CMUT Arrays for Forward-Looking IVUS. *Proc IEEE Ultrasonics Symposium.* 2009:1326–29.
45. Kirkpatrick S, Gelatt CD Jr, Vecchi MP. Optimization by simulated annealing. *Science.* 1983; 220(4598):671–680. [PubMed: 17813860]
46. Selfridge AR, Kino GS, Khuri-Yakub BT. A theory for the radiation pattern of a narrow-strip acoustic transducer. *Appl Phys Lett.* 1980; 37(1):35–37.
47. Hochman, M.; Zahorian, J.; Satir, S.; Gurun, G.; Xu, T.; Karaman, M.; Hasler, P.; Degertekin, FL. CMUT-on-CMOS for forward looking IVUS: Improved fabrication and real time imaging. presented at the IEEE Ultrasonics Symposium; San Diego, CA. 2010.

Fig. 1. Schematic of a FL-IVUS probe with a dual-ring array with integrated front-end electronics.

Fig. 2.
Reference geometry used for analytical expressions and simulated PSFs

Fig. 3. Schematic representation of coarray formation for dual-ring arrays. Choosing the non-redundant elements is demonstrated at the upper right portion of the coarray.

Fig. 4.
Flow-chart of the optimization procedure.

Fig. 5. Simulation results of the dual ring array with 512-element coarray and 50% fractional bandwidth. Each coarray display consists of binary values, i.e., 0 (black) and 1 (white), whereas each 2-D PSF is displayed with a 40-dB dynamic range. 1-D lateral cross-sections of the PSFs (bottom) averaged across the entire ϕ -range (left) and the r -range (right).

Fig. 6.

Simulation results of the dual ring array with 256-element coarray and 50% fractional bandwidth. Each coarray display consists of binary values, i.e., 0 (black) and 1 (white), whereas each 2-D PSF is displayed with a 40-dB dynamic range. 1-D lateral cross-sections of the PSFs (bottom) averaged across the entire ϕ -range (left) and the r -range (right).

Fig. 7. Simulation results of the dual ring array with 512-element coarray and 80% fractional bandwidth. Each coarray display consists of binary values, i.e., 0 (black) and 1 (white), whereas each 2-D PSF is displayed with a 40-dB dynamic range. 1-D lateral cross-sections of the PSFs (bottom) averaged across the entire ϕ -range (left) and the r -range (right).

Fig. 8. Simulation results of the single ring array with the 210-element coarray and 50%-fractional bandwidth. Each coarray display consists of binary values, i.e., 0 (black) and 1 (white), whereas each 2-D PSF is displayed with a 40dB dynamic range. 1-D lateral cross-sections of the PSFs (bottom) averaged across the entire ϕ -range (left) and the r -range (right).

Fig. 9.

Steered 2-D PSFs of the dual ring array with 512-element coarray and 50% fractional bandwidth. Steering angle is ($\theta=30^\circ$, $\phi=0^\circ$)

Table I

Summary Of Simulation Results For Dual Ring Array

Dual Ring 512-Element (BW 50%)			
	-6dB Beamwidth (°)	First Side Lobe Level (dB)	Far Side Lobe Level (dB)
Full set	2.84	-20	<-40
Uniformly sampled	2.66	-23	<-38
Non-uniformly sampled	2.78	-31	<-38
Optimized	2.58	-34	<-42
Dual Ring 256-Element (BW 50%)			
	-6dB Beamwidth (°)	First Side Lobe Level (dB)	Far Side Lobe Level (dB)
Full set	2.82	-20	<-41
Uniformly sampled	2.66	-22	<-35
Non-uniformly sampled	2.58	-25	<-34
Optimized	2.59	-32	<-39
Dual Ring 512-Element (BW 80%)			
	-6dB Beamwidth (°)	First Side Lobe Level (dB)	Far Side Lobe Level (dB)
Full set	2.84	-20	<-47
Uniformly Sampled	2.58	-45	<-42
Non-uniformly Sampled	2.78	-30	<-40
Optimized	2.52	-43	<-47