Published in final edited form as:

J Instrum. 2013 January 1; 8(1): T01006–. doi:10.1088/1748-0221/8/01/T01006.

High-performance electronics for time-of-flight PET systems

W.-S. Choong¹, Q. Peng, C.Q. Vu, B.T. Turko, and W.W. Moses

Lawrence Berkeley National Laboratory, Berkeley, CA 94720, U.S.A.

Abstract

We have designed and built a high-performance readout electronics system for time-of-flight positron emission tomography (TOF PET) cameras. The electronics architecture is based on the electronics for a commercial whole-body PET camera (Siemens/CPS Cardinal electronics), modified to improve the timing performance. The fundamental contributions in the electronics that can limit the timing resolution include the constant fraction discriminator (CFD), which converts the analog electrical signal from the photo-detector to a digital signal whose leading edge is time-correlated with the input signal, and the time-to-digital converter (TDC), which provides a time stamp for the CFD output. Coincident events are identified by digitally comparing the values of the time stamps. In the Cardinal electronics, the front-end processing electronics are performed by an Analog subsection board, which has two application-specific integrated circuits (ASICs), each servicing a PET block detector module. The ASIC has a built-in CFD and TDC. We found that a significant degradation in the timing resolution comes from the ASIC's CFD and TDC. Therefore, we have designed and built an improved Analog subsection board that replaces the ASIC's CFD and TDC with a high-performance CFD (made with discrete components) and TDC (using the CERN high-performance TDC ASIC). The improved Analog subsection board is used in a custom single-ring LSO-based TOF PET camera. The electronics system achieves a timing resolution of 60 ps FWHM. Prototype TOF detector modules are read out with the electronics system and give coincidence timing resolutions of 259 ps FWHM and 156 ps FWHM for detector modules coupled to LSO and LaBr₃ crystals respectively.

Keywords

Analogue electronic circuits; Gamma camera; SPECT; PET PET/CT; coronary CT angiography (CTA); Front-end electronics for detector readout

1 Introduction

We have developed a time-of-flight positron emission tomography (TOF PET) detector module based on Ca co-doped LSO crystals. It consists of two LSO scintillator crystals, each $6.15 \times 6.15 \times 25 \text{ mm}^3$, that are coupled to a single Hamamatsu R-9800 PMT on one of their $6.15 \times 25 \text{ mm}^2$ faces [1]. This side-on coupling of the crystals minimizes the propagation and reflection of the scintillation light prior to detection by the PMT, which improves the timing resolution of the detector module. In addition, the R-9800 PMT uses a super-bialkali photocathode resulting in improved timing resolution due to higher photon detection efficiency. The five sides of each crystal that are not coupled to the PMT are covered with a white reflector, so there is no light sharing between the two crystals. However, the reflector on the face that is opposite the PMT has a hole in it (a 6 mm diameter

semicircle) that is used to decode the crystal of interaction. Figure 1 shows a photograph of the detector module.

A continuous, closely packed single-ring camera is constructed by assembling the detector modules as illustrated in figure 2. The camera ring is 82.5 cm in diameter and uses 192 detector modules, which correspond to 294 individual crystals. The face of the scintillator with the hole in the reflector comes in contact with the PMT photocathode from an opposing detector module, but it is separated by a small (<1 mm) air gap. When a 511 keV gamma ray interacts with one of the scintillator crystals (say Crystal 2A in figure 2), it produces a large signal in the PMT on which the crystal is glued to (PMT 2 in figure 2). In addition, some of the light from this interaction is also detected by the air-coupled PMT (PMT 1 in figure 2), so a smaller signal (because of the smaller opening and the relatively poor optical coupling) is also produced by that PMT. This limited light sharing is used to decode which scintillator crystal the gamma ray interacts. Thus, an interaction in Crystal 2A yields a large signal in PMT 2 and a small signal in PMT 1. Similarly, an interaction in Crystal 2B yields a large signal in PMT 2 and a small signal in PMT 3. Both the timing and the energy are derived solely from the PMT on which the crystal is glued and information from the air-coupled PMT is only used for decoding.

While the timing resolution of the detector will ultimately limit the achievable timing resolution, the readout electronics can contribute significantly to the timing resolution if not optimally designed for timing performance. Therefore, we have constructed a TOF electronics system for TOF PET cameras based on the Siemens/CPS Cardinal electronics. In order to meet the timing requirement of this TOF PET camera, we re-designed the front-end readout board, also known as the Analog subsection (AS) board, to optimize for timing.

2 System architecture

Figure 3 shows the system architecture of the Siemens/CPS Cardinal electronics. The analog signals from the detector modules are processed by the AS board, which has two custom application-specific integrated circuits (ASICs) [2], each servicing a PET block detector module. Therefore, each AS board can process up to eight analog signals. The ASIC contains four differential input variable gain amplifiers and their outputs are digitized by external analog-to-digital converters (ADCs). In addition, all four amplified analog signals are summed together and the output is sent to an on-chip timing chain, which consists of a constant fraction discriminator (CFD) and a time-to-digital converter (TDC). The CFD converts the summed analog signal from the PET block detector to a digital signal whose leading edge is time-correlated with the input signal and is converted by the TDC to generate a time stamp for the event. The time stamp is used to form a singles event word that also includes the total energy and the crystal of interaction. The singles event word is sent to a Control Interface (CI) board, which hosts up to eight AS boards and prioritizes their digital event output before sending it out through high-speed serial lines to a Coincidence Controller (CC) board, where coincident events are identified and sent to the host PC using an optical link. The CC board can accept up to twelve CI boards. The CC board also generates the system clock running at 80 MHz and distributes it to the CI boards and subsequently to the AS boards. We found that the CFD section of the ASIC can contribute over 1 ns to the timing resolution [3]. In addition, the TDC has 300 ps LSB, which essentially defines the timing resolution contribution of this component.

3 TOF Analog subsection board

Since the timing performance of the Siemens/CPS Cardinal electronics is limited by the ASIC, we re-designed the AS board, which we designate as the TOF AS board, to bypass the on-chip CFD and TDC of the ASIC, and replaced them with a high-performance CFD

and a high-performance TDC (HPTDC) developed at CERN [4]. Figures 4 and 5 show a schematic block diagram and a photograph of the TOF AS board respectively. The board accepts up to eight analog inputs and has two identical sections, each processing four analog signals. The ASIC is still used to amplify and shape each analog signal to obtain the energy deposit of the detector module. However, the four analog signals are split to a separate timing chain where the signals are summed using an ultra-wideband operational amplifier (Texas Instrument OPA695) and are processed by the high-performance CFD and the HPTDC.

Figure 6 shows the schematic diagram of the CFD circuit. The high-performance CFD is implemented using an ultra-wideband operational amplifier (Texas Instruments OPA695) and ultra-high-speed comparator (Maxim MAX9600). The delay in the CFD is set using a high-speed delay line chip (Maxim MAX3620) with an optimum delay of 1.5 ns for our TOF detector module. The CFD constant fraction is set at 20% of the pulse amplitude.

The HPTDC has 32 input channels but can only service up to eight channels when operating at the “Very High Resolution” mode where multiple sampling using four TDC channels is used to improve the timing resolution. Figure 7 shows the measured integral non-linearity (INL) of the HPTDC, which has a repetitive fixed pattern with a 25 ns period (40 MHz input clock) caused by the cross talk from the logic part of the chip through the power supply coupling. The INL degrades the timing resolution of the TDC if not corrected. Thus, the INL is mapped out and corrected using a lookup table implemented inside the FPGA. We operate the HPTDC at the “Very High Resolution” mode with a time bin size of 24.4 ps and a timing resolution of 40 ps FWHM [4] after correcting for the INL.

4 Performance measurement

4.1 Timing resolution of TOF electronics

The timing resolution of the our TOF electronics is measured by splitting a square test pulse generated from a function generator to two separate AS boards mounted on two separate CI board. Singles event words are formed with the timestamp information from the HPTDC. Coincident events are formed in the CC board with a coincident window of 100 ns and are then sent to the host PC. The time difference between the two AS boards is calculated to determine the coincidence timing resolution of the AS board. Figure 8 shows the time difference spectrum measuring a coincidence timing resolution of 85 ps FWHM. Dividing by the square root of two, the electronics system achieves a timing resolution of 60 ps FWHM.

4.2 Timing resolution of TOF PET detector modules

A pair of prototype TOF PET detector modules described in section 1 were excited with two back-to-back 511 keV gamma rays from a positron source (Ge-68). In contrast to our production detector module, which has two crystals and a small hole on the face of each crystal that is opposite to the PMT, the prototype detector module only has one crystal coupled to the PMT and the small hole is also covered with reflector material. In addition, we also assembled another pair of prototype detector modules with LaBr₃ crystals of the same geometry and coupling as the LSO crystals. The coincidence timing resolutions were measured the same way as described in section 4.1 except the test pulses were replaced with the PMT analog signals from the detector modules. The pulse heights of the signals were also measured from the ADCs (sampling at 40 MHz) to determine the photopeak positions and energy resolutions. Only photopeak events defined to be two FWHM wide centered on the photopeak are considered in the timing measurements. The pulse height and time difference spectra obtained with our TOF electronics of the detector modules with LSO and LaBr₃ crystals are respectively shown in figures 9 and 10. The LSO detector modules give

an energy resolution of 15.7% FWHM and a coincidence timing resolution of 259 ps FWHM. On the other hand, the LaBr₃ detector modules give an energy resolution of 7.0% FWHM and a coincidence timing resolution of 156 ps FWHM.

As a comparison, we also performed the measurement with high-performance NIM electronics. The PMT signals were read out with Canberra 454 CFD modules, and their outputs were sent to an Ortec 556 TAC module. The amplitudes of the TAC analog signals were digitized using ADCs from the National Instrument NI-7833R and were read out by a host PC. The PMT signals were also amplified by customized shaper amplifiers, and their amplitudes were digitized with ADCs from the NI-7833R. The pulse height and time difference spectra obtained with NIM electronics of the detector modules with LSO and LaBr₃ crystals are respectively shown in figures 11 and 12. The LSO detector modules give an energy resolution of 15.1% FWHM and a coincidence timing resolution of 247 ps FWHM. On the other hand, the LaBr₃ detector modules give an energy resolution of 4.6% FWHM and a coincidence timing resolution of 146 ps FWHM.

5 Discussion and conclusions

We have constructed a high-performance electronics system for TOF PET cameras. The timing resolution of the electronics system was measured at 60 ps FWHM. In developing the electronics, we previously measured an electronics timing resolution of about 35 ps FWHM by splitting a test pulse into two separate channels on the same TOF AS board, but using an external clock generator that was directly sent to the board. In the final system, the clock is generated by the CC board and is distributed to all the CI boards where the AS board are mounted. The degradation in the electronics timing resolution for the system may be due to the time jitter in the clock distribution from the CC board.

Exciting a pair of prototype TOF detector modules, we obtained coincidence timing resolutions of 259 ps FWHM and 156 ps FWHM for detector modules coupled to LSO and LaBr₃ crystals respectively. As expected, the LaBr₃ detector modules achieved significantly better timing resolution than the LSO detector modules because LaBr₃ has higher light yield and shorter decay time than LSO [5]. The detector coincidence timing resolution measured by the electronics system is only slightly worse than or comparable with measurements made by the high-performance NIM electronics, which implies that the timing resolution is limited by the detector module and not by the electronics.

The electronic noise of the system is reasonably good as indicated by the measured detector energy resolutions, which are slightly worse than those of the NIM electronics. The LaBr₃ detector modules exhibit a larger degradation in the energy resolution measured by the electronics system compared to the NIM electronics. This may be because the shaper amplifier in the analog ASIC is optimized for the decay time of LSO scintillation light, which is longer than the decay time of LaBr₃ scintillation light. The electronics system will provide good discrimination between photopeak and scatter events, and good position decoding using the Anger logic for block detectors.

Acknowledgments

The authors would like to thank Mike Casey and John Young of Siemens Medical Solutions, Knoxville, TN, for their support with the Siemens/CPS Cardinal electronics. This work was supported in part by the Director, Office of Science, Office of Biological and Environmental Research, Biological Systems Science Division of the U.S. Department of Energy under contract no. DE-AC02-05CH11231, and in part by the National Institutes of Health, National Institute of Biomedical Imaging and Bioengineering, under Grant Number R01EB006085.

References

1. Moses WW, et al. Optimization of a LSO-based detector module for time-of-flight PET. *IEEE Trans. Nucl. Sci.* 2010; 57:1570. [PubMed: 21738262]
2. Swan BK, et al. A custom mixed-signal CMOS integrated circuit for high performance PET Tomograph front-end applications. *IEEE Trans. Nucl. Sci.* 2003; 50:909.
3. Moses WW, Ullisch M. Factors influencing timing resolution in a commercial LSO PET camera. *IEEE Trans. Nucl. Sci.* 2006; 53:78.
4. Mota M, et al. A flexible multi-channel high-resolution time-to-digital converter ASIC, 2000. *IEEE Nucl. Sci. Symp. Conf. Rec.* 2000; 2:9.
5. van Loef EVD, et al. High-energy-resolution scintillator: Ce³⁺ activated LaBr₃. *Appl. Phys. Lett.* 2001; 79:1573.

Figure 1.
Photograph of the TOF PET detector module.

Figure 2.
Exploded view of the detector ring.

Figure 3.
System architecture of the Siemens/CPS Cardinal electronics.

Figure 4.
Schematic block diagram of the TOF AS board.

Figure 5.
Photograph of the TOF AS board.

Figure 6.
Schematic diagram of the CFD circuit in the TOF AS board.

Figure 7.
Integral non-linearity of one channel of the HPTDC.

Figure 8.
Time difference spectrum obtained with the same test pulses split into two TOF AS boards mounted in two separate CI boards.

Figure 9. Pulse height (top) and time difference (bottom) spectra of detector modules coupled to LSO crystals measured with the TOF electronics system.

Figure 10. Pulse height (top) and time difference (bottom) spectra of detector modules coupled to LaBr3 crystals measured with the TOF electronics system.

Figure 11. Pulse height (top) and time difference (bottom) spectra of detector modules coupled to LSO crystals measured with NIM electronics.

Figure 12. Pulse height (top) and time difference (bottom) spectra of detector modules coupled to LaBr3 crystals measured with NIM electronics.