Published in final edited form as:

IEEE Trans Neural Netw Learn Syst. 2017 September ; 28(9): 2196–2208. doi:10.1109/TNNLS.

2016.2581141

Methodology of Recurrent Laguerre-Volterra Network for Modeling Nonlinear Dynamic Systems

Kunling Geng [Student Member, IEEE] and

Department of Biomedical Engineering and the Biomedical Simulations Resource Center at the University of Southern California, Los Angeles, CA, 90089, USA

Vasilis Z. Marmarelis [Fellow, IEEE]

Department of Biomedical Engineering and the Biomedical Simulations Resource Center at the University of Southern California, Los Angeles, CA, 90089, USA

Abstract

In this paper, we have introduced a general modeling approach for dynamic nonlinear systems that utilizes a variant of the Simulated Annealing (SA) algorithm for training the Laguerre-Volterra Network (LVN) to overcome the local-minima and convergence problems, and employs a pruning technique to achieve sparse LVN representations with ℓ_1 regularization. We tested this new approach with computer simulated systems and extended it to Autoregressive Sparse LVN (ASLVN) model structures that are suitable for input-output modeling of nonlinear systems that exhibit transitions in dynamic states, such as the Hodgkin-Huxley (H-H) equations of neuronal firing. Application of the proposed ASLVN to the H-H equations yields a more parsimonious input-output model with improved predictive capability that is amenable to more insightful physiological/biological interpretation.

Index Terms

Laguerre-Volterra Network; Volterra modeling; Principal Dynamic Modes; Hodgkin-Huxley (H-H) equations; Simulated Annealing; Nonlinear System Modeling; Recurrent Networks

I. Introduction

The data-based nonparametric methods using the Volterra-Wiener formulation of nonlinear input-output models have been used over the last 40 years to study the dynamics of neural systems [5][6][21][35][36]. One key challenge for these methods has been the parsimonious model representation that allows computational efficiency, estimation accuracy and physiological interpretation of the obtained models. A significant advance in this regard has been the practicable use of Laguerre expansions of the Volterra kernels [14]. Subsequent methodologies such as Principal Dynamic Modes [23] and Laguerre-Volterra Networks [24] are developed to achieve model parsimony, estimation efficiency and model interpretation, as demonstrated in various physiological systems [15] and, more recently, in the study of cerebral hemodynamics and neuronal dynamics [6][18–22].

In the Laguerre expansion technique (LET), we use the orthonormal basis of discrete Laguerre functions (DLFs) to compactly represent the Volterra kernels and achieve

estimation efficiency. Although LET reduces significantly the number of unknown parameters in the model, it does not remove the “curse of dimensionality” that comes from the incorporation of higher order kernels and multiple inputs. To overcome this limitation, the concept of Principal Dynamic Mode (PDMs) was introduced aiming to find the minimum set of basis functions for adequate representation of the kernels of a given system [23]. Least-Squares Estimation (LSE) methods have been used to obtain estimates of the expansion coefficients of the kernels in LET. Singular Value Decomposition (SVD) of first-order and second-order kernels has been used to obtain the PDMs by selecting the singular vectors that correspond to the significant singular values (usually $>10\%$ of maximum singular value). The PDMs obtained from this method are orthonormal, forming a functional coordinate basis for the system kernels. Using the obtained PDMs to represent/ expand the kernels, the Associated Nonlinear Functions (ANFs) are subsequently estimated via regression to obtain the Volterra-equivalent PDM-based model of the system [15]. This approach has been successfully used in various applications [6][14–17][51–53].

The Laguerre-Volterra network [24] combines the idea of Laguerre kernel expansions with the connectionist modeling notion of Artificial Neural Network (ANN). It employs cost-minimization training algorithms to obtain estimates of non-orthogonal PDMs of a given system in the context of arbitrary orders of nonlinearity (generally distinct from the original set of PDMs that are orthogonal and extracted from second-order models). The fact that the PDMs obtained from LVN are not necessarily orthogonal is viewed as providing more flexible representations of real physiological systems. Another advantage of LVN is the capability to train the critical Laguerre parameter α , which the original PDM method determines through a search procedure.

Although the LVN approach has found some useful applications [2] [25] [26], its efficacy has been hindered by the limitations of the employed Back-Propagation (BP) training algorithm which, as a gradient-descent based algorithm, suffers from local-minima trapping and convergence problems [9]. Local-minima trapping depends critically on the initialization points that are arbitrarily or randomly selected. The convergence problems relate to the learning rates for each LVN parameter. Several enhancements of BP have been introduced, such as the momentum method [31] and the delta-delta or delta-bar-delta rules [12], that mitigate these problems to some extent for many ANN. However, they have not been always effective in the case of LVN – perhaps due to the non-monotonic activation functions of the LVN (in contrast to the monotonic activation functions of ANN). We have found that these problems can be largely overcome by use of the Simulated Annealing (SA) algorithm [4][9] [13], which is adopted in this study as a stochastic global optimization method for training LVN.

Another challenge of the LVN method is the selection of the proper structural model parameters – viz. the number of DLFs L , the number of hidden units H , and the degree of polynomial nonlinearity Q . Different structures of LVN may have similar predictive power, but the corresponding PDMs in each structure (defined by the parameters of the hidden units) may be significantly different, which would complicate the interpretation of the obtained model. One common method for determining the model order is to search through all possible combinations of the structural parameters (Q, L, H) and use the Bayesian

information criterion (BIC) [32] to select the model order with the lowest BIC value. This approach requires an evaluation of $Q_m L_m (L_m + 1)/2$ models, where Q_m and L_m are the maximum values of Q and L , which results in heavy computational burden, since SA training requires considerable computational effort. We propose a more efficient approach to determine the model order by introducing the concept of Sparse LVN, which will force many elements of an initially high-order LVN to zero and achieve a compact model by successive pruning of the LVN until convergence.

To illustrate the efficacy of the SA training algorithm and the model pruning approach, we present first results from simulated data and, subsequently, propose a novel Autoregressive Sparse Laguerre-Volterra Network (ASLVN) to model the extensively studied Hodgkin-Huxley (H-H) equations of neuronal firing [11]. H-H equations are crucial for understanding the underlying dynamic processes for the generation of an action potential (AP) in computational neuroscience. However, the kinetics-based H-H model does not capture the variabilities within biological systems [39][40]. The recent development of a stochastic H-H model is trying to capture some of these variabilities by introducing noise terms in the deterministic H-H equations [41–46]. On the other hand, the data-based non-parametric methods, such as nonlinear autoregressive Volterra (NARV) modeling [5], conventional PDM analysis [6], and recurrent ANN [47] have been utilized to approximate the AP generation process. These non-parametric methods, however, cannot provide biological insights through interpretation of the obtained models. The proposed ASLVN method in this paper yields a parsimonious input-output representation of the H-H equations with improved predictive capability and more insightful interpretations. Some of the preliminary results were previously presented in [38].

The paper is organized as follows: Section II describes the SA training algorithm for LVN. Section III introduces the concept of sparse LVN and model order pruning technique for LVN. In Section IV, we use simulated data to evaluate the performance of the SA training algorithm and the model-order pruning technique. In Section V, we apply ASLVN for modeling the H-H equations and obtain some insightful interpretations. Finally, conclusions are drawn in Section VI. The Appendix gives the mathematical underpinnings of LVN and the details of the traditional BP training method.

II. LVN training with Simulated Annealing

The structure of the LVN is shown in Fig. 1. Its fundamental properties and BP training method are summarized in Appendix. As mentioned in Section I, the BP algorithm is hindered by local-minima limitations and convergence problems. For this reason, we propose using the Simulated Annealing (SA) approach for training the LVN. For each step in SA, a random move to a neighboring state is performed and, if the cost function decreases, then the new state is accepted. Otherwise, the move will be accepted with the probability that is determined by the Metropolis sampling algorithm (see below). Here is the basic description of how SA works to find the best parameter set $\mathbf{p}$ of LVN which minimizes the cost function J :

1. Initialize the parameter set $\mathbf{p}$ randomly and set the temperature T to a sufficiently large value T_0 .
2. Perform a small random move $\mathbf{p}$ based on the current parameter set, so that the new one is $\mathbf{p}' = \mathbf{p} + \Delta\mathbf{p}$.
3. Propagate the input through the LVN using current and new parameters sets, and compute the cost functions $J(\mathbf{p})$ and $J(\mathbf{p}')$ respectively to get the difference: $\Delta J = J(\mathbf{p}) - J(\mathbf{p}')$.
4. Calculate the acceptance probability:

$$r = \begin{cases} 1 & \text{if } \Delta J < 0 \\ e^{-\Delta J/T} & \text{otherwise} \end{cases} \quad (1)$$

i.e., if $\Delta J < 0$, we accept the new parameter set $\mathbf{p}'$; otherwise, $\mathbf{p}'$ is accepted with the probability defined above.

5. Repeat step 2 to 4 until it reaches an equilibrium, which may close to a local minimum. In practice, we often choose a large but fixed number of iterations.
6. Decrease the temperature T according to the cooling schedule and repeat step 2 to 5 again, until T reaches the frozen point (i.e. a small positive value).

Initially, the temperature T should be sufficiently high and $e^{-\Delta J/T} \approx 1$; so the new state will almost always be accepted. Thus, at the beginning, SA allows random steps that explore the parameter space without fear of getting trapped in a local minimum. In order to ease the selection of the initial temperature, we use as cost function the normalized mean-square error (NMSE) rather than the sum of squared errors (SSE), since SSE varies a lot for different data lengths. As the temperature decreases, the term $e^{-\Delta J/T}$ will be dominated more and more by ΔJ , and SA will take new states more cautiously. When T reaches the frozen point, it allows only steps decreasing J that eventually lead to the global minimum.

The effectiveness and speed of the SA method are largely dependent on the cooling schedule [7]. A practical method is the exponential decay cooling schedule [29]:

$$T(i) = \eta T(i-1), \quad i=1, 2, 3, \dots \quad (2)$$

where η is the cooling constant between 0.9 and 0.99. This schedule achieves only quasi-optimal results, but it reduces significantly the time required by the SA algorithm.

To apply the SA algorithm to LVN, another practical issue is how to perform a small random move in step 2 to get a new configuration of the parameter set. To achieve this, a single parameter p is randomly chosen from the whole set following a uniform distribution, so that each time every parameter would have the same probability to be selected. Then, p is updated by the rule shown below:

$$p^{new} = \begin{cases} p + \gamma_p & \text{if } rn > 0.5 \\ p - \gamma_p & \text{if } rn \leq 0.5 \end{cases} \quad (3)$$

where the constant γ_p is the step size, and rn is a random number drawn from a uniform distribution with range $[0, 1]$. In this way, this parameter p has an equal chance to increase or decrease by a small amount the value of γ_p .

When the DLF critical parameter α is updated, the outputs of the DLF filter-bank, $v_j(n)$, need to be re-computed (see Eq. (A3) and (A4) in Appendix I). Since each time α is updated by decreasing or increasing by a step size γ_α , and α is within the range $(0, 1)$, there are only $1/\gamma_\alpha - 1$ possible values. Therefore, we can calculate all the possible $v_j(n)$ for each α and store them into a look-up table in order to reduce the overall computational burden.

III. Sparse LVN and Model-Order Pruning Algorithm

Define the cost function of LVN as:

$$J = \text{NMSE} + \lambda(\|w\|_0 + \|c\|_0) \quad (4)$$

where $\|\cdot\|_0$ is the ℓ_0 norm, which is the number of non-zero elements. By adding the ℓ_0 regularization term, the optimization results would prefer zeros elements, which would reduce the cost function. Therefore, the trained w and c would contain many zeros and thus the LVN structure should be sparse. This property allows pruning of LVN by removing the unnecessary elements and determining the appropriate model structure. The nonlinear order Q corresponds to the highest degree term in the Polynomial Activation Functions (PAFs) that are associated with each PDM in each hidden node.

We can use SA to optimize the cost function in Eq. (4), but the results are often unsatisfactory because the ℓ_0 norm makes the cost function highly non-smooth and very hard to optimize. To relieve this problem, we are using ℓ_1 regularization, which is obtained by relaxing the hard constraints of ℓ_0 regularization [10][28], and then the cost function becomes:

$$J = \text{NMSE} + \lambda(\|w\|_1 + \|c\|_1) \quad (5)$$

where $\|\cdot\|_1$ is the summation of the absolute values of the parameter. With the ℓ_1 regularization term, the cost function is much easier to optimize by SA and the trained results also have the sparse properties. It should be mentioned that traditionally in ANN BP training methods, the ℓ_2 term, $\|w\|_2 = \sqrt{\sum w^2}$, is added to the cost function in order to prevent over-fitting, which is known as weight decay method [27]. However, the ℓ_2 norm usually cannot generate sparse results in LVN. The ℓ_1 regularization has been recently used in Volterra-based models for neural functional connectivities [33] [34].

Here is a description of the model order pruning algorithm utilizing the sparse LVN:

1. Start with a full model order (e.g. $(Q, L, H) = (3, 9, 9)$ in practice) or a user-specified high model order.
2. Optimize the cost function defined in Eq. (5) with SA algorithm under the current model order.
3. Prune unnecessary elements as many as possible by proposing a new model order.
4. Repeat step 2 and 3 until convergence.

More elaboration is needed in step 3. First, we have to prune H because unnecessary hidden nodes would be inactivated by sparse LVN and the output of these hidden nodes would be around zero. One method to determine the significance of hidden node is to calculate

$RMS_h = \sqrt{\sum_n z_h^2(n) / \sum_{h=1}^H \sum_n z_h^2(n)}$, where RMS_h is the normalized root mean square (RMS) of the hidden node output $z_h(n)$. In practice, when $RMS_h < 0.1$, the corresponding hidden node can be pruned. Then we can inspect the weights of the PDMs and reduce L as much as possible by removing weights which are below a chosen threshold (in this study, < 0.05). The degree Q of the PAFs can be decreased if it can achieve an adequate low-degree approximation of the system nonlinearity within the operating range of the PAF. An illustrative example using the model order pruning algorithm is shown in Section IV.

IV. Method Evaluation Using Simulated Data

The performance of the training algorithm and the model-order pruning technique is evaluated in this section through computer simulations where “ground truth” is available. The simulated system has the two PDMs shown in Fig. 2 and described by the following equations:

$$p_1(m) = e^{-m/20} \sin(\pi m/12) \quad (6)$$

$$p_2(m) = e^{-(m-20)^2/180} \quad (7)$$

In this second-order simulated example, the PAFs associated with each PDM are given by the following polynomials (i.e. quadratic and linear:

$$z_1(n) = 0.5u_1(n) + u_1(n)^2 \quad (8)$$

$$z_2(n) = u_2(n) \quad (9)$$

The PDMs are normalized as $\sum_{m=1}^M p_i^2(m)=1$, $i=1, 2$, and the coefficients of the associated PAFs are adjusted so that the overall model prediction remains the same. The input of the simulated system is Gaussian White Noise (GWN) with unit variance, and the data length is $N=1000$ samples. In order to test the robustness of the algorithm, an independent GWN is added to the output as noise for a Signal-to-Noise Ratio (SNR) of 5 dB. Using the simulated input-output data, we train the LVN with the SA algorithm and apply the model-order pruning algorithm to determine the structural parameters (Q, L, H) . We also compare the results with the traditional BIC model order selection method.

First, we use SA to train the LVN without regularization ($\lambda=0$ in the cost function J) for all possible model orders. The SA-related parameters are given in Table I. Then we use the BIC criterion to select the model order with the lowest BIC value, which is defined as:

$$\text{BIC} = -2\ln\hat{L} + P\ln N \quad (10)$$

where $\hat{L}$ is the maximum likelihood function estimate based on a sample size N , and $P=(L+Q)H$. Since the noise is additive GWN, the BIC can be written as:

$$\text{BIC} = N\ln SSE + P\ln N \quad (11)$$

where SSE is the sum of the squared errors. The BIC values for all 135 models evaluated in this step are summarized in Fig. 3. As we can see, the number of parameters are less for a linear model than nonlinear models but the prediction error is greater and the BIC values are significantly higher. For nonlinear models with $Q=2$ and $Q=3$, the BIC values are similar for different L, H and the best BIC values are the same. Since we favor model parsimony, the selected model order by BIC is $(Q, L, H) = (2, 7, 2)$. This is an appropriate model order because the simulated system has two PDMs and the highest degree of nonlinearity is 2. Evidently, 7 DLFs are able to represent the PDM waveforms defined in Eq. (6) and (7). For this model order, the training results of LVN are summarized in Fig. 4, where $NMSE=0.216$, $\alpha=0.590$, $y_0=-0.0665$. The obtained PDMs and the associated PAFs are very close to their exact counterparts of the simulated system, indicating the efficacy of the SA training algorithm.

Then, we use the pruning technique of Sparse LVN to determine the model order for the cost function defined in Eq. (5), and the SA parameters given in Table I. Here we set $\lambda=0.01$ and detailed description of the effects of λ will be discussed later. In the first step, we start with the full model order $(Q, L, H) = (3, 9, 9)$, and the training results are shown in Fig. 5(A) for the two significant PDMs, since all other PAF coefficients are almost zero indicating that the corresponding hidden nodes do not contribute to the LVN output. Therefore, we can reduce the number of hidden nodes from 9 to 2. Another observation is that one of the PAFs is a straight line, showing linear relation, while the other PAF is parabolic, showing second-order nonlinearity, as in the simulated system. Therefore, we can reduce Q from 3 to 2. If we look into the PDM weights, we see that we can reduce the number of DLFs from 9 to 8 based on the rules from Section III. In the second step, we re-train the sparse LVN again but

with a pruned model order $(Q, L, H) = (2, 8, 2)$, and the training results are shown in Fig. 5(B). This time, we cannot change H or Q , since there is no redundant PDMs and the PAFs still show second order nonlinearity. However, inspection of the weights shows that L can be further reduced to 7. The next step is to examine the model order $(Q, L, H) = (2, 7, 2)$, and the results are shown in Fig. 5(C). This time we cannot prune the LVN anymore, because there are no redundant elements. Thus, $(Q, L, H) = (2, 7, 2)$ is the final selected model-order.

The PDMs and PAFs estimated by Sparse LVN are very close to their actual counterparts of the simulated system, although for lags 0–10s in PDM 1, we can see some deviations. The reason is that with l_1 regularization, the estimates are biased. Therefore, once we have determined the model order with sparse LVN, we should re-estimate the LVN elements without regularization terms.

In the previous training case, we set the regularization parameter $\lambda = 0.01$. It is very important to determine a proper value of λ , because if λ is too small, then the regularization effect is too limited to yield sparse results. On the other hand, if λ is too large, then the training results would be strongly biased by the regularization term. Therefore, how the regularization parameter λ affects the training results must be carefully assessed.

As an example, we use the same system shown in Fig. 2 with noisy data (SNR = 5, additive GWN) and the same pruning technique to examine how the training results vary for different λ values. The pruned model orders in each step are summarized in Table II and the estimated PDMs and PAFs corresponding to the final determined model order are shown in Fig. 6. As we can see when $\lambda = 0.0001$, the selected model order is $(Q, L, H) = (2, 8, 3)$, which has the wrong number of PDMs, and the estimated PDMs are very different from the actual ones. Therefore, when the regularization strength is low, it cannot yield sparse results and the correct model order.

When we increase λ from 0.001 to 0.02, we can see that the pruning algorithm works well and, although the selected L varies a little, the overall model orders are very close to the best one. In addition, the estimated PDMs and PAFs are very consistent and close to their counterparts in the simulated system. When $\lambda = 0.05$, the determined model order is $(Q, L, H) = (2, 5, 5)$, and the estimated PDMs and ANFs are not accurate. The result is expected, because as the regularization strength increases, the selected model order decreases but the estimated PDMs and ANFs are highly biased.

From the results above, we can conclude that, although the regularization strength generally affects the selected model order of sparse LVN, the effect is relatively small over a wide range of λ values (from 0.001 to 0.02). Therefore, in practice, we can set λ to 0.01 or 0.02. In the following, λ is set to 0.01 unless explicitly stated otherwise.

V. Application to the Hodgkin-Huxley Equations

The Hodgkin-Huxley (H-H) equations are a classic conductance-based model describing the underlying dynamic processes for the generation of an action potential (AP) by a neuron [11]. The main H-H equation is:

$$I = C_m \frac{dV}{dt} + \bar{g}_K n^4 (V - E_K) + \bar{g}_{Na} m^3 h (V - E_{Na}) + \bar{g}_L (V - E_L) \quad (12)$$

where I is the injected current, V is the membrane potential, and C_m is the membrane capacitance. The maximum potassium and sodium conductances are represented by $\bar{g}_K$ and $\bar{g}_{Na}$, and $\bar{g}_L$ is the conductance of the leakage ion channel. E_K , E_{Na} , E_L are the reverse potentials for each channel. We use the standard H-H parameters from the giant axon of a squid, which are summarized in Table III, and the resting potential is set at 0 mV. The gating variables m , n , h are responsible for the voltage-dependent activation and deactivation of the channels, which are expressed in the first-order differential equations:

$$\begin{aligned} \frac{dn}{dt} &= \alpha_n(1-n) - \beta_n n \\ \frac{dm}{dt} &= \alpha_m(1-m) - \beta_m m \\ \frac{dh}{dt} &= \alpha_h(1-h) - \beta_h h \end{aligned} \quad (13)$$

where

$$\begin{aligned} \alpha_n(V) &= \frac{-0.01(V-10)}{e^{-(V-10)/10} - 1}, \quad \beta_n(V) = 0.125e^{-V/80} \\ \alpha_m(V) &= \frac{-0.1(V-25)}{e^{-(V-25)/10} - 1}, \quad \beta_m(V) = 4e^{-V/18} \\ \alpha_h(V) &= 0.07e^{-V/20}, \quad \beta_h(V) = \frac{1}{e^{-(V-30)/10} + 1} \end{aligned} \quad (14)$$

To obtain an equivalent I - V relationship of the H-H equations, we propose a novel Autoregressive Sparse Laguerre-Volterra Network (ASLVN), which is shown in Fig. 7. The ASLVN is derived from traditional two-input, single-output LVN. The exogenous input of ASLVN is $x_1(n) = I(n)$, which is the current injected in the H-H model, and the autoregressive input, $x_2(n) = y(n-1)H(y(n-1) - \theta)$ is the thresholded output of the ASLVN with one lag delay, where $H(x)$ is the unit step function. The reason for introducing the threshold θ is to separate the two distinct dynamic states caused by bifurcation of the H-H model [8]. It should be mentioned that in the model estimation phase, the open-loop ASLVN and the membrane potential $V(n)$ from H-H equations are used to train ASLVN for the sake of stability. Thus, the autoregressive input is: $V(n-1)H(V(n-1) - \theta)$, and the cost

function is: $NMSE = \frac{\sum_n (V(n) - y(n))^2}{\sum_n V(n)^2}$. After the training, the ASLVN predicted output $y(n)$ should be used as the autoregressive input.

The output of the forward branch $z^{(1)}(n)$ and autoregressive branch $z^{(2)}(n)$ are:

$$\begin{aligned}
z^{(i)}(n) &= \sum_{h=1}^{H_i} z_h^{(i)}(n) \\
&= \sum_{h=1}^{H_i} \sum_{q=1}^{Q_i} c_{q,h}^{(i)} \left[T \sum_{m=0}^{M_i-1} p_h^{(i)}(m) x_i(n-m) \right]^q
\end{aligned} \tag{15}$$

and the output of the cross-term is:

$$\begin{aligned}
z^{(cx)}(n) &= \sum_{h_1=1}^{H_1} \sum_{h_2=1}^{H_2} \sum_{q_1+q_2=2}^{Q_{cx}} c_{q_1,q_2,h_1,h_2}^{(cx)} [u_{h_1}^{(1)}(n)]^{q_1} [u_{h_2}^{(2)}(n)]^{q_2} \\
&= \sum_{h_1=1}^{H_1} \sum_{h_2=1}^{H_2} \sum_{q_1+q_2=2}^{Q_{cx}} c_{q_1,q_2,h_1,h_2}^{(cx)} \times \left[T \sum_{m_1=0}^{M_1-1} p_{h_1}^{(1)}(m_1) x_1(n-m_1) \right]^{q_1} \times \left[T \sum_{m_2=0}^{M_2-1} p_{h_2}^{(2)}(m_2) x_2(n-m_2) \right]^{q_2}
\end{aligned} \tag{16}$$

We get the output of the ASLVN by adding all the outputs of above three parts:

$$y(n) = y_0 + z^{(1)}(n) + z^{(2)}(n) + z^{(cx)}(n) \tag{17}$$

We can show that ASLVN is equivalent to two-input Volterra model. For the second order system when $Q_1 = Q_2 = Q_{cx} = 2$:

$$\begin{aligned}
y(n) &= k_{0,0} + T \sum_{m=0}^{M_1-1} k_{1,0}(m) x_1(n-m) \\
&+ T \sum_{m=0}^{M_2-1} k_{0,1}(m) x_2(n-m) \\
&+ T^2 \sum_{m_1=0}^{M_1-1} \sum_{m_2=0}^{M_1-1} k_{2,0}(m_1, m_2) x_1(n-m_1) x_1(n-m_2) \\
&+ T^2 \sum_{m_1=0}^{M_2-1} \sum_{m_2=0}^{M_2-1} k_{0,2}(m_1, m_2) x_2(n-m_1) x_2(n-m_2) \\
&+ T^2 \sum_{m_1=0}^{M_1-1} \sum_{m_2=0}^{M_2-1} k_{1,1}(m_1, m_2) x_1(n-m_1) x_2(n-m_2)
\end{aligned} \tag{18}$$

where $k_{1,0}$, $k_{0,1}$ are the first order self-kernels, $k_{2,0}$, $k_{0,2}$ are the second order self-kernels for input 1 and 2, respectively, and $k_{1,1}$ is the cross-kernel. The equivalent Volterra kernels of ASLVN can be expressed as:

$$\begin{aligned}
k_{0,0} &= y_0 \\
k_{1,0}(m) &= \sum_{h=1}^{H_1} c_{1,h}^{(1)} p_h^{(1)}(m) \\
k_{0,1}(m) &= \sum_{h=1}^{H_2} c_{1,h}^{(2)} p_h^{(2)}(m) \\
k_{2,0}(m_1, m_2) &= \sum_{h=1}^{H_1} c_{2,h}^{(1)} p_h^{(1)}(m_1) p_h^{(1)}(m_2) \\
k_{0,2}(m_1, m_2) &= \sum_{h=1}^{H_2} c_{2,h}^{(2)} p_h^{(2)}(m_1) p_h^{(2)}(m_2) \\
k_{1,1}(m_1, m_2) &= \sum_{h=1}^{H_1} \sum_{h_2=1}^{H_2} c_{h_1, h_2}^{(cx)} p_{h_1}^{(1)}(m_1) p_{h_2}^{(2)}(m_2)
\end{aligned} \tag{19}$$

The training data of H-H model are generated by the Euler forward method with the step size as $1 \mu s$ and the input (units in μA) is drawn from a Gaussian distribution $\mathcal{N}(0, 50)$. The current is injected at a frequency of 200 Hz, and each injection lasts 0.5 ms. The total length of the training data is 10^3 ms. In order to evaluate the model prediction performance, we also generate a set of testing data with the length of 10^4 ms. A proper sampling interval $T = 0.25$ ms is carefully chosen based on the autocorrelation method [3] to avoid redundancy and irrelevance problems. Since the resting potential is 0 mV, we set the constant offset y_0 as 0. Although ASLVN has the ability to train the DLF critical parameter α in both forward and autoregressive branches, both of them are fixed to 0.7 in this case. This is due to the fact that the iterative training procedures are drawn to the fast dynamics of the autoregressive component rather than its complete dynamics, resulting in very small α .

Using the SA training algorithm and the model-order pruning technique, described in Section II and III, the obtained ASLVN model is shown in Fig. 8, and the equivalent Volterra kernels of ASLVN are shown in Fig. 9. Our pruned ASLVN model has three PDMs (one forward and two autoregressive) and a total of 18 parameters.

The output of each ASLVN component is illustrated in Fig. 10 and makes a distinct contribution to the model prediction. The forward PDM has the form of a “leaky integrator” and represents the sub-threshold dynamics of the H-H model in Fig. 10(C). The autoregressive PDMs are responsible for the shape of the action potential in Fig. 10(A), which consists of the depolarization and repolarization components, as well as the hyperpolarization after-potential in Fig. 10(B). The two cross-terms in the model help to maintain the refractory period by counteracting the effect of the exogenous input in a transient manner (absolute and relative refractory period). These three elements, including the capacitive leaky integrator, the action potential and the refractory period, constitute the essential functional features described by the H-H model and should be present in equivalent models which try to emulate the H-H dynamics [1].

The threshold θ is chosen at 4.5 mV in this paper. It should be noted that this θ separates the subthreshold from the suprathreshold nonlinear dynamics, which is different from the traditional hard threshold defined in the integrate-and-fire type of models [48–50]. The effect of different values of θ on the estimated PDMs are insignificant within certain range (2–10 mV) and the model predictive performance is not affected. However, θ affects the cross-term coefficients that are estimated in the ASLVN, because the SA training process adapts these coefficients to accommodate the changes of θ . For example, when θ is small, the cross-term contribution would become more negative at the spike initiation phase to prevent over-firing due to the positive integration of the ASLVN forward branch. We can embed the optimization of θ into the training process, but the estimated θ values will not be the same in every SA optimization. So, we fix θ to guarantee consistency and chose 4.5 mV to allow the comparison with previous NARV and PDM models [5][6]. Another advantage of fixing θ is that the computational burden is significantly reduced by avoiding the convolution computations at each iteration when θ is updated.

It is intriguing that the forward PDM in our pruned ASLVN system resembles the capacitive behavior in the “leaky integrate and fire” (LIF) model, which is expressed by:

$$C_m \frac{dV}{dt} = \frac{1}{R}(E - V) + I \quad (20)$$

We can compare the forward PDM with the LIF model in terms of the rate of exponential decay, which is determined by the time constant $\tau = RC_m$. It has been shown that the H-H model can be reduced to the LIF model by replacing the gating variables m , n , h with their steady values $m_{\infty}(V)$, $n_{\infty}(0)$, $h_{\infty}(0)$ [1]. The reason for this approximation is that under subthreshold conditions, m reaches its steady value $m_{\infty}(V)$ very fast, while n and h change very slow over time and do not deviate much from the values at the resting potential $n_{\infty}(0)$, $h_{\infty}(0)$. So, the main H-H equation can be re-written as:

$$I = C_m \frac{dV}{dt} + f(V) \quad (21)$$

where:

$$f(V) = \bar{g}_K n_{\infty}^4(0)(V - E_K) + \bar{g}_{Na} m_{\infty}^3(V) h_{\infty}(0)(V - E_{Na}) + \bar{g}_L (V - E_L) \quad (22)$$

The graph of $f(V)$ is shown in Fig. 11(A) and $f(V)$ can be approximated by a linear function, where $R = 1/0.65 \text{ k}\Omega$ and the time constant for LIF is $\tau = RC_m = 1.54 \text{ ms}$. The comparison between the LIF model and the forward kernel from the ASLVN are shown in Fig. 11(B), and they match very well in their time course.

We can use the out-of-sample data to compare the performances of different Volterra-type models. The prediction results of NARV, traditional PDM method and ASLVN are summarized in Fig. 12, where the ASLVN has very similar prediction power to NARV

model but the number of parameters N_{param} of ASLVN is significantly reduced to 18. For the traditional PDM method, the prediction power is a bit worse than the other two methods and N_{param} is still large because many cross-terms are still included. Another common way to evaluate the model performance is by receiver operating characteristic (ROC) plots, which are shown in Fig. 13. It can be seen that the performance of ASLVN is superior to others at low false-positive rates (FPR), while at high FPR the ASLVN is just slightly worse than the NARV model, but better than the traditional PDM model.

It is instructive to explore the changes of underlying dynamics in the ASLVN for modeling the H-H equations under the effects of tetrodotoxin (TTX) and tetraethylammonium (TEA), which block the Na^+ and K^+ channel, respectively – i.e. we set $\bar{g}_{\text{Na}}$ or $\bar{g}_{\text{K}}$ equal to zero in the H-H equations to represent the blocking effects by TTX or TEA respectively. The obtained ASLVN models are shown in Fig. 14(A) and (B). As we can see, blocking the Na^+ channel has little effect on the forward PDM but affects the autoregressive PDM that exhibits the dynamics of the K^+ channel (the difference is caused by the autoregressive delay in ASLVN), shown in Fig. 15(A). The associated PAF coefficient is negative, which corresponds to the fact that the K^+ current is flowing out of the neuronal membrane. On the other hand, as shown in Fig. 14(B), blocking the K^+ channel should cause the membrane potential to stay depolarized, so that a constant offset y_0 is added to the ASLVN output to compensate for the bias, and cross-terms are not necessary because no refractory property exists for blocked K^+ channel. The estimated forward PDM is under-damped and the autoregressive PDM is different from the control state in Fig. 15(B), but still retains some of the characteristics of the Na^+ channel.

VI. Conclusions

In this paper, we have examined the use of the Simulated Annealing (SA) algorithm for training the Laguerre-Volterra Network (LVN), which is a Volterra-equivalent general model form for nonlinear dynamic systems. SA training offers some advantages over traditional Back-Propagation (BP) training in terms of avoiding local-minima and convergence problems, which are caused by the non-monotonic activation functions (typically polynomial) employed in the LVN – in contrast to the monotonic activation functions employed by perceptron-type Artificial Neural Networks (ANN). Another advantage of SA over BP is that it does not require complex gradient calculations (thus reducing the computational burden) and it removes the restriction of differentiability of the cost function. Thus, ℓ_1 regularization (non-differentiable cost function) becomes feasible.

On the other hand, SA has the disadvantage of slow training speed because it can only update one parameter at each iteration, while the BP method can update all the parameters. This is probably why BP still dominates the ANN training applications. However, in the context of LVN, the training speed of SA is comparable to BP for the following three reasons: (a) unlike ANN which usually has many hidden nodes, LVN usually has a small number of hidden units (<10); (b) BP requires complex calculations of gradients, whereas SA only needs simple calculations; (c) several techniques exist for accelerated SA (e.g. using exponential decay cooling schedule). We also introduce a model-order pruning technique to determine the model order for sparse LVN with ℓ_1 regularization. In a

simulated-system study, the pruning technique was shown to be effective and converged fast to the true model order.

We tested this new nonlinear model training approach with a new model structure of Autoregressive Sparse LVN (ASLVN) that is applicable to input-output modeling of complex non-linear systems that exhibit transitions in dynamic state (e.g. between subthreshold and suprathreshold behaviors), initially demonstrating its use on the celebrated Hodgkin-Huxley (HH) equations of neuronal firing. A compact and accurate ASLVN model was obtained using the SA algorithm and the model-order pruning technique (shown in Fig. 8) that consists of only one forward PDM and two autoregressive PDMs. The resulting model predictions (shown in Fig. 12 and 13) indicate that the ASLVN has better predictive power than the traditional PDM method and comparable to the recently introduced NARV method. The compactness of the ASLVN H-H model (shown in Fig. 10) also facilitates the physiological interpretation of the model. Compared to the traditional “leaky integrate and fire” (LIF) model, our ASLVN model (shown in Fig. 11) exhibits richer and more accurate refractory and after-potential dynamics, while it shows similar subthreshold capacitive characteristics. For example, the LIF utilizes a fixed absolute refractory period, while the ASLVN model captures explicitly the refractory characteristics of the neuron via the autoregressive components and cross-terms. Finally, it was shown that the ASLVN can delineate the effects of altered dynamics in the Na^+ and K^+ ion channels upon action potential generation, as shown in Fig. 14 and 15.

We finally note that the PDMs obtained from LVN/ASLVN are not orthogonal (as in the traditional PDM analysis), which may provide more flexible model representations and better physiological interpretation. Furthermore, LVN/ASLVN uses the SA training algorithm and the pruning technique for sparse modeling to adjust the (non-orthogonal) PDMs so that they fit the system structure in a parsimonious manner, which may minimize the estimation errors and information loss caused by the kernel-based estimation method of traditional (orthogonal) PDMs.

Acknowledgments

This work was supported in part by the NIH/NIBIB grant P41-EB001978 to the Biomedical Simulations Resource Center at the University of Southern California.

Biographies

Kunling Geng received the B.S. degree in Electrical and Computer Engineering from the Shanghai Jiao Tong University (SJTU), Shanghai, China, in 2012. He is currently a Biomedical Engineering Ph.D. candidate at the University of Southern California (USC).

His research focuses on developing compact and powerful methods based on Volterra model to analyze the complex and nonlinear physiological systems, as well as interpret and obtain the insights of the data.

Vasilis Marmarelis, PhD in Engineering Science, Caltech (1976), Professor of Biomedical Engineering at USC and co-Director of the Biomedical Simulations Resource, a research center funded by NIH since 1985. He served as Department Chairman from 1990 to 1996 and on the IEEE Editorial Board for many years. His key research interests are: (1) dynamic nonlinear modeling of biomedical systems; (2) neural information processing; (3) modeling of physiological autoregulation; (4) multimodal ultrasound tomography (MUT) for diagnostic imaging; (5) model-based diagnostic physiomarkers. The key application domains of interest are: cerebral hemodynamics and flow regulation, neurodegenerative and cerebrovascular disease, neurostimulation to treat brain disorders, endocrine-metabolic regulation and diabetes, and non-invasive lesion differentiation via MUT diagnostic imaging. Co-author of the seminal book: “Analysis of Physiological System: The White Noise Approach” (1978; Russian, 1981; Chinese, 1990) and author of the 2004 monograph: “Nonlinear Dynamic Modeling of Physiological Systems”. He has published more than 150 journal papers and book chapters. In 2000, he invented the MUT diagnostic imaging system for early detection of breast cancer, which is currently clinically evaluated in Europe. He is a Fellow of the IEEE and the AIMBE.

References

1. Abbott, L., Kepler, TB. Model neurons: From Hodgkin-Huxley to Hopfield. In: Garrido, L., editor. Stat Mechanics of Neural Networks. New York: Springer; 1990. p. 5-18.
2. Alataris K, Berger T, Marmarelis V. A novel network for non-linear modeling of neural systems with arbitrary point-process inputs. Neural Networks. 2000; 13:255–266. [PubMed: 10935764]
3. Billings S, Aguirre LA. Effects of the sampling time on the dynamics and identification of nonlinear models. Int J of Bifurcation and Chaos. 1995; 5:1541–1556.
4. ernaly V. Thermodynamical approach to the traveling salesman problem: An efficient simulation algorithm. J of Optimization Theory and Applicat. 1985; 45:41–51.
5. Eikenberry SE, Marmarelis VZ. A nonlinear autoregressive Volterra model of the Hodgkin–Huxley equations. J of Computational Neurosci. 2013; 34:163–183.
6. Eikenberry SE, Marmarelis VZ. Principal dynamic mode analysis of the Hodgkin–Huxley equations. Int J of Neural Syst. 2015; 25:1550001. [PubMed: 25630480]
7. Geman S, Geman D. Stochastic relaxation, Gibbs distributions, and the Bayesian restoration of images. IEEE Trans Pattern Anal and Mach Intell. 1984:721–741.
8. Guckenheimer J, Labouriau J. Bifurcation of the Hodgkin and Huxley equations: a new twist. Bulletin of Math Biology. 1993; 55:937–952.
9. Hassoun, MH. Fundamentals of Artificial Neural Networks. Cambridge, MA: MIT press; 1995.

10. Hastie, T., Tibshirani, R., Friedman, J. The Elements of Statistical Learning. New York: Springer; 2009.
11. Hodgkin AL, Huxley AF. A quantitative description of membrane current and its application to conduction and excitation in nerve. The J of Physiology. 1952; 117:500–544.
12. Jacobs RA. Increased rates of convergence through learning rate adaptation. Neural Networks. 1988; 1:295–307.
13. Kirkpatrick S, Gelatt CD, Vecchi MP. Optimization by simulated annealing. Science. 1983; 220:671–680. [PubMed: 17813860]
14. Marmarelis VZ. Identification of nonlinear biological systems using Laguerre expansions of kernels. Ann of Biomed Eng. 1993; 21:573–589. [PubMed: 8116911]
15. Marmarelis, VZ. Nonlinear Dynamic Modeling of Physiological Systems. Hoboken, NJ: John Wiley & Sons; 2004.
16. Marmarelis VZ, Chon KH, Holstein-Rathlou NH, Marsh DJ. Nonlinear analysis of renal autoregulation in rats using principal dynamic modes. Ann of Biomed Eng. 1999; 27:23–31. [PubMed: 9916757]
17. Marmarelis VZ, Juusola M, French AS. Principal dynamic mode analysis of nonlinear transduction in a spider mechanoreceptor. Ann of Biomed Eng. 1999; 27:391–402. [PubMed: 10374731]
18. Marmarelis VZ, Shin DC, Song D, Hampson RE, Deadwyler SA, Berger TW. Nonlinear modeling of dynamic interactions within neuronal ensembles using principal dynamic modes. J of Computational Neurosci. 2013; 34:73–87.
19. Marmarelis VZ, Shin DC, Orme M, Zhang R. Closed-loop dynamic modeling of cerebral hemodynamics. Ann of Biomed Eng. 2013; 41:1029–1048. [PubMed: 23292615]
20. Marmarelis VZ, Shin DC, Zhang R. Linear and nonlinear modeling of cerebral flow autoregulation using principal dynamic modes. The Open Biomed Eng J. 2012; 6:42–55. [PubMed: 22723806]
21. Marmarelis VZ, Shin DC, Song D, Hampson RE, Deadwyler SA, Berger TW. On parsing the neural code in the prefrontal cortex of primates using principal dynamic modes. J of Computational Neurosci. 2014; 36:321–337.
22. Marmarelis VZ, Shin DC, Orme M, Zhang R. Time-varying modeling of cerebral hemodynamics. IEEE Trans Biomed Eng. 2014; 61:694–704. [PubMed: 24184697]
23. Marmarelis VZ. Modeling methodology for nonlinear physiological systems. Ann of Biomed Eng. 1997; 25:239–251. [PubMed: 9084829]
24. Marmarelis VZ, Zhao X. Volterra models and three-layer perceptrons. IEEE Trans Neural Networks. 1997; 8:1421–1433. [PubMed: 18255744]
25. Mitsis GD, Zhang R, Levine B, Marmarelis VZ. Modeling of nonlinear physiological systems with fast and slow dynamics. II. Application to cerebral autoregulation. Ann of Biomed Eng. 2002; 30:555–565. [PubMed: 12086006]
26. Mitsis GD, Poulin MJ, Robbins PA, Marmarelis VZ. Nonlinear modeling of the dynamic effects of arterial pressure and CO₂ variations on cerebral blood flow in healthy humans. IEEE Trans Biomed Eng. 2004; 51:1932–1943. [PubMed: 15536895]
27. Moody J, Hanson S, Krogh A, Hertz JA. A simple weight decay can improve generalization. Advances in Neural Inform Process Sys. 1995; 4:950–957.
28. Murphy, KP. Machine learning: A Probabilistic Perspective. Cambridge, MA: MIT press; 2012.
29. Nourani Y, Andresen B. A comparison of simulated annealing cooling strategies. J of Physics A: Mathematical and General. 1998; 31:8373.
30. Ogura, H. Estimation of Wiener kernels of a nonlinear system and a fast algorithm using digital Laguerre filters. 15th NIBB Conf; Okazaki, Japan. 1985. p. 14–62.
31. Plaut, DC. Experiments on learning by back propagation. Dept. of Comput. Sci., Carnegie-Mellon Univ; Pittsburgh, PA: 1986. Rep. CMU-CS-86-126
32. Schwarz G. Estimating the dimension of a model. The Ann of Stat. 1978; 6:461–464.
33. Song D, Wang H, Berger TW. Estimating sparse Volterra models using group L1-regularization. 2010 Annu Int Conf of the IEEE Eng in Medicine and Biology Soc (EMBC). 2010:4128–4131.

34. Song D, Wang H, Tu CY, Marmarelis VZ, Hampson RE, Deadwyler SA, et al. Identification of sparse neural functional connectivity using penalized likelihood estimation and basis functions. *J of Computational Neurosci.* 2013; 35:335–357.
35. Marmarelis PZ, Naka K-I. White-noise analysis of a neuron chain: an application of the Wiener theory. *Science.* 1972; 175:1276–1278. [PubMed: 5061252]
36. Marmarelis, PZ., Marmarelis, VZ. *Analysis of Physiological Systems: The White-Noise Approach.* New York: Plenum; 1978.
37. Marmarelis VZ. Signal transformation and coding in neural systems. *IEEE Trans Biomed Eng.* 1989; 36:15–24. [PubMed: 2646209]
38. Geng K, Marmarelis VZ. Pattern recognition of Hodgkin-Huxley equations by auto-regressive Laguerre-Volterra network. *BMC Neurosci.* 2015; 16:156.
39. Marder E, Taylor AL. Multiple models to capture the variability in biological neurons and networks. *Nat Neurosci.* 2011; 14(2):133–138. [PubMed: 21270780]
40. Catterall WA, Raman IM, Robinson HPC, Sejnowski TJ, Paulsen O. The Hodgkin-Huxley heritage: from channels to circuits. *The J of Neurosci.* 2012; 32(41):14064–14073. [PubMed: 23055474]
41. O'Donnell C, Van Rossum MC. Systematic analysis of the contributions of stochastic voltage gated channels to neuronal noise. *Frontiers in Computational Neurosci.* 2014; 8:105.
42. Fox RF, Lu YN. Emergent collective behavior in large numbers of globally coupled independently stochastic ion channels. *Physical Review E.* 1994; 49(4):3421–3431.
43. Goldwyn JH, Imenov NS, Famulare M, Shea-Brown E. Stochastic differential equation models for ion channel noise in Hodgkin-Huxley neurons. *Physical Review E.* 2011; 83(4):041908.
44. Güler M. Stochastic Hodgkin-Huxley equations with colored noise terms in the conductances. *Neural Computation.* 2013; 25(1):46–74. [PubMed: 23020107]
45. Yu L, Liu L. Optimal size of stochastic Hodgkin-Huxley neuronal systems for maximal energy efficiency in coding pulse signals. *Physical Review E.* 2014; 89(3):032725.
46. Kang Q, Huang B, Zhou M. Dynamic behavior of artificial Hodgkin-Huxley neuron model subject to additive noise. *IEEE Trans Cybern.* 2015; PP(99):1–1.
47. Saggar, M., Meriçli, T., Andoni, S., Miikkulainen, R. System identification for the Hodgkin-Huxley model using artificial neural networks. *Int. Joint Conf. on Neural Networks*; Orlando, FL. 2007.
48. Kistler W, Gerstner W, Hemmen J. Reduction of the Hodgkin-Huxley equations to a single-variable threshold model. *Neural Computation.* 1997; 9(5):1015–1045.
49. Jolivet R, Rauch A, Luscher H, Gerstner W. Predicting spike timing of neocortical pyramidal neurons by simple threshold models. *J of Computational Neurosci.* 2006; 21(1):35–49.
50. Lazar AA. Population encoding with Hodgkin-Huxley neurons. *IEEE Trans Inform Theory.* 2010; 56(2):821–837.
51. Sandler RA, Song D, Hampson RE, Deadwyler SA, Berger TW, Marmarelis VZ. Model-based assessment of an in-vivo predictive relationship from CA1 to CA3 in the rodent hippocampus. *J of Computational Neurosci.* 2015; 38(1):89–103.
52. Sandler RA, Marmarelis VZ. Understanding spike-triggered covariance using Wiener theory for receptive field identification. *J of Vision.* 2015; 15(9):16–16.
53. Kang Y, Escudero J, Shin DC, Ifeachor E, Marmarelis VZ. Principal dynamic mode analysis of EEG data for assisting the diagnosis of Alzheimer's disease. *IEEE J of Translational Eng in Health and Medicine.* 2015; 3:1–10.

Appendix: Mathematical representation of LVN and the Back-Propagation training Method

The basic structure of the LVN is shown in Fig. 1. First, the input data $x(n)$ is preprocessed by a filter bank of DLFs: $b_0, \dots, b_{L-1}$, which are given by [26]:

$$b_j(m) = \alpha^{(m-j)/2} (1-\alpha)^{1/2} \sum_{k=0}^j (-1)^k \times \binom{m}{k} \binom{j}{k} \alpha^{j-k} (1-\alpha)^k \quad (\text{A1})$$

where m is from 0 to $M-1$ (M is the memory length of the system). The parameter α is critical for controlling the exponential declining rate of DLF: larger α means slower and longer response. Therefore, system kernels with longer memory length would require larger α to guarantee efficient representation. The outputs of filter bank, which can be written as the convolution between input $x(n)$ and DLFs:

$$v_j(n) = \sum_{m=0}^{M-1} b_j(m) x(n-m) \quad (\text{A2})$$

To reduce the computational complexity, an iterative method is proposed in [30] to auto-recursively calculate $v_j(n)$:

$$v_j(n) = \sqrt{\alpha} [v_j(n-1) + v_{j-1}(n)] - v_{j-1}(n-1) \quad (\text{A3})$$

and

$$v_0(n) = \sqrt{\alpha} v_0(n-1) + T \sqrt{(1-\alpha)} x(n) \quad (\text{A4})$$

where T is the sampling interval, and the inputs of the hidden units $u(n)$ is the weighted summation of $v_j(n)$:

$$u_h(n) = \sum_{j=0}^{L-1} w_{j,h} v_j(n) \quad (\text{A5})$$

Then $u_h(n)$ is propagate to the hidden nodes with Q th-order polynomial activation functions (PAFs):

$$z_h(n) = \sum_{q=1}^Q c_{q,h} u_h^q(n) \quad (\text{A6})$$

Finally, adding all the outputs of hidden units and the constant offset value y_0 , we can get the output for the entire LVN:

$$y(n) = \sum_{h=1}^H z_h(n) + y_0 \quad (\text{A7})$$

By summarizing previous equations, the output $y(n)$ can be written as:

$$y(n) = \sum_{h=1}^H \sum_{q=1}^Q c_{q,h} \left[\sum_{j=0}^{L-1} w_{j,h} v_j(n) \right] + y_0 \quad (\text{A8})$$

Principal dynamic mode (PDM) can be represented by the weighted summation of the DLFs:

$$p_h(m) = \sum_{j=0}^{L-1} w_{j,h} b_j(m) \quad (\text{A9})$$

The outputs of the hidden nodes can be written as:

$$u_h(n) = T \sum_{m=0}^{M-1} p_h(m) x(n-m) \quad (\text{A10})$$

The output of LVN can also be expressed in terms of PDMs:

$$y(n) = \sum_{h=1}^H \sum_{q=1}^Q c_{q,h} \left[T \sum_{m=0}^{M-1} p_h(m) x(n-m) \right] + y_0 \quad (\text{A11})$$

Compare the output of LVN in Eq. (A11) to the discrete Volterra model (DVM):

$$y(n) = k_0 + T \sum_{m=1}^M k_1(m) x(n-m) + T^2 \sum_{m_1=1}^M \sum_{m_2=1}^M k_2(m_1, m_2) x(n-m_1) x(n-m_2) + \dots \quad (\text{A12})$$

We can show that LVN is equivalent to DVM:

$$k_1(m) = \sum_{h=1}^H c_{1,h} p_h(m) \quad (\text{A13})$$

$$k_2(m_1, m_2) = \sum_{h=1}^H c_{2,h} p_h(m_1) p_h(m_2) \quad (\text{A14})$$

$$k_Q(m_1, \dots, m_Q) = \sum_{h=1}^H c_{Q,h} p_h(m_1) \dots p_h(m_Q) \quad (\text{A15})$$

The training of the aforementioned four groups of parameters – i.e. the DLF parameter α , the PDM weights $w_{j,h}$, the polynomial activation coefficients $c_{q,h}$ and the constant offset value y_0 – was previously achieved by use of the BP algorithm that is outlined below. Define the error for each data point as:

$$\varepsilon(n) = d(n) - y(n) \quad (\text{A16})$$

where $d(n)$ is the actual output, and $y(n)$ is the estimated output of LVN. The cost function is often defined as the square of the error:

$$J(n) = \frac{1}{2} \varepsilon(n)^2 = \frac{1}{2} (d(n) - y(n))^2 \quad (\text{A17})$$

Use p denotes as a single parameter in LVN, each time we update p using gradient descent, and the step change for p in each iteration should be:

$$\Delta p = p^{\text{new}} - p^{\text{old}} = -\gamma_p \frac{\partial J(n)}{\partial p} = \gamma_p \varepsilon(n) \frac{\partial y(n)}{\partial p} \quad (\text{A18})$$

where γ_p is the learning rate for parameter p . Applying chain rules for Eq. (A8) with respect to each parameter, we can get first order derivative $\frac{\partial y(n)}{\partial p}$. Substitute it in Eq. (A18), the step change for each type of parameters can be expressed by:

$$\Delta \beta = \gamma_\beta \varepsilon(n) \sum_{h=1}^H f'_h[u_h(n)] \sum_{j=0}^{L-1} w_{j,h} [v_j(n-1) + v_{j-1}(n)] \quad (\text{A19})$$

$$\Delta w_{j,h} = \gamma_w \varepsilon(n) f'_h[u_h(n)] v_j(n) \quad (\text{A20})$$

$$\Delta c_{q,h} = \gamma_c \varepsilon(n) [u_h(n)]^q \quad (\text{A21})$$

$$\Delta y_0 = \gamma_y \varepsilon(n) \quad (\text{A22})$$

where $\beta = \sqrt{\alpha}$ and $f'_h[u_h(n)]$ is the derivative of the PAF of the h th hidden unit:

$$f'_h[u_h(n)] = \sum_{q=1}^Q q c_{q,h} [u_h(n)]^{q-1} \quad (\text{A23})$$

Fig. 1.
The Architecture of Laguerre-Volterra Network [24].

Fig. 2.

The simulated system contains two distinct PDMs and the associated PAFs (second order polynomial function for 1st PDM and linear function for 2nd PDM).

Fig. 3.

BIC values for LVN for all model orders ($Q_{max} = 3, L_{max} = 9$). The lowest BIC values are: 1.018×10^4 , 0.9496×10^4 , 0.9496×10^4 , and the corresponding model orders are: $(Q, L, H) = (1, 6, 1), (2, 7, 2), (3, 7, 2)$ for $Q = 1, 2, 3$, respectively.

Fig. 4.

After 400,000 iterations of the SA algorithm: **(A)** tracking curves of NMSE, α , and y_0 ; **(B)** tracking curves of the LVN weights and PAF coefficients; **(C)** the actual and estimated PDMs; **(D)** the actual and estimated PAFs. The model order is $(Q, L, H) = (2, 7, 2)$, which is determined by BIC.

Fig. 5.

The PDMs and PAFs estimated in each step of model order pruning technique: **(A)** Step 1 with full model order $(Q, L, H) = (3, 9, 9)$; **(B)** Step 2 with pruned model order $(Q, L, H) = (2, 8, 2)$; **(C)** Step 3 with final selected model order $(Q, L, H) = (2, 7, 2)$.

Fig. 6. The PDMs and PAFs that are estimated by Sparse LVN under different regularization strengths with $\lambda = 0.0001, 0.001, 0.005, 0.01, 0.02, 0.05$.

Fig. 7.

The structure of autoregressive sparse Laguerre-Volterra Network (ASLVN) for modeling H-H equations. It consists of three parts: (1) the forward branch with input $I(n)$, (2) the autoregressive branch with input $y(n-1)H(y(n-1)-\theta)$ and (3) the cross-terms representing the interactions between the forward and autoregressive branches.

Fig. 8.

The obtained ASLVN model using the SA training algorithm and the model-order pruning technique. The model orders for the forward branch and the autoregressive branch are: $(Q_1, L_1, H_1) = (1, 3, 1)$ and $(Q_2, L_2, H_2) = (2, 4, 2)$, respectively. The model contains only one forward PDM with a linear PAF, two autoregressive PDMs with second-order PAFs, and two bilinear cross-terms.

Fig. 9.

The equivalent Volterra kernels constructed from the trained ASLVN model, where $k_{1,0}$ is the first order forward kernel, $k_{0,1}$ and $k_{0,2}$ are the first and second order autoregressive kernels, and $k_{1,1}$ is the cross-kernel.

Fig. 10.

The traces of total output y , forward branch output $z^{(1)}$, autoregressive branch output $z^{(2)}$ and cross-term output $z^{(cx)}$ in **(A)** spike (action potential) generation phase, **(B)** refractory phase and **(C)** sub-threshold phase.

Fig. 11.

(A) The linear approximation $f(V) = 0.65V + 0.37$ of the nonlinear characteristic function $f(V)$ under subthreshold conditions ($V < 4.5\text{mV}$); and (B) comparison of subthreshold dynamics of the ASLVN and LIF models.

Fig. 12.

Out-of-sample prediction results by NARV (top), PDM (middle) and ASLVN (bottom) models. For NARV, the model order is: $Q_1 = Q_2 = 2$, $L_1 = L_2 = 5$. For PDM, the model order is: $(Q_1, L_1, H_1) = (2, 5, 2)$, $(Q_2, L_2, H_2) = (2, 5, 4)$. For ASLVN, the model order is: $(Q_1, L_1, H_1) = (1, 3, 3)$, $(Q_2, L_2, H_2) = (2, 4, 2)$. The number of parameters, N_{param} for these three methods are 65, 50 and 18.

Fig. 13.

Receiver operating characteristic (ROC) plots for NARV, PDM and ASLVN models.

Fig. 14.

The obtained ASLVN input-output model of the H-H equations with blocked ion channels:
(A) blocked Na^+ channel; **(B)** blocked K^+ channel.

Fig. 15.

(A) Comparison of the estimated autoregressive PDM in Fig. 14(A) and K^+ conductance during an action potential; (B) Comparison of the estimated autoregressive PDM in Fig. 14(B) and Na^+ conductance during an action potential.

TABLE I

Simulated annealing parameters

Symbol	Name	Value
T_0	Initial temperature	100
η	Cooling constant	0.99
N_t	No. of temperature droppings	2000
N_i	No. of iterations at each temperature	200
$\gamma_a, \gamma_w, \gamma_c, \gamma_{y0}$	Step sizes	0.01

TABLE II

Model order pruning results for different regularization strengths

Symbol	$\lambda=0.0001$	$\lambda=0.001$	$\lambda=0.005$	$\lambda=0.01$	$\lambda=0.02$	$\lambda=0.05$
Step 1	(3, 9, 9)	(3, 9, 9)	(3, 9, 9)	(3, 9, 9)	(3, 9, 9)	(3, 9, 9)
Step 2	(3, 9, 3)	(2, 8, 4)	(2, 8, 2)	(2, 8, 2)	(2, 7, 2)	(2, 6, 2)
Step 3	(3, 8, 2)	(2, 8, 2)	\	(2, 7, 2)	\	(2, 5, 2)

Note that for $\lambda = 0.05$ and 0.02 , the model order pruning technique stops at step 2.

TABLE III

Parameters of hodgkin-huxley equations

Symbol	Name	Value
C_M	Membrane conductance	1 uF/cm ²
E_K	Reverse potential of K ⁺ channel	−12 mV
E_{Na}	Reverse potential of Na ⁺ channel	115 mV
E_L	Reverse potential of leak channel	10.6 mV
$\bar{g}_{Na}$	Maximum conductance of Na ⁺ channel	120 mS/cm ²
$\bar{g}_K$	Maximum conductance of K ⁺ channel	36 mS/cm ²
$\bar{g}_L$	Conductance of leak channel	0.3 mS/cm ²