Published in final edited form as:

IEEE Trans Electromagn Compat. 2006 August 21; 48(3): 579–588. doi:10.1109/TEM.2006.877785.

International Intercomparison of Specific Absorption Rates in a Flat Absorbing Phantom in the Near-Field of Dipole Antennas

Christopher C. Davis [Fellow, IEEE],

Department of Electrical and Computer Engineering, University of Maryland, College Park, MD 20742 USA

Brian B. Beard,

Center for Devices and Radiological Health, Food and Drug Administration, Rockville, MD 20850 USA

Ahlia Tillman,

Department of Electrical and Computer Engineering, University of Maryland, College Park, MD 20742 USA, and also with Integrated Defense Systems Division, Raytheon, Waltham, MA 02451 USA

John Rzasa,

Department of Electrical and Computer Engineering, University of Maryland, College Park, MD 20742 USA

Eric Merideth, and

Department of Electrical and Computer Engineering, University of Maryland, College Park, MD 20742 USA. He is now with the Lincoln Laboratory, Massachusetts Institute of Technology, Lexington, MA 02420 USA

Quirino Balzano [Fellow, IEEE]

Department of Electrical and Computer Engineering, University of Maryland, College Park, MD 20742 USA

Abstract

This paper reports the results of an international intercomparison of the specific absorption rates (SARs) measured in a flat-bottomed container (flat phantom), filled with human head tissue simulant fluid, placed in the near-field of custom-built dipole antennas operating at 900 and 1800 MHz, respectively. These tests of the reliability of experimental SAR measurements have been conducted as part of a verification of the ways in which wireless phones are tested and certified for compliance with safety standards. The measurements are made using small electric-field probes scanned in the simulant fluid in the phantom to record the spatial SAR distribution. The intercomparison involved a standard flat phantom, antennas, power meters, and RF components being circulated among 15 different governmental and industrial laboratories. At the conclusion of each laboratory's measurements, the following results were communicated to the coordinators: Spatial SAR scans at 900 and 1800 MHz and 1 and 10 g maximum spatial SAR averages for cubic volumes at 900 and 1800 MHz. The overall results, given as meanstandard deviation, are the following: at 900 MHz, 1 g average 7.850.76; 10 g average 5.160.45; at 1800 MHz, 1 g average 18.44 ± 1.65 ; 10 g average 10.14 ± 0.85 , all measured in units of watt per kilogram, per watt of radiated power.

Index Terms

FCC certification; near-field antenna measurement; specific absorption rate; wireless phones

I. Introduction

Current compliance testing procedures for hand-held wireless cellular telephones require that manufacturers assess the maximum near-field exposures that they might produce in the head of a phone user. Federal Communications Commission (FCC) guidelines currently specify that the maximum specific absorption rate (SAR) averaged over 1 g of tissue should not exceed 1.6 W/kg [1]. The IEEE Standards Coordinating Committee 34 (SCC-34), sub-Committee 2 (SC2) has published a compliance verification standard 1528 [2], which specifies the measurement procedures to be followed in testing whether a wireless phone is compliant with international standards, such as those established by the FCC, the IEEE [3], and the International Electrotechnical Commission (IEC) [4]. Compliance standards and procedures specified by international bodies include the IEC 62209 [4] and CENELEC EN 50361 [5] standards, which are broadly similar to the IEEE Standard 1528.

The current industry standard for assessing the compliance of a wireless phone is to place such a phone in a specified orientation in the ear region of an anthropomorphic phantom (head model). This phantom is manufactured as a thin nonabsorbing shell, shaped to model the anatomic contours of the human head and torso, and filled with a lossy dielectric fluid whose dielectric properties are representative of the worst-case RF absorption in the human head. Then, the maximum volume-averaged SAR is measured by scanning the phantom with an E-field probe. The rationale of this approach is that if the SAR limits as per the guidelines are not exceeded in the phantom, then they will not be exceeded in the more complex structure of a real human head. This conclusion is based on theoretical comparisons of the spatial SAR produced by model antennas placed in close proximity to the models of the head of varying degrees of complexity.

In July 2000, the Mobile Manufacturers Forum (MMF), which is a wireless phone industry group, initiated an international intercomparison of compliance SAR testing to be coordinated by the University of Maryland. Testing the reliability of the experimental SAR assessments involved an international intercomparison of SAR measurements made in a simple flat phantom filled with head simulant fluids. It was not the intention of this intercomparison to replicate the procedures being developed at that time into IEEE Standard 1528. A simple flat phantom design was chosen that was sufficiently robust to withstand the repeated moves and setups involved in using it in many laboratories. Custom antennas were prepared for the intercomparison that had not previously been analyzed by any of the participating laboratories, so as to provide a degree of “blindness” in the measurements. SAR measurements were made using small electric-field probes placed in the simulant fluid in the phantom and scanned in three-dimensions (3-D) to produce the spatial SAR distribution values in the phantom. The intercomparison involved a standard flat phantom, antennas, some critical power meters, and RF components being circulated among 16 different laboratories, including governmental and industrial laboratories, and the University

of Maryland. Each participating laboratory provided its own electric-field probes, scanning system, and a simulant fluid prepared to a required prescription. At the conclusion of each laboratory's measurements, its results were communicated to the coordinators including: spatial SAR scans at 900 and 1800 MHz and 1 and 10-g spatial SAR averages for cubic volumes at 900 and 1800 MHz. In this paper, we describe the detailed protocols involved in the intercomparison, and provide a detailed summary of all the results.

The participating industrial laboratories were Alcatel (France), Ericsson (Sweden), Mitsubishi (Japan), Motorola (USA), Nokia (Finland), N.T.T. DoCoMo (Japan), Panasonic (Japan), Sagem (France), Samsung (Korea), Siemens (Germany), Sony-Ericsson (USA), and Telecom Engineering Center (Telec) (Japan); and the following governmental laboratories: Center for Devices and Radiological Health (Food and Drug Administration, USA), the Federal Communications Commission (FCC, USA), and Telecommunication Metrology Center (TMC) (Beijing, PRC). Each laboratory reported its results only to the University of Maryland and is identified in this paper by a letter (A–O). Each laboratory was informed only of its own identifier letter.

II. Experimental Details

A. Circulating Flat Phantom System

To establish uniformity of the SAR measurement method among the participating laboratories, an exposure system and phantom shell were prepared for circulation. This system consisted of the following items: a flat phantom (size: $340 \times 440 \times 210 \text{ mm}^3$), two printed circuit antennas (one each designed for 900- and 1800-MHz operation), a dual power meter (Agilent Model E4419B with Power Sensors, Model: 8481A), a precision 30-dB dual directional coupler (Narda Model 3282B-30, 800–4000 MHz), a 30-dB attenuator (Weinschel Model 1A), antenna cable, and mounting stand for the flat phantom and antenna. Each participating laboratory had to provide its own head tissue simulant fluid, prepared according to a prescription, as well as electric-field probe, and 3-D scanning and data acquisition system. At the conclusion of each laboratory's measurements, they sent the flat phantom and associated equipment to the next participating laboratory. Half way through the process, the system returned to the University of Maryland for checks to determine if any problems had developed.

B. Flat Phantom

The flat phantom was fabricated from 6-mm-thick high-density polyethylene of dimensions $340 \times 440 \times 210 \text{ mm}^3$. These dimensions were chosen so that for 900- and 1800-MHz dipole antennas, the phantom constituted an infinite half space when filled with simulant fluid. The phantom is shown in Fig. 1.

C. Dipole Antenna

To enable an original study of SAR, two novel printed-circuit dipole antennas were fabricated. These are shown in Fig. 2. The antennas were non-standard so that none of the participants would know the “true” value of the SAR induced by the dipole in flat phantoms by referring to previously published data [2]. The antennas were fabricated from double-

sided printed circuit board material, etched on both sides to produce the stripline feed sections and dipole arms. The feed line was also a balun to excite both the arms of the dipole antennas with equal current. The antennas in Fig. 1 are metal runners on both sides of a PC board. The two branches of the dipoles were strips 4-mm wide and 65-mm long at 900 MHz and 33-mm long at 1800 MHz. The two runners overlapped over 4-mm of their length so that the total length of the antennas was 123 mm at 900 MHz and 58 mm at 1800 MHz. Further details of the antenna design have been published earlier [6].

D. Phantom-Mounting Assembly

The flat phantom was supplied to each participating laboratory with a mounting frame, as shown in Fig. 3. Fig. 4 shows the placement of an antenna below the bottom center of the phantom in the geometry used for SAR measurements. Each participating laboratory was instructed to mount the antenna flush with the bottom of the phantom to ensure a uniform geometry for SAR measurements. The antenna-mounting arrangement included a strain-relief clamp to prevent the connection coaxial cable moving the antenna from its desired position.

The block diagram of the overall system is shown in Fig. 5. Each participating laboratory provided their own 900- and 1800-MHz RF power sources. The source in use was connected to the input port of the precision 30-dB dual-directional coupler, and the supplied antenna cable was connected from the output port of the coupler to the antenna. Forward and reflected power measurements were made using the coupler and the supplied power meters. Each laboratory also reported the power (P_1) at the input port of the coupler and the power (P_2) at the distal end of the antenna cable (before connection to the antenna). In order to avoid possible damage to the power meters, each laboratory was instructed to make these measurements using a supplied 30-dB attenuator.

E. Head Tissue Simulant Fluid

Each laboratory was required to mix its own simulant for filling the phantom. The prescriptions for the 900- and 1800-MHz simulant fluids are specified in IEEE Standard 1528. They are as follows.

1) Simulant for Head Tissue at 900 MHz—Targets (dielectric constant, conductivity in siemens per meter): 41.5, 0.97. Recipe by weight: 56.50% sugar, 40.92% deionized water, 1.48% salt, 1.00% hydroxyethyl cellulose (HEC), 0.10% bactericide.

2) Simulant for Head Tissue at 1800 MHz—Targets (dielectric constant, conductivity in siemens per meter): 40.0, 1.40. Recipe by weight: 47.00% diethylene glycol (mono) butyl ether (DGBE), 52.64% deionized water, 0.36% salt.

F. Experimental Protocol

Each participant performed a 3-D scan of the electric-field distribution in the flat phantom on a grid with a spacing of 10 mm or less. The electric field was measured with a calibrated electric-field probe and electronics supplied by each participant. Each laboratory provided its own system for moving the probe in three dimensions. All scanning systems except those

used by the University of Maryland and the U.S. Food and Drug Administration were DASY-3 or DASY-4 SAR-scanning systems from SPEAG. The University of Maryland used a SPEAG E-field probe Model ET3DV6R and scanning system based on linear scanning stages (Arrick Robotics with MD-2 Dual Stepper Motor Drivers). The FDA used a SPEAG E-field probe Model ET3DV6R probe and a three-axis linear scanning system based on Arrick Robotics linear positioning hardware and LabView software.

III. Calibration Results

A. Reporting

Each laboratory participating in the intercomparison was required to provide the following results:

1. power measurements P_1 , P_2 , P_{FWD} , and P_{REV} (see Fig. 5), taken at the time of volume E-field scans. From these measurements, the antenna cable insertion loss could be determined. As much as possible, the laboratories were requested to make measurements at a nominal drive power (P_1) of 200 mW;
2. the measured dielectric properties of the simulant fluid mixed for 900- and 1800-MHz measurements. The IEEE 1528 specifies the accepted methods for dielectric measurement. The most common method used by the various laboratories was the “open-probe” technique, generally using a network analyzer and Agilent Model HP 85070M dielectric probe measurement system;
3. volume E-field/SAR scans on a spatial grid in the simulant;
4. maximum SAR values averaged over a 1- and a 10-m³ cube, which correspond to 1- and 10-g cubes for a fluid with density 1 g/cm³. These measurements were to be made directly from a fine-grid scan in 3-D in the region of the phantom above the antenna feed point;
5. an assessment of the random errors involved in various parts of the measurement protocol;
6. all results from the participating laboratories were supplied to the University of Maryland in “raw” form. No power measurements were corrected for coupler or 30-dB attenuator exact calibrations or for cable insertion loss.

B. Coupler and Attenuator Calibrations

Reported values of P_1 , P_2 , P_{FWD} , and P_{REV} were corrected according to measured values of coupler directionality factors, attenuator attenuation, and cable insertion loss. These values were measured at the University of Maryland on several occasions by several individuals, and the results were averaged. These measurements are summarized in Table I.

From the corrected values of P_{FWD} , P_{REV} , and the cable insertion loss dB_{cable} , the power radiated from the antenna could be calculated as

$$R_{\text{RAD}} = P_{\text{FWD}} 10^{-\alpha} - P_{\text{REV}} 10^{\alpha} \quad (1)$$

where the dimensionless factor α is $\text{dB}_{\text{cable}}/10$. Equation (1) assumes that there is no loss in the antenna and its balun. This equation was used to normalize the results reported by the participating laboratories to units of watt per kilogram, per watt of radiated power.

C. Cable Insertion Loss

Figs. 6 and 7 show the antenna cable loss at 900 and 1800 MHz, measured by the participating laboratories. Each bar graph shows the value measured by each participating laboratory, identified by a code letter A–O. The average (AVG) and tested (T) values (see Table I) from the University of Maryland are also shown in Figs. 6 and 7. Laboratory L did not report all its power measurements, so its cable attenuation factor could not be computed. The error bars show the standard deviation from the mean of the results reported by the participating laboratories.

The average measured loss (mean $\pm$ standard deviation) at 900 MHz was 0.62 ± 0.10 dB, and at 1800 MHz, it was 0.94 ± 0.08 dB, respectively, compared to calibrated values of 0.56 ± 0.08 dB and 0.89 ± 0.10 dB. No laboratory reported measurement more than two standard deviations from the mean, although the degree of variability does indicate the surprising difficulty of making such an apparently simple measurement.

D. Dielectric Measurements

Figs. 8 and 9 show the measured simulant dielectric properties at 900 and 1800 MHz, respectively, together with the average (AVG) and the target (T) values. Error bars were derived as described earlier.

E. E-Field Probe Calibration

The SPEAG E-field probes that we used for measurements come with calibration data and correction factors to allow their use in simulant fluids with different dielectric properties. These probes are calibrated by the manufacturer using a waveguide partly filled with the fluid being used, for example, a WR waveguide at 900 MHz and a WR waveguide at 1800 MHz. The method has been described by Pokovic *et al.* [7]. We verified the calibration of our probe by this method. A section of each waveguide is mounted vertically and fed from a shorted section fitted with a coaxial feed. Halfway up the waveguide section, there is a thin lossless plastic window, and the section of waveguide above this is filled with the simulant fluid. If the forward power (P_{FWD}) and the reverse power (P_{REV}) entering the waveguide are measured, then the SAR as a function of distance z from the window is

$$\text{SAR} = \frac{4(P_{\text{FWD}} - P_{\text{REV}})\exp[-2z/\delta]}{ab\delta\rho} \quad (2)$$

where a and b are the dimensions of the waveguide rectangular cross section, δ is the skin depth in the simulant fluid, and ρ is the fluid density. The skin depth is

$$\delta = \frac{1}{\text{Re}(\gamma)} \quad (3)$$

where γ is the propagation constant in the fluid, which is given by

$$\gamma = \left[\left(\frac{\pi}{a} \right)^2 - \omega^2 \mu_0 \epsilon_0 (\epsilon' - j\epsilon'') \right]^{1/2} \quad (4)$$

where the complex dielectric constant of the fluid is $\epsilon' - j\epsilon''$, and $\epsilon'' = \sigma/\omega\epsilon_0$, where σ is the equivalent conductivity associated with dielectric loss. We have measured the vertical dependence of E-field and the SAR in this way. Figs. 10 and 11 show examples of these calibrations. The E-field and SAR decay is a single pure exponential with distance. Lateral scans of the E-field probe in the waveguide showed a pure TE₁₀ mode in the waveguide, which demonstrates that there is negligible mode conversion from this single mode, even though the dielectric-loaded guide is multimode. The exact conductivity of the simulant can be determined from the measured skin depth. We see small differences, typically 5%, between the SARs calculated from (2) and those measured with SPEAG probe calibration factors. However, much of this discrepancy results from uncertainties in measurements of forward and reflected powers. The precise attenuation factors of the 30-dB dual-directional coupler have only been determined with errors on the order of 0.06–0.27 dB, which lead to errors in the power factor in (2) of up to 7%. We have not, therefore, changed the calibration factors of our probe for SAR measurements, as we feel that further work is necessary to properly verify any discrepancy between the actual and the manufacturer-supplied calibration factors, if any.

The error limits in Figs. 10 and 11 have been determined from a cumulative error analysis based on estimated errors in the skin depth, probe position in the waveguide, forward power, and reflected power.

IV. Results: Volume-Averaged SAR

The most important results from the intercomparison are the maximum SAR values spatially averaged over 1- and 10-cm³ volumes. These were measured by each laboratory by scanning in the phantom. These values are shown in Figs. 12–15. In each case, the results from the various laboratories are shown together with the average value for all laboratories, plus a theoretical value. These theoretical values were computed by the University of Maryland using a rigorous model of the antenna and phantom [8]. The error bars show the standard deviations computed from the results reported by the 15 laboratories participating in the study. The data used in the bar graphs shown in Figs. 12–15 are summarized in Table II, as are the average maximum volume-averaged SARs. These values are based on the raw SAR

and power readings supplied by each laboratory, which have been corrected for cable attenuation, and coupler attenuation factors. The SAR values are normalized to watt per kilogram per watt, assuming simulant fluid densities of 1000 kg/m³. The data supplied have been truncated at two decimal places.

V. Discussion

The maximum spatial SAR values averaged over 1- and 10-cm³ volumes at 900 and 1800 MHz obtained by the 15 laboratories participating in this intercomparison are consistent with the average values listed in Table II. The variations about the mean are generally consistent with random measurement errors with the standard deviations listed in Table II. There is, however, some evidence from the results that there might be procedural systematic errors in a few measurements from the participating laboratories. This can be demonstrated by a statistical analysis of the distribution of reported results. For example, for the maximum spatially averaged SAR for 1 and 10 cm³ at 900 MHz, the distributions of reported results are shown in Figs. 16 and 17, respectively. The 1- and 10-cm³ average results at 1800 MHz are shown in Figs. 18. and 19, respectively. The 1- and 10-cm³ average values obtained by a particular laboratory at 900 or 1800 MHz are strongly correlated. If the 1-cm³ average results at 900 and 1800 MHz are pooled, there are 30 observations in total, with three of these being between 2 and 2.5 standard deviations from the mean. These “outliers” might have resulted from procedural errors. A Monte Carlo simulation of the results expected from a normal distribution shows that the p value for this is $p = 0.073$. This is not statistically significant at the $p = 0.05$ level. In this simulation, we ran multiple sets of 15 experiments with results Gaussian distributed about the observed means and standard deviations to determine whether the observed results could have resulted from chance. Interestingly, there was no uniform pattern regarding which laboratories report measurements more than two standard deviations from the mean. No individual laboratory reports results more than two standard deviations from the mean at both 900 and 1800 MHz. There was no systematic correlation in this study between the results obtained by participating laboratories and the types of probes or scanner that they used.

Based on our experience in making SAR measurements in flat phantoms, we can identify several problems that may arise in these measurements. These can explain the variation of reported results from the participating laboratories:

1. improper cable connection to the antenna. This is strongly suggested by the variability of cable attenuations at 900 and 1800 MHz reported by the laboratories, as shown in Figs. 6 and 7. For example at 900 MHz, these attenuations are 0.62 ± 0.11 dB, and at 1800 MHz, they are 0.94 ± 0.08 dB;
2. improper placement of the antenna under the phantom. Despite the use of a cable strain relief clamp, it is possible for the antenna placement to slip during measurements;
3. failure to use freshly mixed simulant fluid or not stirring this vigorously prior to the measurement. We have measured 5% variations in conductivity in the 900-MHz simulant because of the development of sucrose density gradients in the

phantom. For example, at the bottom of the phantom $\sigma = 0.9$ S/m at 900 MHz, 150 mm vertically upwards $\sigma = 0.95$. These measurements were made by drawing fluid from different locations in the phantom;

4. evaporation of the simulant fluid;
5. errors in measuring forward and reflected powers at the antenna, so the radiated power can be correctly determined.

This last source of error is, in our judgment, a very important one. It is not easy to calibrate the attenuation factors associated with the couplers and attenuators used to better than about 0.1 dB. This alone will lead to an error of about 5% in the SAR values. In addition, there is a cable connection error of about 0.1 dB, and conductivity errors, which come from two sources: random error in conductivity (about 2%) and possible conductivity gradients in the phantom (perhaps as high as 5%). These sources of error can easily lead to an overall error in SAR measurement of about 11%, which is well in line with what was actually observed in the results from the intercomparison, namely an average overall error in volume-averaged SAR of 9%. Although the IEEE 1528 measurement protocol lists many other sources of error, for example, probe positioning, probe calibration, volume averaging, and the effects of boundaries on the probe calibration, it appears that the sources of error described earlier account for much of the variability of the reported measurements from the participating laboratories.

VI. Conclusion

Overall, we feel that the results of the intercomparison are satisfactory, given the diversity of the laboratories involved and the complexity of the measurement procedures. They generally demonstrate the reliability of the SAR measurements carried out in the different laboratories. The measurement system traveled many thousands of miles and was assembled and disassembled many times. On its return to the University of Maryland, all the equipment was still functioning correctly.

Power measurement is the most probable source of uncertainty in these measurements. We recommend that power meters used should be carefully calibrated within specific narrow-frequency bands. Another problematic variable in this intercomparison was the composition of the simulant fluid. Even though the dielectric measurements from the participating laboratories are consistent, it is still difficult to control for fluid evaporation and density gradients. We found that it was not always easy to get all the mixture constituents to dissolve, and often, the dielectric properties of the mixture were outside the range specified in the 1528 measurement protocol. We recommend that if a future comparison is to be made, then it should be carried out on a single component fluid, for example, water or a saline solution, which would be easier to prepare and less susceptible to density gradients, and for which the effects of evaporation would be small. Finally, we recommend uniform, detailed training of the personnel performing the SAR measurements.

Acknowledgments

This work was supported by the Mobile Manufacturers Forum.

The authors would like to thank M. Milligan of the Mobile Manufacturers Forum and would like to acknowledge the help of B. Hakim (University of Maryland). The authors would also like to thank their colleagues from the participating laboratories for their help: D. Altabella (Sony-Ericsson, USA), P. Boutier (Alcatel, France), K. Chan (FCC), J. H. Choi (Samsung, Korea), C.-K. Chou (Motorola, USA), M. Douglas (Motorola, USA), A. Faraone (Motorola, USA), C. Grangeat (Alcatel, France), L. Hamberg (Ericsson, Sweden), G. Hayes (Sony-Ericsson, USA), M. Hinz (Siemens, Germany), Y. Ichino (Telec, Japan), M. Kanda (Motorola, USA), H. Kim (Samsung, Korea), N. Kuster (SPEAG, Switzerland), C. Leray (Sagem, France), P. Oliver (M.D. Anderson Medical Center, formerly with Motorola, USA), T. Onishi (N.T.T. DoCoMo, Japan), K. Osabe (Panasonic, Japan), K. Pokovic (SPEAG, Switzerland), M. Richard (Motorola, USA), P. Sinisalo (Nokia, Finland), M. Swicord (Motorola USA), C. Törnevik (Ericsson, Sweden), S. Tanabe (Mitsubishi, Japan), and H. Wang (T.M.C., Beijing, PRC). The opinions and conclusions stated in this article are those of the authors and do not represent the official position of the United States Food and Drug Administration.

References

1. FCC OET Bulletin 65. Revised Supplement C. Evaluating compliance with FCC guidelines for human exposure to radiofrequency electromagnetic fields. Jun. 2001
2. IEEE Stand. Dec 19. 2003 IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques; p. 1528
3. IEEE Stand. IEEE Recommended Practice for the Measurement of Potentially Hazardous Electromagnetic Fields—RF and Microwave. C95.3-1991
4. Int Electrotechnical Commission Stand. 2005. Methods for the Assessment of Electric, Magnetic and Electromagnetic Fields Associated with Human Exposure. 62209-1
5. *Basic Standard for the Measurement of SAR Related to the Human Exposure to EM Fields from Mobile Phones (300 MHz–3GHz)*, CENELEC EN 50361.
6. Richard, M., Kanda, M., DiNallo, C., Chou, CK. A rugged microstrip tapered balun printed dipole reference for SAR system verification. 2002 IEEE MTT-S Int. Microwave Symp. Dig; Seattle, WA. Jun. 2–7, 2002; p. 1743-1746.
7. Pokovic, K., Schmid, T., Kuster, N. Robust setup for precise calibration of e-field probes in tissue simulating liquids at mobile communications frequencies. Proc. Int. Conf. Applied Electromagnetics and Communications'97; Dubrovnik, Croatia. Oct. 16–17, 1997; p. 120-124.
8. Balzano, Q., Kanda, M., Davis, CC. Specific absorption rates in a flat absorbing phantom in the near-field of dipole antennas. Univ Maryland Inst System Res Rep, TR-2005-35, 2005, [Online]. 2005. Available: <http://www.isr.umd.edu>

Biographies

Christopher C. Davis (SM'82–F'93) received the B.A. degree in natural sciences and the M.A. degree from the University of Cambridge, Cambridge, U.K., in 1965 and 1970, respectively, and the Ph.D. degree on the fundamental processes that occur in gaseous noble gas lasers from the University of Manchester, Manchester, U.K., in 1970.

From 1973 to 1975, he was a Research Associate at Cornell University, Ithaca, NY, working on processes important in chemical lasers. Since 1975, he has been with the University of Maryland, College Park, where he is currently a Professor of electrical and computer

engineering. During 1982–1983, he was a Senior Visiting Fellow at the University of Cambridge. He is the author of *Lasers and Electro-Optics* (Cambridge, U.K.: Cambridge Univ. Press) and the co-author of *Building Scientific Apparatus* (New York: Perseus). His current research interests include optical wireless communication systems, sensor nets, nano-optics, plasmon optics, near-field scanning optical microscopy, fiber sensors, biosensors, and characterization of antennas in the near field.

Dr. Davis is a Fellow of the Institute of Physics and a Member of the Optical Society of America and the Bioelectromagnetics Society.

Brian B. Beard received the B.S. degree from the U.S. Air Force Academy, USAFA, CO, in 1973, in electrical engineering and the M.S. and the Ph.D. degrees from Vanderbilt University, Nashville, TN, in 1993 and 1995, respectively, both in biomedical engineering. His Ph.D. thesis work was based on instrumentation for *in vivo* measurement of cardiac dynamics.

Currently, he is with the U.S. Food and Drug Administration's Center for Devices and Radiological Health, Rockville, MD. His current research interests include RF dosimetry and auditory prosthetics.

Ahlia Tillman received the B.S. degree in electrical engineering from the Rensselaer Polytechnic Institute, Troy, NY, in 2001.

Currently, she is with Raytheon, Waltham, MA, at their Integrated Defense Systems Division.

John Rzasa is a Senior Undergraduate Student at the University of Maryland, College Park, working toward the degrees in electrical engineering and German.

His current research interests include the specific absorption rate of microwave radiation in lossy media.

Eric Merideth received the B.S. degree from the Milwaukee School of Engineering, Milwaukee, WI, in 1999, in electrical engineering, the Diplom-Ingenieur (FH) degree from the Fachhochschule Lübeck, in 1999, in elektrotechnik, and the M.S. degree from the University of Maryland, College Park, in 2001, in electrical engineering. His M.S. thesis work was based on a system for measuring the near field of a dipole antenna and assessing the specific absorption rate in a lossy medium. He is also enrolled at the University of New Hampshire, Durham, studying International Politics in a Master of Public Administration program.

Since 2001, he has been at the Massachusetts Institute of Technology, Lincoln Laboratory, Lexington, where he is currently a Member Associate Staff in the Tactical Defense Systems Group. His current research interests include electronic warfare, counter terrorism, and foreign policy.

Quirino Balzano (S'63–M'72–SM'83–F'02) was born in Rome, Italy, in 1940. He received the Doctorate degree from the University of Rome in 1965 in electronics engineering.

In 1966, he was with FIAT, SpA, Turin, Italy. From 1967 to 1974, he was with the Missile Systems Division, Raytheon Corporation. He was involved in the research and development of planar and conformal phased arrays. In 1974, he joined Motorola, Inc., Plantation, FL, where he was the Corporate Vice President and Director of the Florida Research Laboratories. He retired from Motorola in February 2001 and is currently a Consulting Scientist. Since August 2002, he is with the Department of Electrical and Computer Engineering, University of Maryland, College Park, where he is a Senior Staff Researcher and teaches a graduate course on antennas. His current research interests include the biological effects of human exposure to RF electromagnetic energy. He has authored more than 50 papers on RF dosimetry near electromagnetic sources and the biological effects of RD energy. He is the holder of 27 patents in antenna and IC technology and has authored or co-authored more than 100 publications.

Dr. Balzano was on the Board of Directors of the Bioelectromagnetics Society, which is a scientific society dedicated to the research of the biological effects of electromagnetic fields. He received the IEEE Vehicular Technology Society Paper Prize Award in 1978 and 1982 and a Certificate of Merit from the Radiological Society of North America in 1981 for the treatment of tumors with RF energy. He is the past Chair of the Commission A of the International Union of Radio Science.

Author Manuscript

Author Manuscript

Author Manuscript

Author Manuscript

Fig. 1.
Flat phantom.

Fig. 2.
Dipole antennas for 1800 MHz (left) and 900 MHz (right).

Fig. 3.
Flat phantom in its mounting frame with the antenna cable connected to the primary power coupler and dual-port power meter.

Fig. 4. Nine-hundred-MHz antenna and antenna feed cable in its strain relief clamp shown under the flat phantom.

Fig. 5.
Schematic layout of the antenna drive and power measurement configuration.

Fig. 6.

Measured antenna cable insertion loss at 900 MHz. AVG: Average over laboratories A–O. T: Test value from the University of Maryland.

Fig. 7.
 Measured antenna cable insertion loss at 1800 MHz. AVG: Average over laboratories A–O.
 T: Test value from the University of Maryland.

Fig. 8.

(a) Real part of measured dielectric constant at 900 MHz. Average value 41.55 ± 0.96 . AVG: Average value over laboratories A–O. T: Target value. (b) Conductivity (S/m) measured at 900 MHz. Average value 0.97 ± 0.02 S/m. AVG: Average value over laboratories A–O. T: Target value.

(a)

(b)

Fig. 9.

(a) Real part of measured dielectric constant at 1800 MHz. Average value 39.8 ± 1.1 . AVG: Average value over laboratories A–O. T: Target value. (b) Conductivity (S/m) measured at 1800 MHz. Average value 1.39 ± 0.03 S/m. AVG: Average value over laboratories A–O. T: Target value.

Fig. 10.
Waveguide E-field probe calibration at 900 MHz.

Fig. 11.
Waveguide E-field probe calibration at 1800 MHz.

Fig. 12.
One-cm³ average SAR results at 900 MHz.

Fig. 13.
Ten-cm³ average SAR results at 900 MHz.

Fig. 14.
One-cm³ average SAR results at 1800 MHz.

Fig. 15.
Ten-cm³ average SAR results at 1800 MHz.

Fig. 16.
Distribution of 1-g average SAR measurements at 900 MHz.

Fig. 17.
Distribution of 10-g average SAR measurements at 900 MHz.

Fig. 18.
Distribution of 1-g average SAR measurements at 1800 MHz.

Fig. 19.
Distribution of 10-g average SAR measurements at 1800 MHz.

TABLE I

Coupler and Attenuator Factors

Parameter	dB at 900 MHz	S.D.(dB)	dB at 1800 MHz	S.D.(dB)
30 dB attenuator	30.42dB	0.11	30.49	0.04
Coupler FWD	30.015	0.04	30.39	0.27
Coupler REV	29.66	0.06	29.84	0.11
Cable insertion loss	0.56	0.08	0.89	0.1

TABLE II

SAR Data From 15 Laboratories, With Average Maximum Volume-Averaged SARs and Standard Deviations

Laboratory	SAR Average 900 MHz 1cm ³ W/kg/W	SAR Average 900 MHz 10cm ³ W/kg/W	SAR Average 1800 MHz 1cm ³ W/kg/W	SAR Average 1800 MHz 10cm ³ W/kg/W
A	9.40	6.09	18.92	10.34
B	8.33	5.45	18.78	10.24
C	7.71	5.02	19.78	10.63
D	8.24	5.37	19.98	10.85
E	8.35	5.42	20.39	11.18
F	7.93	5.19	18.50	10.14
G	7.56	4.95	17.93	9.88
H	7.59	5.02	17.11	9.57
I	8.30	5.49	17.02	9.35
J	6.82	4.46	15.96	9.04
K	8.44	5.53	19.56	10.83
L	7.51	5.01	14.89	8.12
M	7.52	4.96	18.09	10.00
N	7.87	5.18	20.78	10.98
O	6.10	4.18	18.97	11.01
Average	7.85	5.16	18.44	10.14
S.D.	0.76	0.45	1.65	0.85