Published in final edited form as:

Concepts Magn Reson Part B Magn Reson Eng. 2017 April ; 47B(2): . doi:10.1002/cmr.b.21356.

250 MHz passive Q-modulator for reflection resonators

Epel Boris, Subramanian V. Sundramoorthy, and Howard J. Halpern

Center for EPR Imaging In Vivo Physiology, Department of Radiation and Cellular Oncology, University of Chicago, Chicago, IL 60637

Abstract

A simple scheme for dynamically switching the quality factor, Q , of a Loop-Gap Resonator (LGR); working at 250 MHz is presented. The addition of this Q-modulator resulted in 30% improvement in Electron Paramagnetic Resonance imager signal-to-noise ratio. During pulse excitation, this scheme lowered the Q , while higher Q was obtained during signal detection. These conditions favored the image acquisition. The Q-modulator is passive; the transition between different states was actuated by the radio frequency power itself.

1. Introduction

Reflection type resonators are commonly used in pulse Electron Paramagnetic Resonance (EPR) instruments; particularly in the EPR imagers [1, 2]. The quality factor, Q , is the ratio of the energy stored and the energy dissipated by a resonator during one cycle of radio frequency power. Typically, the Q of a resonator is kept the same during the measurements. However, there are advantages to dynamically control the Q . During pulse measurements, there are two distinguished time periods. At first, high radio-frequency (RF) power is applied to spin system. Then the low power spin system response is detected. In the case of EPR imaging, the Q is selected based on the required bandwidth for excitation and detection. The imaging magnetic field gradients applied to an object, frequency-encode the object's spatial locations. This results in the increase of the EPR signal bandwidth and demands an adjustment of the imager bandwidth to the object extent [2]. For the uniform excitation of the object frequencies the low Q is optimal (see Table 1). After the excitation, the energy of the RF pulses dissipates from the resonator. Until the stored energy in the resonator is dissipated to the level of the signal, EPR detection is not possible. The time during which the EPR signal detection is impossible is inversely proportional to Q . Thus, lowest Q is beneficial during this period. Finally, during the detection period, Q can be selected as a compromise between signal amplitude proportional to the Q and detection bandwidth, which is reciprocal to the Q . During detection higher Q is beneficial.

In contrast to bimodal resonators where Q of excitation and detection resonators can be set differently, the reflection mode resonators require an electric circuitry to facilitate the Q

manipulations. In this work, we describe a simple device that can alter resonator Q during a pulse sequence. This device switches the resonator's Q passively with the incident power itself, without the need of any external control signal.

2. Passive Q-modulator

Two approaches to alter the Q are possible, either an active externally-timed switching circuit or a passive circuit activated by the incident RF power itself can be employed. Ref. [3] describes a typical scheme for active Q modulation for a 250 MHz bimodal resonator. In this scheme, a diode is connected across the capacitive element of the loop-gap resonator (LGR). The voltage generated by an external switching scheme varies the bias voltage of the diode during excitation and detection. While the diode is in reverse bias mode, the resonator Q is high and when the diode is in the forward conduction mode the Q is spoiled to a much lower value. The timing of the circuit is designed to spoil resonator Q immediately after the pump pulse thus shortening the dead time and to return Q to normal during the detection period. Similar circuits were also published for nuclear magnetic resonance applications [4].

An alternative approach is to use a passive network that does not require external control. Figures 1A and 1B present the electric scheme of an LGR with tuning and matching networks and a passive Q-modulator. The modulator consists of diodes in anti-parallel configuration (D1-D4) and a resistor, R , in series. The unique feature of this modulator is that it provides two defined states with different Q . When high power (>15 dBm) is applied, diodes conduct and effective impedance of the circuit is close to R . When power is below the diodes conducting threshold the impedance of the circuit is the vector sum of resistance R and the reactance of the diodes X_D at the operational frequency. Two serially connected sections of anti-parallel diodes allow to reduce the modulator capacitance and thus reactance X_D and to achieve a larger range of Q modulation. The capacitance of 1N4151 diodes used in this design was ~ 2 pF each. Thus the overall capacitance of the Q-modulator is also ~ 2 pF. The power dissipated in the diodes is rather small. In the case of empty resonator, most of the applied RF power is dissipated in the shunt resistor, which should be chosen accordingly.

In addition to Q , the change in the modulator impedance affects resonator matching. Consequently, two operational modes are possible. In the first mode, the resonator is critically coupled at high power and exhibits low Q . When the power is reduced, the Q of resonator will rise and the coupling required to match the resonator should be lowered. With the critical coupling set during high-power, the resonator becomes slightly over-coupled during detection. In the second mode resonator is critically coupled at low power and exhibits raising the power will reduce the Q and under-couple the resonator at high power (low Q). For our operation, we chose the first mode as it provides the best delivery of excitation power to the resonator in the critically coupled state and highest signal in the over-coupled state. Over-coupling during detection has the advantage of increased signal amplitude compared to the critically coupled resonator with the same Q [5]. The shift of the mismatched resonator frequency was below 0.2 MHz and considerably smaller than the resonator bandwidth.

3. Results

The performance of the modulator was tested using 19 mm loop-gap resonator similar to 16 mm described in Ref. [2] in two different Q ranges that correspond to different EPR imaging conditions. In both cases, the performance was compared with the performance of the same resonator critically coupled and without Q-modulator. For comparison, the equal imaging bandwidths of the resonators were set. The Q of the resonator was adjusted using a shunt resistor. The sample was always installed in the resonator and the modulator was replaced with an appropriate resistor. For measurements we have used a bottle phantom (~1 ml) with the 1 mM solution of OX063H trityl radical, prepared according to Ref. [2]. The Q-modulated resonator was critically coupled during application of 17 dBm of RF power. Agilent 8753ES (Keysight Technologies, Santa Rosa, CA) network analyzer with the high power option (maximum power 18 dBm) was used for our Q measurements.

The results of the measurements are summarized in Table 2. The imaging bandwidth was measured for two pulse spin-echo sequence as a full-width at half-height of spin-echo signal frequency dependence on the magnetic field. The method involves the recording of signal amplitude vs. the magnetic field. The change of the magnetic field alters the EPR resonance frequency and allows probing the imager response at different frequencies. [2] The Q of the resonator during high power critically coupled state is denoted Q_{CC}^H . During testing at low power (−15 dBm) the Q of the resonator is higher and the resonator is slightly over-coupled, with overcoupled Q_{OC}^L . The critically coupled Q_{CC}^L at low power was measured by adjusting the coupling to critical. Note that resonator frequency, during this measurement, was slightly shifted upward.

The dead time of the imager was measured by the observation of the time trace and locating the first time at which undistorted spin-echo signal was observed.

Signal-to-noise (SNR) was determined as the ratio of the maximum spin-echo amplitude to the noise Root Mean Square (RMS) value. For SNR measurements a spin echo time trace averaged from 64000 measurements (16-step CYCLOPS, 4000 traces) was used. SNR presented in Table 2 were normalized to SNR obtained using the resonator without the modulator. One can see that 30% higher SNR was achieved using the Q-modulator in both Q ranges.

The 1N4151 diodes used for this work were found slightly magnetic and produced minor image distortion at the spot adjacent to the diodes. Application of totally non-magnetic diodes is preferable for this design.

4. Discussion and Conclusion

The improvement in imager performance is higher with the larger range of the modulator Q changes. We have found that for 250 MHz imager in the lower Q range, the Q-modulator achieved two-fold change in the Q. In the higher Q range, only about 50% change was achieved. The factor that limits the range of Q changes is the diode's capacitance in an unbiased mode. The capacitive reactance of the diode in this mode is roughly $X_D = (j\omega C_D)^{-1}$, where ω is resonator frequency, and C_D is diodes effective capacitance. To provide good

range of the Q changes, $|X_D|$ has to be comparable or larger than R . Thus the modulation range is governed by the resonator frequency and the diode's capacitance. Considering the availability of diodes with low capacity of p-n junction our design can be useful up to ~1 GHz.

Active and passive Q -modulators have different areas of applicability. For low-power applications, the active modulators are preferable due to their flexibility in choosing the Q -transition time. However, at high RF powers, active Q -modulators require high-power electronics and are harder to build. For these applications, simple and effective passive device presented in this work is a better solution. For EPR imaging applications the Q -modulator presented in this work allowed to achieve 30% improvement in SNR and as such is a useful improvement.

Acknowledgments

We acknowledge our colleagues from the Center for EPR Imaging *In vivo* Physiology and NIH grants P41-EB002034, R01-CA98575 and R50-CA211408.

References

1. Epel B, Sundramoorthy SV, Halpern HJ. Retractable Loop-Gap Resonators for Electron Paramagnetic Resonance Imaging with In Situ Irradiation Capabilities. *Conc Magn Reson B*. 2011; 39B:167–172.
2. Epel B, Sundramoorthy SV, Mailer C, Halpern HJ. A versatile high speed 250-MHz pulse imager for biomedical applications. *Conc Magn Reson B*. 2008; 33B:163–176. DOI: 10.1002/Cmr.B.20119
3. Rinard GA, Quine RW, Eaton GR, Eaton SS. 250 MHz crossed-loop electron paramagnetic resonator for pulsed resonance. *Concept Magnetic Res*. 2002; 15:37–46.
4. Hoult DI. Fast Recovery, High Sensitivity Nmr Probe and Pre-Amplifier for Low-Frequencies. *Rev Sci Instrum*. 1979; 50:193–200. DOI: 10.1063/1.1135786 [PubMed: 18699468]
5. Rinard GA, Quine RW, Eaton SS, Eaton GR, Froncisz W. Relative Benefits of Overcoupled Resonators Vs Inherently Low- Q Resonators for Pulsed Magnetic-Resonance. *J Magn Reson Ser A*. 1994; 108:71–81. DOI: 10.1006/jmra.1994.1090

Figure 1.

A Equivalent electrical scheme of LGR resonator with tune and match elements. M is the Q-modulator circuit. B. Circuit diagram of the Q-modulator.

Table 1

Optimal quality factor during pulse measurement

Pulse measurement period	Optimal Q	Q-dependent parameter
Pulse excitation	Low Q	Excitation bandwidth
Resonator ringing	Very low Q	Resonator ringing
Detection	High Q	Signal amplitude

Author Manuscript

Author Manuscript

Author Manuscript

Author Manuscript

Table 2
Parameters and performance of 250 MHz loop-gap resonator with and without Q-modulator different Q ranges.

Low Q, high bandwidth range					
	R [k Ω]	BW* [MHz]	Q ^H _{CC}	Q ^L _{OC}	SNR _{mod} /SNR _{nomod}
Q-modulator	500	9.1	11	21	1.33
No modulator	750	9	13.5		1

High Q, low bandwidth range					
	R [k Ω]	BW* [MHz]	Q ^H _{CC}	Q ^L _{OC}	SNR/SNR _{nomod}
Q-modulator	1.495	4.8	23	39	1.29
No modulator	1.8	4.8	30		1

Q^L_{CC} is 30. Imager dead time 550 ns.

* $\pi/2$ - π spin-echo pulse sequence, 35 ns pulses with 1:2 amplitude ratio.

Q^L_{CC} is 47. Imager dead time 650 ns.

* $\pi/2$ - π spin-echo pulse sequence, 65 ns pulses with 1:2 amplitude ratio.