Published in final edited form as:

Am J Phys. 2014 July ; 82(7): 708–722. doi:10.1119/1.4869188.

Inexpensive electronics and software for photon statistics and correlation spectroscopy

Benjamin D. Gamari,

Department of Physics, University of Massachusetts, Amherst, Massachusetts 01002

Dianwen Zhang^a,

Department of Physics, University of Massachusetts, Amherst, Massachusetts 01002

Richard E. Buckman,

Department of Physics, University of Massachusetts, Amherst, Massachusetts 01002

Peker Milas,

Department of Physics, University of Massachusetts, Amherst, Massachusetts 01002

John S. Denker,

AT&T Laboratories Research (ret.), Florham Park NJ, 07932

Hui Chen,

Wadsworth Center, New York State Department of Health, 120 New Scotland Ave, Albany, New York 12208

Hongmin Li, and

Wadsworth Center, New York State Department of Health, 120 New Scotland Ave, Albany, New York 12208 and Department of Biomedical Sciences, School of Public Health, State University of New York at Albany, P.O. BOX 509, Albany, New York 12201-0509

Lori S. Goldner^b

Department of Physics, University of Massachusetts, Amherst, Massachusetts 01002

Abstract

Single-molecule-sensitive microscopy and spectroscopy are transforming biophysics and materials science laboratories. Techniques such as fluorescence correlation spectroscopy (FCS) and single-molecule sensitive fluorescence resonance energy transfer (FRET) are now commonly available in research laboratories but are as yet infrequently available in teaching laboratories. We describe inexpensive electronics and open-source software that bridges this gap, making state-of-the-art research capabilities accessible to undergraduates interested in biophysics. We include a discussion of the intensity correlation function relevant to FCS and how it can be determined from photon arrival times. We demonstrate the system with a measurement of the hydrodynamic radius of a protein using FCS that is suitable for the undergraduate teaching laboratory. The FPGA-based electronics, which are easy to construct, are suitable for more advanced measurements as well, and

^bAuthor to whom correspondence should be addressed. lgoldner@physics.umass.edu.

^aPresent address: Beckman Institute for Advanced Science and Technology, University of Illinois at Urbana-Champaign, 405 North Mathews, Urbana, Illinois 61801.

several applications are described. As implemented, the system has 8 ns timing resolution, can control up to four laser sources, and can collect information from as many as four photon-counting detectors.

I. INTRODUCTION

Through techniques such as fluorescence correlation spectroscopy (FCS) and dynamic light scattering (DLS), photon statistics has provided a window into molecular and materials properties for over 40 years. Common to these widely used techniques is the need to rapidly and efficiently collect photons and calculate photon correlation functions with time resolution below 1 μ s. In recent years, high-quantum-yield, low-dark-count photodetectors have become commonplace, lowering the detection limit to a level that makes it possible to routinely observe fluorescence from individual molecules. At the same time, the availability of fast timing circuitry has meant that the arrival time of every detected photon can be determined with high resolution.^{1,2} Detailed information about the photon stream has provided many new opportunities to examine photon statistics.^{1,2} Single-molecule-sensitive fluorescence measurements, which are now revolutionizing our understanding of molecular biophysics, have particularly benefitted from better hardware. High-end commercial instruments¹⁻³ and software^{1,4,5} to evaluate photon statistics are commonly found in biophysics, materials research, and optics laboratories. However, the cost of these systems, which ranges from a few thousand to tens of thousands of dollars, is beyond the reach of nearly all teaching laboratories and many research laboratories. Our intent is to provide inexpensive electronics and open-source software that brings state-of-the-art capabilities for measuring and analyzing photon statistics into the teaching lab while providing a valuable lesson in instrumentation for intrepid students. We include a pedagogical discussion of the intensity correlation function relevant to FCS and its calculation directly from the photon arrival times that constitute the data in most modern instruments. Graduate students or other researchers interested in building or better understanding their own hardware and software may also find this work useful.

The examples and applications described here all involve fluorescence detection. The use of fluorescent dyes to study biological or organic materials is very common, and many students may have at least some experience with staining. Staining often consists of the random intercalation of dyes and is useful mostly for visualization. In molecular biophysics, it is common to modify a specific biomolecule by covalent attachment of a fluorophore (dye molecule). To the extent that the fluorophore's photophysical properties are coupled to the physical motion (including linear and rotational diffusion, folding, twisting, and bending) or the chemical kinetics (binding) of the host biomolecule, the dye can be used as a nanoscopic reporter of these molecular properties. The photons emitted from the fluorophore carry information about the biomolecule that is received by a detector and timing hardware, and decoded by statistical analysis.

In FCS, fluctuations in dye brightness that are coupled to molecular folding or binding can be used to infer the correlation or relaxation times for these processes.⁶ The utility of the

technique arises from the relationship between the diffusivity D and the molecular size, given by the Stokes–Einstein relation,⁷

$$D = \frac{k_B T}{6\pi\eta R_h}, \quad (1)$$

where k_B is Boltzmann's constant, T is the absolute temperature, η is the dynamic viscosity of the medium, and R_h is the hydrodynamic radius of the diffusing particle. In FCS, fluorescent molecules are permitted to diffuse freely through the detection volume (≈ 1 fL) of a confocal microscope. The diffusion time through the volume is determined by the Brownian motion of the particle, which in turn depends on the diffusivity. If the concentration of the fluorophores is sufficiently low, then the largest fluorescence intensity fluctuations occur simply because the average number of molecules in the detection volume fluctuates substantially as molecules diffuse in and out. The typical diffusion time for a molecule to cross the detection volume in a plane perpendicular to the optical axis of the microscope is given by $\tau_D = \omega_0^2/4D$, where ω_0 is the $1/e^2$ radius of the cylindrically symmetric detection volume. This diffusion time is reflected in the correlation function of the fluorescence intensity as a characteristic decay time, discussed in detail in Sec. III. If ω_0 is known, a determination of the diffusion time τ_D using FCS gives D and therefore also R_h using Eq. (1); a specific example is described in Sec. IV A. We note that the use of FCS to observe Brownian diffusion and measure equilibrium constants using a simple instrument was the topic of a previous article in this journal,⁸ which also covered complementary topics such as modeling and fitting the correlation function data.

Until about ten years ago, photon correlation functions were usually generated by hardware designed specifically for this purpose. This process is efficient but costly in terms of information, since no representation of the original photon stream is preserved. Alternatively, a record of the intensity as a function of time can be stored as photon counts detected in sequential time bins; this approach is used in Ref. 8. For photons detected in time bins with widths smaller than $1 \mu\text{s}$, the intensity data can be very sparse. In FCS, it is not unusual for *average* photon count rates to be a few kHz; even with a $1 \mu\text{s}$ bin width, the vast majority of bins will be empty. A better alternative is to record the arrival time of each photon. This method has the distinct advantage of providing the most information about the photon stream in a compact manner. The correlation function, given in FCS by

$$G(\tau) = \frac{\langle I_a(t) I_b(t+\tau) \rangle}{\langle I_a(t) \rangle \langle I_b(t) \rangle} \quad (2)$$

can be calculated directly from the arrival times. Here, I denotes the fluorescence intensity and the subscripts a and b can denote data taken in a single channel (i.e., $a = b$ for autocorrelation) or in different detector channels, corresponding to different colors or polarizations (cross-correlation). Discussions on how to calculate correlation functions from photon arrival times exist in the literature,⁴ but none are accessible at the undergraduate level.

Examples of more advanced biophysical measurements using this system are discussed in Secs. IV B and IV C. In fluorescence resonance energy transfer (FRET), described in Sec. IV B, two different dyes, rather than a single dye, are attached to a biomolecule. Changes in the distance between the dye molecules are recorded as changes in their relative fluorescent intensities, the result of a resonant dipole–dipole interaction. By combining FRET with FCS,⁹ the timescale and nature of fluctuations in molecular structure, occurring on the nanometer length scale, can be determined with a time resolution limited only by the electronics.

To facilitate fast, multi-channel detection, and control of multiple sources for fluorescence excitation (e.g., different wavelength lasers lines to excite different dyes), the electronics are based on a field-programmable gate array (FPGA). Using the FPGA, the electronics are straightforward to construct, as discussed in Sec. II and in the Supplementary Material, and provides an opportunity to explore instrumentation that makes a good bridge for students interested in experimental research. The instrument described has eight input channels, four sequencer outputs for control of the excitation light, and 8 ns timing resolution with no dead time between events. The use of an FPGA ensures design flexibility; notably, the number and configuration of the input and output channels are easily modified to suit different experimental requirements. The FPGA used here costs under \$200. With the required oscillator, connectors, and break-out box, the total cost is less than \$400. The software and firmware necessary to implement and run the device are included in the Supplementary Material.¹⁰

High-end systems (e.g., by Picoquant or Becker & Hickl) that are designed for more demanding time-correlated single-photon counting applications have timing accuracy measured in picoseconds and costs measured in tens of thousands of dollars. Home-built systems based on data acquisition cards such as the National Instruments PCI 6602 can be constructed for about \$2000 but only provide microsecond time resolution.¹¹ A card with 42 ns timing resolution and four input channels is sold by ISS for about \$15,000. None of these systems provide output channels for laser control.

II. INSTRUMENTATION

A. Optics

The minimal optical instrumentation necessary for FCS consists of a confocal microscope, laser, filters, and detector. Rieger *et al.*⁸ give a detailed description, including parts list, for a home-built FCS microscope suitable for use in teaching laboratories that include a laser and a detector for approximately \$6000. An open-frame FCS system kit suitable for both teaching and research applications is currently under development in collaboration with Thorlabs. The cost of this setup including a DPSS laser and detector might be around \$10,000.

The optics used in our experiment are shown schematically in Fig. 1. The excitation light is coupled into the microscope via a single-mode optical fiber, which also serves as a spatial filter in place of the pinhole in Rieger *et al.*⁸ An acousto-optic tunable filter (AOTF, NEOS part number 48058-5-.55) is used to switch between excitation lines but need not be

included in a teaching apparatus that uses a single laser line. A narrow-pass single- or dual-band excitation filter is necessary before the dichroic mirror to eliminate leakage from unwanted laser lines or the diode-pumped solid-state laser pump. The dichroic mirror reflects the excitation light and transmits longer wavelength fluorescence. The telescope after the fiber collimator serves two purposes. First, it works to expand the laser beam diameter to match the size of the back aperture of the objective lens. This ensures that the entire numerical aperture (NA) of the lens is used in focusing the laser beam, thereby minimizing the corresponding focal volume. The telescope also serves to image the first mirror to the back focal plane of the objective, greatly simplifying the alignment of the microscope. The objective used is an Olympus UPlanSApo 60 $\times$ with a NA of 1.2. A high NA water or oil objective is necessary for FCS. The diffraction-limited focal volume of these lenses is typically 1 fL, leading to a similarly small and well-defined detection volume that satisfies the low-background requirements of FCS or single-fluorophore detection.

Fluorescence from the focal (detection) volume of the microscope is collected back through the objective and imaged through a 50- μ m-diameter pinhole. The pinhole size depends on the choice of the objective, the beam diameter, and the focusing lens (tube lens) and is roughly chosen to match the size of the focal spot.¹² The tube lens under the dichroic should be a good achromat to avoid aberrations at the pinhole. The alignment of the instrument with a single detector is discussed in detail in Ref. 8.

In the experiments described here, two detectors are used. In fluorescence correlation spectroscopy (FCS), it is often convenient to use a non-polarizing beamsplitter between the two detectors so that the instrument is arranged in a Hanbury Brown and Twiss configuration (HBT)¹³ with the two detectors sampling the same signal. In this configuration, the cross-correlation is insensitive to detector deadtime and afterpulsing.¹⁴ For example, in a single channel measurement it is not possible to observe correlations below the deadtime of the detectors, which is typically tens of nanoseconds. Below 1 μ s the signal is dominated by detector afterpulsing. In the HBT configuration, photon timing between channels is limited only by the speed of the electronics, which have no intrinsic deadtime.²

The detectors can also be set up for polarization and/or two-color measurements by replacing the non-polarizing beamsplitter with a polarizing beamsplitter or dichroic mirror. The detectors used in our experiments are high-efficiency, low-dark-count, photon-counting modules such as the Hamamatsu's model H7421-40 photomultiplier tube or the Picoquant's τ -SPAD single photon-counting avalanche photodiode. A less expensive alternative, suitable for a teaching laboratory, is the Hamamatsu H10682-110, costing approximately \$1300. All of these units generate TTL level output pulses.

B. Electronics

A schematic of the electronics used in our measurements is shown in Fig. 2. The device is built on the KNJN Xylo EM FPGA development board. This board includes an Altera Cyclone II (EP2C5) FPGA, connected to the host computer through a Cypress FX2 USB interface. No additional hardware or modifications to the Xylo are necessary, although an external crystal oscillator at 32 MHz was installed and multiplied on the chip to 128 MHz to

achieve a timing resolution of 7.8 ns. An overview of the operation of the electronics is described here. Detailed construction information can be found in the Supplementary Material.¹⁰

The hardware records the arrival time of TTL level pulses from up to four photon-counting devices and provides four digital output lines for experimental control. Here the outputs control the acousto-optic tunable filter (AOTF) that is used to switch between excitation wavelengths. For single-line excitation, typically used in a teaching laboratory, the output lines are unused.

The FPGA's firmware¹⁵ is derived from the time-tagging multiple-coincidence detector design developed by Polyakov *et al.*¹⁶ The code was adapted and extended to include additional input channels and digital outputs for experimental control and timing. The firmware is split into two logical blocks: the time tagger and the sequencer.

The time tagger (Tagger in Fig. 2) is responsible for recording the arrival time of events on a set of inputs. The inputs are denoted "delta" and "strobe" and require TTL level signals. Delta inputs capture changes of the digital output channels (sequencer events), while strobe inputs record the photon timing signals. Strobe and delta data types are recorded by the Tagger using the format shown in Fig. 3. The first 36 bits contain the event time in clock cycles, and the higher-order bits contain ancillary information about the event. For strobe events, bits 37–40 indicate the event's originating channel (or channels). For delta events, bits 37–40 record the state of the sequencer immediately after a change. Bit 46 indicates the type of event (strobe or delta). Bits 47 and 48 indicate counter overflows and dropped record events, respectively.

The sequencer module is designed to control laser excitation sources. Each sequencer channel can be programmed to produce a periodic TTL waveform. Sequencer outputs can be used for example to drive the digital input channels of an AOTF, thereby controlling the wavelength of the excitation light. Changes of the sequencer outputs, and therefore of the excitation wavelength(s), are recorded at the delta channel inputs of the event tagger as described above. In this way, output state transitions of the sequencer are captured alongside photon events recorded using the strobe channels. This facilitates the implementation of alternating laser excitation, as described in Sec. IV C. With different electro-optic elements, the strobe channels can also be used in polarization switching or photoactivation.

Software and firmware packages to program and run the electronics on a Linux platform and installation instructions are included in the Supplementary Material.¹⁰ These materials include the necessary firmware (in the packages "timetag-fpga" and "timetag-fx2"), a user interface for experimental control ("timetag-tools"), and data manipulation and analysis tools written in Python and C++ ("photon-tools").

III. CALCULATION OF THE CORRELATION FUNCTION FOR FCS

A. Conceptual overview

The correlation function used in FCS is given by Eq. (2). The intensity $I(t)$ is not usually a continuous function of time but consists of discrete photon arrival events. The *average*

photon count rates in FCS are typically in the range from 1 to 100 kHz. However, the timescale of interest in most measurements is frequently well below 1 ms, and data are acquired with timing accuracies between 1 ps and 1 μ s. The sparsity of the intensity data makes conventional numerical schemes for storing data and performing calculations inefficient. Consider, for example, collecting photon counts for a time T in time bins of width t . For sparse data, the number of bins required (T/t) far exceeds the total number of photons acquired, which is typically of the order 10^6 – 10^8 . In this case, it is more efficient and more informative to record photon arrival times directly.

We begin our conceptual discussion with a conventional discretization of $I(t)$ into an array $I(t_i)$ with T/t elements. The numerator in Eq. (2) can be considered a “lagged dot product.” The meaning of this can be understood with the help of Fig. 4, which illustrates the case where channel a and channel b each have 20 bins. Each matrix element (small square) represents the product $I_a(t_i) I_b(t_j)$. The numerator of Eq. (2) at $\tau = 0$ is represented by summing over the main diagonal in the diagram, for which $j = i$. Similarly, at $\tau = 4$ the numerator is represented by summing along a path parallel to the main diagonal for which $j = i + 4$, as shown in the figure.

The boundary conditions are also illustrated in Fig. 4. We consider three possibilities: periodic boundaries, “dark” boundaries, and “extended” boundaries. In the case of periodic boundaries with 20 elements in each channel (Fig. 4), the evaluation of the numerator in Eq. (2) for a lag of $\tau = 4$ includes both the path at $\tau = 4$ and also the path labeled $\tau = -16$. When using periodic boundaries there will always be T/t squares contributing to the lagged dot product. This simplifies the calculation of the denominator in Eq. (2), since it needs to be calculated only once for a particular choice of bin size. However, $G(\tau)$ calculated with periodic boundaries can sometimes yield unphysical results if $I(t)$ is not periodic and has correlations on timescales that are not much less than T . Periodic boundaries are implicit in the use of a Fourier transformation to calculate the correlation function.

For dark boundary conditions, we include only the path labeled $\tau = 4$ in the calculation of the lagged dot product. As a consequence, the number of contributing squares decreases as the lag increases. The denominator in Eq. (2) should reflect averages over only that part of each intensity that is used in the corresponding numerator, which changes for every τ . The same subset of data that contributes to the numerator in Eq. (2) also contributes to the denominator. In some treatments, the denominator in Eq. (2) is written as $\langle I_a(t) \rangle \langle I_b(t + \tau) \rangle$ to indicate that $\langle I_a(t) \rangle$ is calculated over the range $0 < t_i < T - \tau$ while $\langle I_b(t + \tau) \rangle$ is calculated over the range $\tau < t_j < T$.

For extended boundary conditions, only the data inside of the shaded parallelogram in Fig. 4 is used. The same number of squares, and approximately the same number of photons, are used in each calculation of $G(\tau)$. Data in channel a with $t_i > T - \tau_{\max}$ will not be used at all, where $\tau_{\max}$ is the maximum lag time to be calculated. The subset of data in channel b that contributes to the correlation function changes with each lag time: only data in the window between with $\tau < t_j < T + \tau - \tau_{\max}$ will contribute. The denominator in Eq. (2) does not change systematically with τ , but will fluctuate as the data contributing to the numerator

changes. In a properly designed experiment, $T \gg \tau_{\max}$ and only a small amount of data is unused. Extended boundaries are implemented here.

From Fig. 4, it can be seen that the calculation of the numerator of Eq. (2) requires approximately T/τ calculations at each lag $\tau \ll T$. The number of operations needed to calculate $G(\tau)$ for all τ with a fixed resolution τ therefore scales like $(T/\tau)^2$. The required time can be reduced considerably using a “multi-tau” algorithm,¹⁷ initially introduced for hardware correlators to reduce the number of lag times τ at which to calculate $G(\tau)$. As the spacing between lag times increases, the bin width is also increased, resulting in a calculation that requires only $(T/\tau)\log(T/\tau)$ operations.¹⁷ It is worth noting that a calculation of $G(\tau)$ from the Fourier transform of the power spectrum¹⁸ also scales with $(T/\tau)\log(T/\tau)$ but maintains the original resolution τ between successive τ .

An example of the rebinning necessary to implement a multi-tau algorithm is shown in Fig. 5. Each square contains the product $I_a(t_i) I_b(t_j)$. The correlation function at a given lag is represented by the sum of the matrix elements along a line parallel to the diagonal, with $G(0)$ given by the sum along the diagonal, subject to the chosen boundary conditions. The first eight computations ($0 \leq \tau \leq 7$) use a bin size τ . Starting at $\tau = 8$ the bin size is doubled. By the overlap of small and large squares at $\tau = 8$, it is evident that some of the photons that contributed to the sum for $\tau = 7$ also contribute to $\tau = 8$. This leads to some smoothing of the correlation function at the rebinning boundaries, and will contribute to higher-order correlations that can complicate the analysis of uncertainties. For these reasons rebinning is generally done only once an octave: At $\tau = 16$, the bin size is again doubled to 4τ .

B. Calculation from time tags

It is possible to calculate $G(\tau)$ more efficiently by recognizing and utilizing the sparse nature of the data.⁴ Consider a list of photon arrival times and associated photon counts $\{(t_1, \mu_1), (t_2, \mu_2), \dots, (t_\alpha, \mu_\alpha)\}$, frequently abbreviated as $\{(t, \mu)\}$ with α entries. The arrival times t_i are measured with a precision ℓ that is a multiple of the hardware clock time τ ; for raw data, we have $\ell = \tau$. In this compact representation of the data, the photon count μ_i is always greater than or equal to one. For very sparse data, $\mu_i = 1$ and the number of entries $\alpha = M$, where M is the total number of photons detected. For dense data, the arrival times t_i are sequential and μ_i is just the number of photons in the i^{th} bin. The number of entries in the list is the same as the number of bins $\alpha = N \equiv T/\ell$. If we now consider two such lists $\{(t^a, \mu^a)\}$ and $\{(t^b, \mu^b)\}$, with α and β entries respectively, Eq. (2) can be approximated as

$$G(\tau) = \frac{\frac{1}{N} \sum_{i,j} \mu_i^a \mu_j^b \delta_{t_i, \tau+t_j}}{\frac{M_a}{N} \frac{M_b}{N}}, \quad (3)$$

where $M_a = \sum_i \mu_i^a$ and $M_b = \sum_j \mu_j^b$ are the total number of photons in each list, and δ is the Kronecker delta. The limits on the sum over i and j depend on choice of boundary conditions, as discussed above. We have assumed that the precision with which the time tags are measured is the same in both lists. For sparse data, each computation of this sum requires $M_a + M_b$ calculations (the total number of photons), which can be many orders of

magnitude smaller than T/ℓ . The sum in the numerator of Eq. (3) is the lagged dot product of the discretized intensities, expressed in a compact form. Our implementation of this compact lagged dot product is described by the pseudo-code shown in Fig. 6.

To implement multi-tau analysis,¹⁷ the spacing between lags (ℓ) increases in stages with τ , while ℓ also increases, thus decreasing N . The bin size ℓ is chosen to be sufficiently smaller than τ to obviate the much-discussed triangular error in the approximation of Eq. (2).¹⁹ Our implementation of the rounding (i.e., rebinning) step for a multi-tau analysis is described by the pseudo-code shown in Fig. 7.

The complete calculation of $G(\tau)$ is described by the pseudo-code shown in Fig. 8. The calculation is organized in a series of stages. The minimal time resolution or bin size $\ell = \tau$ is used only for the first 16 possible lag times where $0 \leq \tau \leq 15\tau$. Thereafter, the bin size and the steps in τ are increased by a factor of two at the beginning of each stage. After the first 16 lags, a new stage begins at every doubling of the lag time, i.e., every octave in τ . In each stage except the first, Γ different equally spaced values of τ are evaluated; by default $\Gamma = 8$. After the first 16 lags have been evaluated, the bin size is doubled for the next 8 lag times, $16\tau \leq \tau \leq 30\tau$ ($8 - \tau^g \leq 15$ where τ^g is expressed in units of the new bin size of $\ell = 2\tau$). The bin size continues to double with each octave in τ .

The denominator in Eq. (3) is given by the multiplication of the total number of photons in each compact list divided by N^2 . The total measurement time T of the experiment is usually the same in both channels, in which case $N = T/\ell$ is also the same in both channels. At a given value of the bin size ℓ and for most experimental conditions (i.e., $T \gg \tau_{max}$ and the system in equilibrium), the denominator will change only slightly at each τ (if at all) in a way that depends on the boundary conditions.

C. Calculation of uncertainty in the correlation function

The most straightforward method to find the experimental uncertainty in the correlation function is by calculating the standard deviation of the mean of several measurements.²⁰ Typically, a single data run contains 10^6 – 10^7 photons. Dividing the data into Q consecutive subsets (where typically $Q = 10$), we calculate

$$\sigma(\tau) = \frac{\sqrt{\langle G(\tau)^2 \rangle - \langle G(\tau) \rangle^2}}{\sqrt{Q-1}}, \quad (4)$$

which works as long as $G(\tau) \rightarrow 1$ at long lag times and the sample is in equilibrium (there is no drift in the signal from data subset to data subset).

The statistical uncertainty and bias in $G(\tau)$ has been reviewed and discussed in detail by Saffarian and Elson,²¹ who base much of their discussion on earlier work by Schatzel.^{19,22} A good understanding of the uncertainty in correlation data requires a model of the underlying photophysics of the signal. The calculation of the uncertainty using Eq. (4) does not tell the complete story of uncertainty in the correlation function; in particular, the calculation of the standard deviation does not describe the strongly correlated noise at different lag times that is to be expected at short lags.²³

IV. EXAMPLES

In this section, we describe several measurements performed using the hardware and software described in this paper. The first example, like the examples in Rieger *et al.*,⁸ is suitable for use in a teaching laboratory. The other examples are more advanced to implement, but serve as an introduction to the many other biophysical measurement techniques that are possible with this system. These examples may also be of interest to graduate students and researchers interested in implementing this low-cost system in their laboratories.

A. Measuring the hydrodynamic radius of a fluorescent protein

Fluorescent proteins, which were first isolated from the jellyfish *Aequorea victoria*, have become one of the most ubiquitous probes of protein expression, localization, and transport in living cells.²⁴ Yellow Fluorescent Protein (YFP, molecular mass 27 kDa) can be purchased in lyophilized form from Biovision Inc. Alternately, it can be expressed using the plasmid pEYFP-C1 available through Clontech.

YFP was prepared to a final concentration of 5.0 nmol/L protein in 50 mmol/L glycine (pH = 7) and 0.16 mmol/L Tween 20 detergent. The detergent helps prevent protein aggregation and surface adsorption. The preparation and loading of a sample cell coated with bovine serum albumin (BSA) is described by Rieger *et al.*⁸ The sample is placed on the microscope stage and the focus is positioned approximately 30 μm above the coverslip surface. YFP was excited with the 514 nm line of the Argon-Krypton laser. The line intensity, measured before the objective, was 10 μW . Fluorescence from YFP was detected in a single channel (channel 0) using an APD (Perkin Elmer model SPCM-AQRH-15).

Data were collected using the timetagger's GUI interface, which can be downloaded and installed from the "timetagger tools" package in the Supplemental Materials.¹⁰ Once launched by clicking on the "Timetag UI" icon, the GUI permits a user to set the data acquisition time or to stop and start data acquisition manually. The GUI can also be used to monitor the detector count rates, and it continuously updates the correlation functions during the course of a measurement.

An example of the typical data acquired with this system is shown in Fig. 9(a), where the arrival times of photons at the channel 0 detector are plotted against photon number during a one-second period. A histogram of the time tags in 1 ms bins results in the more familiar plot of intensity (in photons/ms) vs time, shown in Fig. 9(b). The correlation function is generated using the `fcs-corr` command in the `photon tools` package provided in the Supplementary Material¹⁰ and is shown in Fig. 9(c).

As described in Ref. 8, correlation data can often be fit using a model that assumes free diffusion of the fluorophore

$$G_D(\tau) = \frac{1}{n} \left[1 + \frac{\tau}{\tau_D} \right]^{-1} \left[1 + \frac{\tau}{w^2 \tau_D} \right]^{-1/2}, \quad (5)$$

where n is the average number of particles in the detection volume, τ_D is the diffusion time across the rms beam waist, and w is the aspect ratio of the detection volume, which is approximated by a cylindrically symmetric three-dimensional Gaussian with $\omega_0^2 = \omega_z^2 / w^2$ where w is the aspect ratio of the volume and ω_z is the axial radius. Since the correlation data shown here are calculated at shorter lags than possible in Ref. 8, we must also account for the existence of a “dark” state, most likely a photoisomer,²⁵ that gives rise to fluorescence fluctuations on a shorter time scale than particle diffusion. Assuming that transitions in and out of the dark state do not affect diffusion, it is possible to separate the diffusion and photophysical dynamics so that

$$G(\tau) = G_D(\tau) G_{dk}(\tau), \quad (6)$$

where

$$G_{dk}(\tau) = \left[1 - F + F \exp\left(\frac{-\tau}{\tau_{dk}}\right) \right]. \quad (7)$$

Here, F is the probability of finding the molecule in the dark state at equilibrium in the excitation field and τ_{dk} is a kinetic coherence time associated with the buildup of this population.²⁶ Using a calibration measurement, as described in Sec. V B of Rieger *et al.*,⁸ we find $w = 10.3 \pm 3$ and $\omega_0 = 278 \pm 13$ nm for our instrument.

To find the hydrodynamic radius of the protein, we fit Eq. (6) to the data shown in Fig. 9(c), with adjustable parameters n , F , τ_{dk} , and τ_D . For Brownian motion in two-dimensions, the diffusion time is given by $\tau_D = \omega_0^2 / 4D$, from which D can be determined. Using Eq. (1) and propagating the uncertainties in w and τ_D , we find $R_h = k_B T / 6\pi\eta D = 2.29 \pm 0.12$ nm. This is in agreement with the previously reported values for the hydrodynamic radius of the closely related Green Fluorescent Protein (GFP).²⁷

Figure 10 shows the typical data taken for YFP-labeled protein aggregates whose preparation is described in the Supplementary Materials.¹⁰ In this case, the diffusion across the sample volume is slow, and because there are multiple fluorophores in the protein particles, the signal is much brighter. Individual particles can be detected as large bright spikes in Fig. 10(b). It is immediately apparent from the correlation function, shown in Fig. 10(c) with the YFP monomer correlation function, that the diffusion time for these aggregates, with their larger values of R_h , is much larger than the diffusion time for YFP.

B. Dual-channel experiment demonstrating FRET

An example of two-channel data acquired with this system is shown in Fig. 11. The sample used in this measurement is double-stranded DNA that is doubly labeled with a pair of dyes, Cyanine 3 (Cy3) and Cyanine 5 (Cy5), suitable for demonstrating fluorescence resonance energy transfer (FRET). The DNA, which is described in the The DNA, described in the Supplementary Materials,¹⁰ was diluted to 6.6 nmol/L in 20 mmol/L Hepes-NaOH ($pH = 7.5$) and 50 mmol/L NaCl.

FRET describes the non-radiative energy transfer that occurs between an excited dipole (the donor, Cy3 here) and another dipole (the acceptor, Cy5 here) when the absorption spectrum of the acceptor and the emission spectrum of the donor overlap.²⁸ The probability of energy transfer, also called the FRET efficiency E , is dependent on the distance R between two dipoles and can be expressed as

$$E = [1 + (R/R_0)^6]^{-1}. \quad (8)$$

The Förster distance R_0 can be calculated from the spectral properties of the donor and the acceptor and their relative orientation.^{28–30} A typical value of R_0 for freely rotating dyes is 5 nm, making FRET a sensitive “spectroscopic ruler”²⁹ in a small range around R_0 . In two-channel FCS, the presence of FRET results in an anti-correlation between the donor and the acceptor signals that suppresses the amplitude of the cross-correlation: high FRET means the donor signal is suppressed in the presence of the acceptor.

For the data shown in Fig. 11, the donor was excited with the 514 nm line of the Argon-Krypton laser. Excitation power before entering the microscope was nominally 10 μ W. Fluorescence from Cy3 and Cy5 were detected in separate channels using a dichroic mirror between the two detectors in Fig. 1. Data were acquired for 10 min and more than 4.1×10^6 photons in the acceptor channel and 1.6×10^6 photons in the donor channel were collected.

Figure 11(a) shows a typical one-second-long interval of the data, histogrammed in 1 ms bins. Fig. 11(b) shows the auto- and cross-correlation functions for the entire data set. The donor channel autocorrelation is shown as triangles, and the acceptor channel as diamonds. In the absence of the acceptor, unavoidable cross talk from the Cy3 channel into the Cy5 channel results in a correlated signal between these channels. In that case, the auto- and cross-correlations all have approximately the same amplitude, reflecting primarily the concentration of the Cy3 donors. The presence of a FRET pair results in an anti-correlated signal that shows up as a substantially suppressed cross-correlation [squares in Fig. 11(b)]. The cross-correlation is also free of the large detector afterpulsing peak that dominates the autocorrelations for $\tau < 2 \mu$ s.

C. Alternating laser excitation and single-molecule FRET

A more powerful method to measure FRET uses alternating laser excitation (ALEX) of the donor and acceptor dyes, and a low enough sample concentration so that there is never more than one molecule in the detection volume.³¹ Single-molecule-sensitive detection makes it possible to distinguish subpopulations of biomolecules, and ALEX makes it possible to distinguish between low FRET states and the signal that arises from biomolecules with inactive or absent acceptor dyes (“donor-only” signal). To implement ALEX, we used an AOTF to switch between donor and acceptor excitation lines.

ALEX is demonstrated in Fig. 12 using the same doubly labeled DNA used in the experiments described in Sec. IV B, except that the sample is diluted to the point where there is never more than one molecule in the detection volume at a time (50 pmol/L). Cy3 was excited with 514 nm at 205 μ W and Cy5 with 647 nm at 42 μ W. The excitation light was switched every 50 μ s using the sequencer outputs to drive the AOTF. Fluorescence from

Cy3 and Cy5 were detected in channels 0 and 1, respectively. Fluorescence acquired with 514 nm excitation (donor excitation) can be distinguished from 647-nm excitation (acceptor excitation). In Figs. 12(a)–12(c), one second worth of time tags are histogrammed with 1 ms bins. The three separate traces represent (a) donor channel photons during donor excitation, (b) acceptor channel photons during donor excitation (from FRET), and (c) acceptor channel photons during acceptor excitation. Photon bursts representing single fluorescent molecules crossing the detection volume are evident in all three measurements. For each photon (strobe event), the detection channel is recorded by the Channel bits and the excitation source is determined by the state of the Channel bits at the preceding delta event. A total of 663,656 photons were acquired in all three channels during the 465 s of this measurement. ALEX data sets typically contain as many or more delta events from the sequencer as strobe events from the detectors; the two are distinguished by the Record Type bit in the data word (Fig. 3).

The utility of ALEX becomes evident in Fig. 12(d), which shows a scatter plot of the stoichiometry vs proximity ratio.³¹ The stoichiometry is given by the ratio of intensities

$$S = (I_D^A + I_D^D) / (I_D^A + I_D^D + I_A^A), \quad (9)$$

where the subscripts denote the excitation source and the superscripts denote the detection channel: *D* indicates donor and *A* indicates acceptor. The proximity ratio is defined as

$$P = (I_D^A) / (I_D^A + I_D^D) \quad (10)$$

and is related to *E* of Eq. (8), but lacks the corrections for background, cross-talk between the two channels, relative quantum-yields/detector efficiency, and direct excitation of the acceptor that are necessary for a quantitative measurement³¹ of *E*. In Fig. 12(d), *S* and *P* are calculated for all photon bursts with more than 30 photons; the intensities *I* represent the number of photons in any particular burst. A Bayesian inference algorithm is used to find photon bursts directly from time tags,³² but a simpler scheme that applies a threshold to the binned data shown in Figs. 12(a)–12(c) can also be used. The advantage of this two-dimensional representation of the data is that it permits immediate identification of peaks that are associated with a missing or photobleached donor or acceptor dye. Values of *S* near 1 indicate a missing acceptor (donor-only peak), while very low values of *S* correspond to a missing donor (acceptor-only peak). By plotting the data in this way, we immediately see that the low value of *P* with a peak near 0.15 is an artifact of acceptor photobleaching, and not associated with a configuration of the molecule. Figure 6(e) is a histogram of the proximity ratio regardless of *S*; the broad, high *P* peak is what is expected for this flexible oligo.

V. DISCUSSION

A wide variety of fluorescence techniques are now available to study the organization, structure, and structural changes of molecules both in living systems and *in vitro*. Among these, single-molecule-sensitive FCS and FRET, and variations thereof, are arguably the most widely used. While both techniques have been around for many years, the advent and

wide dissemination of single-molecule-sensitive optical instrumentation has ushered in a new era in molecular biophysics. We have presented simple and inexpensive electronics and open-source software that bring state-of-the-art capabilities to both the teaching and research laboratories. By providing outputs for laser control, this system makes it possible to run experiments with multiple dyes in several modalities without any physical changes to the apparatus or reprogramming required. This adds substantially to the information content of the data and simplifies experimental design and control.

In addition to the measurements discussed in Sec. IV, we note that this system can equally well be used in an undergraduate laboratory to measure the kinetics of intermolecular interactions,⁸ perform time-correlated single-photon counting experiments relevant to the fundamentals of quantum mechanics,³³ and study phase transitions or measure particle size via dynamic light scattering.³⁴

Because it accommodates multiple input and output channels, the electronics described in this paper are also useful in the research laboratory. For example, three- and four-color FRET³⁵ with multicolor ALEX³⁶ and coincidence measurements with multiple dyes are straightforward to implement, as is the use of photoactivation. By adding appropriate electro-optic elements, the electronics can be used to switch polarization instead of wavelength, facilitating polarimetric measurements such as are used in rotational studies of single molecules.

The use of an FPGA provides flexibility: with some modification, control channels may also be used to run a scanner for confocal imaging applications. High-end TCSPC systems typically include one or more time-to-digital converters (TDCs) with time resolution as small as a few picoseconds, suitable for applications such as fluorescence lifetime or polarization anisotropy lifetime and demonstrations of anti-bunching. Schemes for an FPGA implementation of a TDC³⁷ can now achieve 6 ps resolution³⁸ and would be the next obvious modification to this system.

Supplementary Material

Refer to Web version on PubMed Central for supplementary material.

Acknowledgments

This work was supported by NSF grant MCB-0920139. The authors thank Dr. Daugherty for the gift of plasmid pYpet-His. Work on the WNV MTase was supported by Grant Nos. AI07079201A1 and AI09433501 from NIH.

References

1. Eid JS, Muller JD, Gratton E. Data acquisition card for fluctuation correlation spectroscopy allowing full access to the detected photon sequence. *Rev. Sci. Instrum.* 2000; 71(2):361–368.
2. Wahl M, Rahn H-J, Gregor I, Erdmann R, Enderlein J. Dead-time optimized time-correlated photon counting instrument with synchronized, independent timing channels. *Rev. Sci. Instrum.* 2007; 78(3):033106. [PubMed: 17411177]
3. Felekyan S, Kuhnemuth R, Kudryavtsev V, Sandhagen C, Becker W, Seidel CAM. Full correlation from picoseconds to seconds by time-resolved and time-correlated single photon detection. *Rev. Sci. Instrum.* 2005; 76(8):083104.

4. Meltzer D, Mandel L. Determination of intensity correlation functions from photoelectric counting distributions. *IEEE J. Quantum Electron.* 1970; 6(11):661–668. Matsumoto G, Shimizu H, Shimada J. Computer-based photoelectron counting system. *Rev. Sci. Instrum.* 1976; 47(7):861–865. Magatti D, Ferri F. 25 ns software correlator for photon and fluorescence correlation spectroscopy. *Rev. Sci. Instrum.* 2003; 74(2):1135–1144. Wahl M, Gregor I, Patting M, Enderlein J. Fast calculation of fluorescence correlation data with asynchronous time-correlated single-photon counting. *Opt. Express.* 2003; 11(26):3583–3591. [PubMed: 19471494]
5. Laurence TA, Fore S, Huser T. Fast, flexible algorithm for calculating photon correlations. *Opt. Lett.* 2006; 31(6):829–831. [PubMed: 16544638]
6. Hess ST, Huang SH, Heikal AA, Webb WW. Biological and chemical applications of fluorescence correlation spectroscopy: A review. *Biochemistry.* 2002; 41(3):697–705. [PubMed: 11790090] Thompson NL, Lieto AM, Allen NW. Recent advances in fluorescence correlation spectroscopy. *Curr. Opin. Struct. Biol.* 2002; 12(5):634–641. [PubMed: 12464316] Widengren J, Rigler R. Review - Fluorescence correlation spectroscopy as a tool to investigate chemical reactions in solutions and on cell surfaces. *Cell. Mol. Biol.* 1998; 44(5):857–879. [PubMed: 9764752]
7. Einstein A. The motion of elements suspended in static liquids as claimed in the molecular kinetic theory of heat. *Ann. Phys.-Berlin.* 1905; 17(8):549–560. Sutherland W. A dynamical theory of diffusion for non-electrolytes and the molecular mass of albumin. *Philos. Mag.* 1905; 9(49–54): 781–785.
8. Rieger R, Rocker C, Nienhaus GU. Fluctuation correlation spectroscopy for the advanced physics laboratory. *Am. J. Phys.* 2005; 73(12):1129–1134.
9. Widengren J, Schweinberger E, Berger S, Seidel CAM. Two new concepts to measure fluorescence resonance energy transfer via fluorescence correlation spectroscopy: Theory and experimental realizations. *J. Phys. Chem. A.* 2001; 105(28):6851–6866. Wallace MI, Ying LM, Balasubramanian S, Klenerman D. FRET fluctuation spectroscopy: Exploring the conformational dynamics of a DNA hairpin loop. *J. Phys. Chem. B.* 2000; 104(48):11551–11555. Joo C, Balci H, Ishitsuka Y, Buranachai C, Ha T. Advances in single-molecule fluorescence methods for molecular biology. *Annu. Rev. Biochem.* 2008; 77:51–76. [PubMed: 18412538] Kuhnemuth R, Seidel CAM. Principles of single molecule multiparameter fluorescence spectroscopy. *Single Mol.* 2001; 2(4): 251–254.
10. The necessary firmware, a user interface for experimental control, data manipulation and analysis tools written in Python and C++, and a description of the samples used in this work are available as supplementary material <http://dx.doi.org/10.1119/1.4869188>. Updates to the software and firmware and a users manual can additionally be found at the author's website at <http://goldnerlab.physics.umass.edu/wiki/FpgaTimeTagger>.
11. Laurence TA, Kapanidis AN, Kong XX, Chemla DS, Weiss S. Photon arrival-time interval distribution (PAID): A novel tool for analyzing molecular interactions. *J. Phys. Chem. B.* 2004; 108(9):3051–3067.
12. Hess ST, Webb WW. Focal volume optics and experimental artifacts in confocal fluorescence correlation spectroscopy. *Biophys. J.* 2002; 83(4):2300–2317. [PubMed: 12324447]
13. Brown RH, Twiss RQ. Correlation between photons in 2 coherent beams of light. *Nature.* 1956; 177(4497):27–29.
14. Zhao M, Jin L, Chen B, Ding Y, Ma H, Chen DY. Afterpulsing and its correction in fluorescence correlation spectroscopy experiments. *Appl. Opt.* 2003; 42(19):4031–4036. [PubMed: 12868844]
15. Gamari B, Goldner LS. FPGATimeTagger. 2011 <<http://goldnerlab.physics.umass.edu/wiki/FpgaTimeTagger>>.
16. Polyakov, SV.; Migdall, A.; Nam, SW. presented at the International Conference on Advances in Quantum Theory; 2010; Vaxjo, Sweden. (unpublished) Polyakov, SV.; Migdall, A.; Nam, SW. FPGA-based multicoincidence recipe and software. 2011. <<http://www.nist.gov/pml/div684/grp03/multicoincidence.cfm>>
17. Schätzel K. Correlation techniques in dynamic light-scattering. *Appl. Phys. B-.* 1987; 42(4):193–213.
18. Chu, B. Light Scattering. 2nd. New York: Academic Press, Inc.; 1991.
19. Schätzel, K. Single-photon correlation techniques. In: Brown, W., editor. *Dynamic Light Scattering: The Method and Some Applications*. Clarendon, Oxford: 1993.

20. Wohland T, Rigler R, Vogel H. The standard deviation in fluorescence correlation spectroscopy. *Biophys. J.* 2001; 80(6):2987–2999. [PubMed: 11371471]
21. Saffarian S, Elson EL. Statistical analysis of fluorescence correlation spectroscopy: The standard deviation and bias. *Biophys. J.* 2003; 84(3):2030–2042. [PubMed: 12609905]
22. Schätzel K, Drewel M, Stimac S. Photon-correlation measurements at large lag times - improving statistical accuracy. *J. Mod. Opt.* 1988; 35(4):711–718.
23. Schätzel K, Peters R. Noise on multiple-tau photon correlation data. *Proc. SPIE.* 1991; 1430:109–115.
24. Tsien RY. The green fluorescent protein. *Annu. Rev. Biochem.* 1998; 67:509–544. [PubMed: 9759496]
25. Schwille P, Kummer S, Heikal AA, Moerner WE, Webb WW. Fluorescence correlation spectroscopy reveals fast optical excitation-driven intramolecular dynamics of yellow fluorescent proteins. *Proc. Natl. Acad. Sci. U. S. A.* 2000; 97(1):151–156. [PubMed: 10618386]
26. Widengren J, Rigler R, Mets U. Triplet-state monitoring by fluorescence correlation spectroscopy. *J. Fluoresc.* 1994; 4:255–258. [PubMed: 24233457]
27. Hink MA, Griep RA, Borst JW, van Hoek A, Eppink MHM, Schots A, Visse Ajwg. Structural dynamics of green fluorescent protein alone and fused with a single chain Fv protein. *J. Biol. Chem.* 2000; 275(23):17556–17560. [PubMed: 10748019] Uskova MA, Borst JW, Hink MA, van Hoek A, Schots A, Klyachko NL, Visser A. Fluorescence dynamics of green fluorescent protein in AOT reversed micelles. *Biophys. Chem.* 2000; 87(1):73–84. [PubMed: 11036971]
28. Clegg RM. Fluorescence resonance energy-transfer and nucleic-acids. *Methods Enzymol.* 1992; 211:353–388. [PubMed: 1406315]
29. Stryer L, Haugland RP. Energy Transfer: A Spectroscopic Ruler. *Proc. Natl. Acad. Sci. U. S. A.* 1967; 58:719–726. [PubMed: 5233469]
30. Forster T. Energiewanderung und fluoreszenz. *Naturwissenschaften.* 1946; 33:166–175.
31. Lee NK, Kapanidis AN, Wang Y, Michalet X, Mukhopadhyay J, Ebright RH, Weiss S. Accurate FRET measurements within single diffusing biomolecules using alternating-laser excitation. *Biophys. J.* 2005; 88(4):2939–2953. [PubMed: 15653725] Kapanidis A, Lee NK, Wang Y, Laurence TA, Doose S, Michalet X, Margeat E, Mukhopadhyay J, Ebright RH, Weiss S. Accurate measurement of-distances and interactions using alternating-laser excitation of single biomolecules. *Biophys. J.* 2005; 88(1):660A–661A.
32. Gamari B, Buckman R, Milas P, Goldner LS. (unpublished).
33. Pearson BJ, Jackson DP. A hands-on introduction to single photons and quantum mechanics for undergraduates. *Am. J. Phys.* 2010; 78(5):471–484.
34. Goldburg WI. Dynamic light scattering. *Am. J. Phys.* 1999; 67(12):1152–1160.
35. Hohng S, Joo C, Ha T. Single-molecule three-color FRET. *Biophys. J.* 2004; 87(2):1328–1337. [PubMed: 15298935] Clamme JP, Deniz AA. Three-color single-molecule fluorescence resonance energy transfer. *ChemPhysChem.* 2005; 6(1):74–77. [PubMed: 15688649] Lee J, Lee S, Ragunathan K, Joo C, Ha T, Hohng S. Single-molecule four-color FRET. *Ang. Chem.-Int. Ed.* 2010; 49(51):9922–9925.
36. Lee NK, Kapanidis AN, Koh HR, Korlann Y, Ho SO, Kim Y, Gassman N, Kim SK, Weiss S. Three-color alternating-laser excitation of single molecules: Monitoring multiple interactions and distances. *Biophys. J.* 2007; 92(1):303–312. [PubMed: 17040983]
37. Kalisz J, Szplet R, Pasierbinski J, Poniecki A. Field-programmable-gate-array-based time-to-digital converter with 200-ps resolution. *IEEE Trans. Instrum. Meas.* 1997; 46(1):51–55. Song J, An Q, Liu SB. A high-resolution time-to-digital converter implemented in field-programmable-gate-arrays. *IEEE Trans. Nucl. Sci.* 2006; 53(1):236–241.
38. Bayer E, Traxler M. A high-resolution (<10 ps RMS) 48-channel time-to-digital converter (TDC) implemented in a field programmable gate array (FPGA). *IEEE Trans. Nucl. Sci.* 2011; 58(4):1547–1552.

Fig. 1.

Schematic of the optics. Obj: objective; AOTF: acousto-optical tunable filter; FPGA: field programmable gate array; det: detector. The photon-counting detectors generate TTL-level pulses whose arrival times are recorded by the FPGA. The FPGA also controls the operation of the AOTF and registers the timing of its state changes.

Fig. 2.

Schematic of the electronics. The device is built on the KNJN Xylo EM FPGA development board. This board includes an Altera Cyclone II (EP2C5) FPGA connected to the host computer through a Cypress FX2 USB interface. The Tagger records the arrival time of photons from up to four detectors on the Strobe channels, and sequencer (Seq) events on the delta channels. The sequencer controls the laser-line switching, if needed, through the AOTF.

Fig. 3.

The data record format. The first 36 bits contain the event time in clock cycles. The higher-order bits of the record contain ancillary information about the event. Bits 37–40 indicate the event's originating channel (or channels) and bit 46 indicates the type of event (strobe or delta). Bits 47 and 48 indicate counter overflows and dropped record events, respectively.

Fig. 4.

Graphical example of the calculation of the lagged dot product in the numerator of Eq. (2) with various boundary conditions. Indices i and j are used to denote specific bins in channel a and b , respectively. Each square contains the product $I_a(t_i) I_b(t_j)$. For dark boundary conditions, the dot product at a given lag is represented by the sum of the matrix elements along a line parallel to the main diagonal. With 20 bins per channel, periodic boundary conditions result in the matrix elements at $\tau = -16$ contributing the dot product at $\tau = 4$. Extended boundary conditions use only those matrix elements inside the shaded region.

Fig. 5.

Graphical representation of the calculation of the lagged dot product with rebinning for conventional, sequentially binned lists. Each square contains the product $I_a(t_i) I_b(t_j)$. The numerator of Eq. (2) at a given lag is represented by the sum of the matrix elements along a line parallel to the diagonal, with $G(0)$ given by the sum along the diagonal itself. Referring to Sec. III B, in this example $\Gamma = 4$ and $\ell = 1$. In the first stage of the calculation, $0 \leq \tau \leq 7$. Starting at $\tau = 8$, the bin size is $\ell = 2$. At $\tau = 16$ the bin size doubles again. The small number of bins and relatively large lag times are used to simplify this example; in a well-

designed experiment $T \gg \tau_{max}$ and only a small portion of the matrix around the diagonal contributes to the signal.

```

DotProduct( $\{(t^a, \mu^a)\}, \{(t^b, \mu^b)\}, \tau_\ell$ )


---


i  $\leftarrow$  1; j  $\leftarrow$  1; dot  $\leftarrow$  0
//  $\alpha$  and  $\beta$  are the lengths of  $\{(t^a, \mu^a)\}$  and
 $\{(t^b, \mu^b)\}$ 
while i  $\leq \alpha$  and j  $\leq \beta$  do
    diff  $\leftarrow t_i^a - (t_j^b + \tau_\ell)$ 
    if diff = 0 then
        dot  $\leftarrow$  dot +  $\mu_i^a \cdot \mu_j^b$ 
    if (diff  $\leq$  0) then i  $\leftarrow$  i + 1
    if (diff  $\geq$  0) then j  $\leftarrow$  j + 1
return dot

```

Fig. 6.

Pseudo-code representing the lagged dot product using a compact representation of the data, $\{(t, \mu)\}$, where the t 's are a list of time tags and the μ 's, which are always 1, are the number of photons arriving in a bin at time t . The list $\{(t^a, \mu^a)\}$ has α elements and the list $\{(t^b, \mu^b)\}$ has β elements. τ_ℓ is a lag time measured in units of the bin width ℓ . The arrow symbol " $\leftarrow$ " is the assignment operator and is often read as "gets."

```

Rebin( $\{(t, \mu)\}$ )      // Input bins of size  $\ell$ 


---


 $(t'_1, \mu'_1) \leftarrow (\lfloor t_1 / 2 \rfloor, \mu_1)$ 
 $j \leftarrow 2$ 
//  $\alpha$  is the length of  $\{(t, \mu)\}$ 
for  $i = 2$  to  $\alpha$  do
    if  $t'_{j-1} = \lfloor t_i / 2 \rfloor$  then
         $(t'_{j-1}, \mu'_{j-1}) \leftarrow (t'_{j-1}, \mu'_{j-1} + \mu_i)$ 
    else
         $(t'_j, \mu'_j) \leftarrow (\lfloor t_i / 2 \rfloor, \mu_i)$ 
         $j \leftarrow j + 1$ 
return  $\{(t', \mu')\}$       // Output bins of size  $2\ell$ 

```

Fig. 7.

Pseudo-code for changing the bin size (which is the same as the resolution of the time tags t) by a factor of two. The symbol “ $\leftarrow$ ” is the assignment operator and is often read as “gets,” while “ $\lfloor \cdot \rfloor$ ” means lower bound. Since the time tags t are integers, a division by two followed by the lower bound operator effectively increases the bin size by a factor of two.

$\text{Correlation}(\{(t^a, \mu^a)\}, \{(t^b, \mu^b)\}, \tau_{max})$

```

 $\Gamma \leftarrow 8$       // Constant: calculations per octave
 $\ell \leftarrow \Delta t$   // bin size
 $\tau_\ell \leftarrow 0$   //  $\tau$  measured in bins
while  $\ell\tau_\ell \leq \tau_{max}$  do
    if  $\tau_\ell = 2\Gamma$  then
         $\{(t^a, \mu^a)\} \leftarrow \text{Rebin}(\{(t^a, \mu^a)\})$ 
         $\{(t^b, \mu^b)\} \leftarrow \text{Rebin}(\{(t^b, \mu^b)\})$ 
         $\ell \leftarrow 2\ell$       // resize bins
         $\tau_\ell \leftarrow \Gamma$     // set  $\tau_\ell$  to octave start
     $G(\ell\tau_\ell) \leftarrow \frac{\text{DotProduct}(\{(t^a, \mu^a)\}, \{(t^b, \mu^b)\}, \tau_\ell)}{N \cdot (M_a/N) \cdot (M_b/N)}$ 
     $\tau_\ell \leftarrow \tau_\ell + 1$ 
return  $G$ 

```

Fig. 8.

Pseudo-code for calculation of Eq. (3) with rebinning as described in the text; τ is a lag time measured in units of the bin width ℓ , and $\leftarrow$ is the assignment operator often read as “gets.” After the first stage of the calculation, $G(\tau)$ is evaluated at Γ different equally spaced values of the lag time τ , ranging from $\Gamma\tau_\ell$ to $(2\Gamma - 1)\tau_\ell$, for each octave in the lag time. Here, $N \equiv T/\ell$, M_a and M_b are the total number of photons in each list, and T is the total time of the measurement, which is presumed to be the same in both channels.

Fig. 9.

Example of a single-channel data set. The sample is YFP at 5 nmol/L as described in the text. (a) A small segment of the 3.2×10^6 photon data set, showing photon arrival time vs photon number for photons arriving between 3 s and 4 s after the start of acquisition. (b) A histogram of the time-tag data shown in (a), displaying the number of photons arriving in each 1 ms bin. (c) Diamonds: correlation function and uncertainties calculated from the full data set. The error bars, which are smaller than the symbols except at short lag, are calculated using Eq. (4). The line is the result of a fit using Eq. (6); the best-fit parameters

are $n = 1.68 \pm 0.02$, $\tau_D = 209 \pm 3 \mu\text{s}$, $\tau_{dk} = 50 \pm 1 \mu\text{s}$, and $F = 0.42 \pm 0.01$. The χ^2 per degree of freedom for this fit is 0.94.

Fig. 10.

Aggregated protein sample. (a) A small segment of a 2.8×10^6 -photon data set, showing photon arrival time vs photon number for photons arriving between 3 s and 4 s after the start of acquisition. (b) A histogram of the time-tag data shown in (a), displaying the number of photons arriving in each 1 ms bin. Here the prominent spikes correspond to individual, very bright protein clumps diffusing through the detection volume. (c) Squares: correlation function calculated from aggregated protein sample, a portion of which is shown in (a) and

(b). Triangles: YFP correlation function from Fig. 9(c) scaled up for comparison with aggregated protein. Lines are corresponding fits of Eq. (6) to the data.

Fig. 11.

Example of dual-channel data. The sample is DNA oligo at 6.6 nmol/L, described in the text. (a) A histogram of the time-tag data, showing the number of photons arriving in each 1 ms bin in a 1 s interval. For clarity, both channels are offset slightly from zero, and the donor channel is plotted inverted. (b) Diamonds: acceptor channel correlation function; Triangles: donor channel correlation function; Squares: cross correlation function. The error bars are calculated using Eq. (4).

Fig. 12.

Demonstration of FRET with ALEX. Panels (a)–(c) are histograms of the time-tag data, showing the number of photons arriving in each 1 ms bin in a 1 s interval: (a) fluorescence in the donor channel with the donor excitation, (b) fluorescence in the acceptor channel with donor excitation, and (c) fluorescence in the acceptor channel with acceptor excitation. The peaks correspond to individual molecules crossing the detection volume of the microscope. (d) A scatter plot of stoichiometry vs proximity ratio. (e) Proximity ratio histogram. The

large peak on the right corresponds to FRET; the smaller peak on the left represents molecules with dark or photobleached acceptors.

Author Manuscript

Author Manuscript

Author Manuscript

Author Manuscript