Published in final edited form as:

Ear Hear. 2016 ; 37(5): e341–e345. doi:10.1097/AUD.0000000000000297.

The effect of microphone placement on interaural level differences and sound localization across the horizontal plane in bilateral cochlear implant users

Heath G. Jones, Alan Kan, and Ruth Y. Litovsky

Waisman Center, University of Wisconsin–Madison, 1500 Highland Avenue, Madison, WI 53705

Abstract

The effect of microphone placement on the interaural level differences (ILDs) available to bilateral cochlear implant (BiCI) users, and subsequent effects on horizontal-plane sound localization were investigated. Presently, microphones are most commonly placed behind the ear (BTE) in adults, and sometimes on the shoulders (SHD) in children. While efforts to position microphones in the ear (ITE) exist, the impact of such placements on sound localization in BiCI users is not well understood. Sound localization was tested for these three microphone placements using virtual acoustic stimuli created from individual acoustic measurements made for each participant and placement. Acoustical analysis revealed a significant reduction in ILDs for BTE and SHD placements compared to ITE placement, which was correlated with a decrease in localization performance.

Introduction

Bilateral cochlear implants (BiCIs) offer spatial hearing benefits over a single implant, such as improved sound localization; however performance remains poor compared to normal hearing (NH) listeners (Grantham et al. 2007; Litovsky et al. 2009; Jones et al. 2014). While NH listeners are able to use both interaural time differences (ITDs) and interaural level differences (ILDs) for sound localization along the azimuth, BiCI users rely predominately on ILDs with limited ITD use (van Hoesel & Tyler 2003; Grantham et al. 2007; Grantham et al. 2008; Aronoff et al. 2010; Dorman et al. 2014). Further complicating matters, speech processor microphones are typically placed behind the ear (BTE), and in children the microphones are also sometimes placed on the shoulders (SHD). Such placements do not capture the natural amplification of the pinna, and potentially reduce the ILDs available compared to a more natural, in the ear (ITE) microphone placement. Additionally, microphone placement has been shown to have a significant impact on the frequency response of signals (Ricketts et al. 2006; Durin et al. 2014; Kolberg et al. 2015). As ILDs result from an interaural comparison of signal amplitudes across frequency, we tested the hypothesis that microphone placement impacts the ILDs available to BiCI users, and subsequently affects sound localization performance.

To date, only one study has examined sound localization abilities in BiCI users for different microphone placements (Frohne-Büchner et al. 2004). This was achieved by using an accessory that places the speech processor microphone partially in front of the ear canal (TMic®, Advanced Bionics). Frohne-Büchner et al. (2004) reported improved sound localization performance for a single BiCI user listening with the T-Mic® compared to the standard BTE placement. The present study included 8 BiCI users, and examined (a) the impact of three different microphone placements (ITE, BTE and SHD) on ILDs, and (b) the impact of each microphone placement on horizontal-plane sound localization. For each participant, acoustic transfer function measurements were used to create individualized virtual acoustic space (VAS) stimuli. This novel approach allowed for the analysis of the acoustic ILDs available to individual participants.

Materials and Methods

Participants and Equipment

Eight post-lingually deafened BiCI users (ages 32-71), fitted with Cochlear® Freedom or N5 processors (see Table I) participated in this study. Participants signed a consent form approved by the University of Wisconsin-Madison Institutional Review Board and were paid for their participation. Acoustic transfer function measurements and localization testing were conducted in the same sound booth (IAC, RS 254S). A Tucker-Davis Technologies (TDT) System 3 was used to select and drive 19 loudspeakers (Cambridge SoundWorks, Newton, MA) hidden behind a dark, acoustically transparent curtain. Loudspeakers were mounted on a semi-circular arc (radius = 1.2 m) at 10° increments between $\pm 90^\circ$ along the horizontal plane. All stimulus presentation and data acquisition was done through the use of custom software written in MATLAB (Mathworks, Natick, MA). Statistical analysis was performed using IBM SPSS Statistics for Windows, Version 22.0 (Armonk, NY: IBM Corp).

Acoustic measurements

For each participant, acoustic transfer function measurements for all 19 loudspeaker locations were made using established head-related transfer function measurement techniques (Møller 1992; Jones et al. 2014). Briefly, participants were seated with their head in the center of the loudspeaker array. Golay codes (200 ms long, 5 repetitions) were used as probe signals, and recorded by a pair of omnidirectional microphones (HeadZap binaural probe microphones, AuPMC002, AuSim, Mountain View, CA) placed either in the ear (ITE), behind the ear (BTE) or on the shoulders (SHD) of participants. Microphone output signals were amplified (MP-1, Sound Devices, Reedsburg, WI) and recorded using a TDT RP2.1 at 48 kHz. For the BTE and SHD placements, the microphones were positioned to face forward.

Interaural Level Difference Analysis

ILDs were derived by computing the difference in the RMS energy between right and left microphone measurements below 8 kHz, for each location (see Fig. 1A). The ILD data were fitted with a four-parameter sigmoid logistic function of the form:

$$ILD(Loc) = y_0 + a / (1 + \exp(-(Loc - Loc_0)/b))$$

were Loc is the speaker location, ILD is the predicted ILD magnitude, y_0 is the function's minimum value, a is the difference between the function's maximum and minimum value, Loc_0 is the midpoint location of the sigmoid, and b is the slope. Metrics of ILD range (dB) and slope (dB/angle) were computed from the ILD function (see Fig. 1B, top panel). The ILD range was defined as the absolute difference between the maximum ILD for left and right hemi-field.

Localization testing

Localization stimuli were a train of 4 pink noise bursts (170 ms each burst, 10 ms inter-stimulus interval), which were digitally processed to simulate free-field presentation using previously described techniques (Wightman & Kistler 1989; Jones et al. 2014). Briefly, individualized virtual acoustic space (VAS) stimuli were created for each microphone placement by passing the train of pink noise bursts through a digital filter constructed from the acoustic transfer functions measurements made for each participant. A new pink noise burst was generated for each presentation prior to being filtered by an acoustic transfer function for a particular location. Stimuli were presented at approximately 60 dB SPL directly to the CI speech processors via the auxiliary port. The overall level of the stimuli was roved (± 4 dB) trial-by-trial, in order to reduce the possibility of localizing spatial locations based on the use of monaural cues (Majdak et al. 2011; Jones et al. 2014; Dorman et al. 2014). Participants used their everyday clinical settings during localization testing.

Prior to testing, the VAS stimulus for the front loudspeaker location (0°) created from the BTE acoustic measurements was presented to the participants in order to ensure acoustical signals were being delivered appropriately. Following this initial presentation, participants confirmed the VAS stimuli being presented to their speech processors via direct connect cables was externalized and at a similar level as free-field presentation. Each microphone condition was fixed within a block of trials, and tested over 3 separate blocks of 95 trials (5 trials $\times$ 19 locations) each, for a total of 15 trials per location per microphone condition. The 9 blocks of trials were randomized so that microphone conditions were interleaved across blocks. On each trial, participants initiated testing by pressing a button on a touch-screen computer monitor, and responses were recorded on a graphical user interface that displayed a continuous arc representing the loudspeaker array. Participants were aware the loudspeakers were not active. It is important to note this was an acute study, thus participants had no experience or training with the novel microphone placements prior to testing.

Results

Average ILD dynamic range and slope values are shown in Fig. 1C and D, respectively. Each ILD metric was analyzed separately as a dependent variable with microphone placement as the independent variable using a one-way, repeated-measures analysis of variance (ANOVA). Results indicated a significant effect for both ILD range [$F(2,23) = 76.49$, $p < 0.001$] and slope [$F(2,23) = 29.87$, $p < 0.001$]. Scheffe's post-hoc analyses revealed

significantly smaller ranges ($p < 0.05$) and slopes ($p < 0.05$) for BTE and SHD placements compared to ITE placements (Fig. 1C and Fig. 1D, asterisks indicate differences). Thus, BTE and SHD placements have two consequences: (a) they do not capture the full range of acoustic ILDs available in the ITE placement, and (b) they reduce the change in the magnitude of ILD when sound sources vary in location along the horizontal plane.

Individual data are shown in Figure 2A (the across-subject average RMS error and standard deviation plotted on the right). The average RMS error for the ITE placement ($25.1 \pm 4.4^\circ$) was lower than the BTE ($28.6 \pm 7.3^\circ$) and SHD ($29.0 \pm 6.5^\circ$) placements. Ricketts et al. (2006) reported a similar effect size for 7 BiCI users listening ‘without’ front-end compression (24.8° RMS error) compared to listening ‘with’ front-end compression activated (29.2° RMS error). To understand the relationship between acoustic ILDs and localization errors, RMS errors for all three microphone placements were plotted against their ILD range (Fig. 2B) and slope (Fig. 2C) metrics. A linear regression analysis revealed a correlation between ILD range and RMS error (Fig. 2B, $\rho = -0.62$, $p < 0.01$), such that larger ILD ranges typically resulted in lower RMS errors. Additionally, there was a correlation between ILD slope and RMS error (Fig. 2C, $\rho = -0.73$, $p < 0.01$), indicating performance was typically better when there was a greater change in ILD magnitude (i.e. steeper slope) as a function of target location angle.

Discussion

The present study examined the effect of microphone placement on the acoustic ILDs available to BiCI users and the subsequent effects on horizontal-plane sound localization. Changes in the acoustic ILDs available across sound source location were quantified from individual acoustic transfer function measurements made for each microphone placement and each participant. Acoustical analysis revealed that ILDs were reduced for BTE and SHD compared to the ITE placement. Localization testing found ITE placement typically resulted in nominally lower overall localization errors compared to the other conditions. The correlational analysis reported here suggest localization performance improves as a result of the increased ILDs provided by the ITE microphone placement. However, it should be noted that the average improvement across the group was small ($\sim 3\text{--}4^\circ$ RMS) and not every participant showed improvement.

The dynamic range of the acoustic ILDs available increased significantly for the ITE compared to BTE and SHD placements (Fig. 1). Additionally, the slope of the ILD functions increased for the ITE placements (Fig. 1D) indicating a greater change in ILD magnitude as sound sources moved from central to lateral locations. Effectively, the ITE placement increases both the range of useable ILDs and the number of discriminable steps across target locations. Given that many BiCI users often have ILD discrimination thresholds on the order of 1-2 dB (Grantham et al. 2008), it was expected that the increased change in ILD magnitudes across target locations would improve sound localization accuracy in BiCI users for an ITE placement of microphones. Similar effects have been previously reported for studies manipulating the availability of acoustic ILDs provided to BiCI users. Ricketts et al. (2006) showed that turning off front-end compression increased ILDs by approximately 7-8 dB for angles around 90° and resulted in an average improvement of 4.4° RMS error

compared to when front-end compression was activated. The acoustical analysis reported here found an increase in ILDs of approximately 6-7 dB for 90° target angles with the ITE compared to BTE placement, and an average improvement of 3.5° RMS error. In a recent study, Dorman et al. (2014) showed average localization performance was significantly degraded, on the order of ~23° RMS error, for BiCI users listening to low-passed filtered signals. The ILDs for these low-pass stimuli were also shown to be further reduced when front-end compression and automatic gain control were simulated. Additionally, localization response patterns of BiCI users were shown to be related to the magnitude of the ILDs available to the listeners (Dorman et al. 2014). Consistent with these findings, we observed a similar correlation between individual ILD metrics and overall localization accuracy across listening conditions.

The present study also observed a high variability in localization performance across participants similar to that reported in the two studies mentioned above (Ricketts et al. 2006; Dorman et al. 2014). Nonetheless, acute testing with an ITE placement resulted in lower average sound localization error along the horizontal plane compared to the other placements for the group tested here. The relatively small sound localization improvement for ITE compared to BTE placement reported here differs from a previous study which reported a difference of ~40° RMS error in a single BiCI user between these two microphone placements (Frohne-Büchner et al., 2004). However, the lower RMS error reported in that study appears to be a result of fewer front-back errors, and not a reduction in lateral errors (see Frohne-Büchner et al. 2004, Fig. 4). In another study using similar techniques as those reported here, Mantokoudis et al. (2011) concluded the placement of ITE microphones improved spatial discrimination on the side of the head by increasing front-to-rear cues compared to BTE placement. The authors verified that acoustic ILDs were only present for an ITE microphone placement and not for the BTE placement (Mantokoudis et al. 2011). Thus, while an ITE microphone placement helps reduce front-back confusions, our data suggest that this placement also has the potential to improve sound localization accuracy for sources along the horizontal plane in the frontal field in some patients.

One important consideration mentioned above is that the automatic gain control (AGC) and front-end compression independently implemented at each ear reduces ILDs (Ricketts et al. 2006; Dorman et al. 2014). Since AGC and front-end compression are necessary components for converting acoustic signals into electrical stimulation and patient comfort, the presented study tested the effect of microphone placement on sound localization with both features left unchanged. As such, the significant correlation between the individual ILD metrics and overall localization accuracy across listening conditions (Fig. 2B and 2C) suggest the difference in ILDs between ITE and BTE placements may be somewhat preserved post compression. Recently, significantly higher speech reception scores in noise were reported for BiCI users using the TMic® accessory compared to the standard BTE (Kolberg et al. 2015) or when presented artificially enlarged ILD magnitudes (Brown 2014). For these studies, the AGC and front-end compression were left on indicating BiCI users were able to make use of the additional cues provided. Thus, it may be the case that BiCI users are able to take advantage of an ITE placement or enlarged ILDs for speech understanding in noise, and to a lesser extent sound localization.

Conclusion

The current BTE microphones that many BiCI users use in everyday life do not capture the full range of acoustic ILDs available, and also reduce the change in cue magnitudes for sound source locations across the horizontal plane. Our findings indicate that while an ITE microphone placement provides a larger range of acoustic ILDs, the availability of these enlarged cues does not translate into lateral sound localization improvements along the horizontal plane for all patients. It is important to note these findings are the result of acute testing with unfamiliar microphone placements and improvements might be observed if patients were allowed prolonged experience or training with the new ILD cues provided by an ITE microphone placement.

Acknowledgements

We would like to thank our bilateral CI research participants who traveled to Madison to participate in these experiments. We would also like to thank Cochlear (Dr. Zachary Smith and Dr. Aaron Parkinson) for technical support and equipment. This study was supported by NIH/NIDCD grants (R01 DC003083 and R01 DC010494) and in part by a core grant to the Waisman Center from the NIH-NICHD (P30 HD03352).

References

- Aronoff JM, Yoon YS, Freed DJ, et al. The use of interaural time and level difference cues by bilateral cochlear implant users. *J Acoust Soc Am.* 2010; 127:EL87–92. [PubMed: 20329812]
- Brown CA. Binaural enhancement for bilateral cochlear implant users. *Ear Hear.* 2014; 35:580–4. [PubMed: 25144252]
- Dorman MF, Loiselle L, Stohl J, et al. Interaural level differences and sound source localization for bilateral cochlear implant patients. *Ear Hear.* 2014; 35:633–40. [PubMed: 25127322]
- Durin V, Carlile S, Guillon P, et al. Acoustic analysis of the directional information captured by five different hearing aid styles. *J. Acoust. Soc. Am.* 2014; 136:818. [PubMed: 25096115]
- Frohne-Büchner C, Büchner A, Gärtner L, et al. Experience of uni- and bilateral cochlear implant users with a microphone positioned in the pinna. *Int. Congr. Ser.* 2004; 1273:93–96.
- Grantham DW, Ashmead DH, Ricketts TA, et al. Horizontal-plane localization of noise and speech signals by postlingually deafened adults fitted with bilateral cochlear implants. *Ear Hear.* 2007; 28:524–541. [PubMed: 17609614]
- Grantham DW, Ashmead DH, Ricketts TA, et al. Interaural time and level difference thresholds for acoustically presented signals in post-lingually deafened adults fitted with bilateral cochlear implants using CIS+ processing. *Ear Hear.* 2008; 29:33–44. [PubMed: 18091105]
- Van Hoesel RJM, Tyler RS. Speech perception, localization, and lateralization with bilateral cochlear implants. *J. Acoust. Soc. Am.* 2003; 113:1617–30. [PubMed: 12656396]
- Jones H, Kan A, Litovsky RY. Comparing sound localization deficits in bilateral cochlear-implant users and vocoder simulations with normal-hearing listeners. *Trends Hear.* 2014; 18:2331216514554574. [PubMed: 25385244]
- Kolberg ER, Sheffield SW, Davis TJ, et al. Cochlear implant microphone location affects speech recognition in diffuse noise. *J. Am. Acad. Audiol.* 2015; 26:51–8. quiz 109–10. [PubMed: 25597460]
- Litovsky RY, Parkinson A, Arcaroli J. Spatial hearing and speech intelligibility in bilateral cochlear implant users. *Ear Hear.* 2009; 30:419–431. [PubMed: 19455039]
- Majdak P, Goupell MJ, Laback B. Two-dimensional localization of virtual sound sources in cochlear-implant listeners. *Ear Hear.* 2011; 32:198–208. [PubMed: 21052005]
- Mantokoudis G, Kompis M, Vischer M, et al. In-the-canal versus behind-the-ear microphones improve spatial discrimination on the side of the head in bilateral cochlear implant users. *Otol. Neurotol.* 2011; 32:1–6. [PubMed: 21131889]

- Møller H. Fundamentals of binaural technology. *Appl. Acoust.* 1992; 36:171–218.
- Ricketts T, Grantham WD, D'Haese P, et al. Cochlear Implant Speech Processor Placement and Compression Effects on Sound Sensitivity and Interaural Level Difference. *J. Am. Acad. Audiol.* 2006; 17:133–140. [PubMed: 16640065]
- Wightman FL, Kistler DJ. Headphone simulation of free-field listening. II: Psychophysical validation. *J Acoust Soc Am.* 1989; 85:868–878. [PubMed: 2926001]

Author Manuscript

Author Manuscript

Author Manuscript

Author Manuscript

Fig. 1.

Interaural level difference (ILD) measurements. A) Acoustic ILDs were derived by computing the difference in the RMS energy between right and left microphone measurements for each location. Color represents the ILD magnitude. B) Mean ILD across frequency plotted as a function of measurement angle. Representation of ILD metrics are also shown in grey. C) The average ILD range (dB) across subjects for each microphone placement. D.) The average ILD slope (dB/angle) across subjects for each microphone placement. Asterisks indicate significant differences revealed from statistical testing and post-hoc analysis ($p < 0.05$).

Fig. 2.

Localization performance. A) Localization data for each BiCI listener across all listening conditions tested. The group average RMS errors and standard deviations are plotted on the far right (bar and error bars, respectively). B) Linear regression analysis found a negative correlation ($\rho = -0.62, p < 0.05$) between dynamic range and overall RMS error, such that smaller ILD dynamic ranges typically resulted in larger RMS errors. C) Linear regression analysis found a negative correlation ($\rho = -0.73, p < 0.05$) between dynamic range and overall RMS error, such that shallower slopes (i.e., smaller change in ILDs as a function of location) typically resulted in larger RMS errors.

Table I

Profile and etiology of BiCI subjects.

Subject	Age	Approx. Age of at Hearing Loss Onset	Years CI Experience (L/R)	Years Bilateral Experience	Etiology
IBX	71	40	3/2	2	Progressive/Sensorineural
IBZ	44	30	5/4	4	Sudden loss/Unknown
ICB	61	9	9/6	6	Progressive/Hereditary
ICF	70	21	1/1	1	Otosclerosis
ICI	54	31	4/3	3	Sudden loss/Unknown
ICJ	63	13	3/3	3	Childhood illness
ICK	69	30	2/1	1	Noise induced
ICO	32	5	1/1	1	Unknown