Published in final edited form as:

J Neurosci Methods. 2006 June 30; 154(1-2): 1–18.

Cell-attached voltage-clamp and current-clamp recording and stimulation techniques in brain slices

Katherine L. Perkins

Dept. of Physiology and Pharmacology, State University of New York, Downstate Medical Center, Brooklyn, New York, USA

Abstract

Cell-attached recording provides a way to record the activity of – and to stimulate – neurons in brain slices without rupturing the cell membrane. This review uses theory and experimental data to address the proper application of this technique and the correct interpretation of the data. Voltage-clamp mode is best-suited for recording cell firing activity, and current-clamp mode is best-suited for recording resting membrane potential and synaptic potentials. The magnitude of the seal resistance determines what types of experiments can be accomplished with a cell-attached recording: a loose seal is adequate for recording action potential currents, and a tight seal is required for evoking action potentials in the attached cell and for recording resting and synaptic potentials. When recording action potential currents, if the researcher does not want to change the firing activity of the cell, then it is important that no current passes from the amplifier through the patch resistance. In order to accomplish this condition, the recording pipette should be held at the potential that gives a holding current of zero. An advantage of cell-attached current clamp over whole-cell recording is that it accurately depicts whether a synaptic potential is hyperpolarizing or depolarizing without the risk of changing its polarity.

Introduction

Cell-attached recording, in which a patch electrode is attached to the cell but the membrane is not broken, has been widely used for recording single channel currents, for recording the summed current of many single channels in a patch of membrane, and for recording spontaneous cell firing activity. In this review I will use theory and new experimental data from neurons in hippocampal slices to discuss three uses of cell-attached recording: 1) the recording of resting and synaptic potentials, 2) the recording of spontaneous cell firing activity, and 3) the stimulation of the attached cell.

Probably the most common use of cell-attached recordings in brain slices is to record spontaneous cell firing activity. This technique is popular because the recordings are easy to achieve, they are stable, and firing activity can be recorded without changing the activity. The use of cell-attached voltage-clamp mode for recording action potential currents was first described by Fenwick et al. (1982) in cultured bovine chromaffin cells. Since then, cell-attached recordings have been used in over 100 papers to record spontaneous action potential currents. A perusal of these papers reveals that many do not report the command potential or seal resistance (R_{seal}) used for the recordings. Apparently, many researchers are unaware that the

telephone: 718-270-2772, fax: 718-270-2241, Email address: kperkins@downstate.edu.

Publisher's Disclaimer: This is a PDF file of an unedited manuscript that has been accepted for publication. As a service to our customers we are providing this early version of the manuscript. The manuscript will undergo copyediting, typesetting, and review of the resulting proof before it is published in its final citable form. Please note that during the production process errors may be discovered which could affect the content, and all legal disclaimers that apply to the journal pertain.

command potential can affect cell firing rate. Among those papers that do report command potential, there is a lack of consensus about the proper potential at which to voltage-clamp the recording pipette in order to record the firing activity of the cell without changing that activity. Some researchers use a 0-mV command potential when recording tight-seal cell-attached because they mistakenly believe this setting does not change the membrane potential of the cell (e.g., Costantin and Charles, 1999). This paper discusses how to set the command potential so that the recording does not change the cell membrane potential. It also explains why a loose seal is adequate for recording spontaneous action potential currents and why voltage-clamp mode, rather than current-clamp mode, is best-suited for recording the firing activity of the cell.

This paper also addresses another use of the cell-attached technique: to evoke action potentials in the attached cell. Fenwick et al. (1982) first demonstrated that command potential can affect the firing rate of the attached cell. Since then, the technique has been underutilized as a method for stimulating cells. This paper demonstrates the method of stimulating the attached cell by commanding a depolarization. It also uses theory and experimental data to address why it is possible to evoke action potentials in some attached cells but not in others.

If the amplifier is switched to current-clamp mode, cell-attached recording can be used to record resting membrane potential and synaptic potentials from neurons in brain slices. A figure showing a cell-attached recording of resting membrane potential from a neuron was published in 2004 (Hayar et al. 2004), but the method was not discussed in that paper. Aside from abstracts (Perkins, 2004; 2005), the recent paper by Mason et al. (2005), which uses non-excitable cells, was the first to discuss the method of cell-attached current-clamp recording of membrane potential. Here I use theory and experimental data to address the conditions necessary for recording resting and synaptic potentials from neurons and discuss how to correctly interpret the data. In particular, I show that cell-attached current-clamp mode, with its ability to record without changing the cell's ionic composition or input resistance, can be used to determine whether a synaptic potential (particularly a GABAergic potential) is depolarizing or hyperpolarizing, and whether a depolarizing synaptic potential is excitatory.

Materials and Methods

Slice preparation

Experiments were done in hippocampal brain slices from adult guinea pigs using animals over a fairly large weight range (180–450 g). The protocol was approved by the Animal Care and Use Committee at SUNY Downstate Medical Center and is in compliance with international guidelines. Guinea pigs were anesthetized with halothane and decapitated with a guillotine. The brain was cut into 2 hemispheres, and one hippocampus was removed. Transverse slices (300 μ m) were cut from the middle third of the hippocampus. Slicing was done in oxygenated, ice-cold solution (same as the extracellular solution detailed below, except 8 mM MgCl_2 and 0.5 mM CaCl_2) using a vibratome (Technical Products International, Inc., St. Louis, MO). Slices were transferred to the holding chamber (Gibb and Edwards, 1987) where they were maintained in extracellular solution continuously perfused with 95% O_2 , 5% CO_2 gas at 31 – 32°C for 1 hour. At 1 hour the holding chamber containing the slices was removed from the heated water bath and allowed to cool to room temperature. Slices were maintained in the holding chamber until ready to record, at which time a slice was placed in the recording chamber.

Extracellular solution

The extracellular solution contained (in mM) 125 NaCl, 25 NaHCO_3 , 2.5 KCl, 1.6 MgCl_2 , 2.0 CaCl_2 , 11 D-glucose. When noted, the solution included 4-aminopyridine (4-AP, 50 μ M),

which causes rhythmic, synchronous giant GABA-mediated postsynaptic potentials (GPSPs) in hippocampal pyramidal cells (Michelson and Wong, 1991; Perkins and Wong, 1996). When noted, the recording solution included the AMPA/kainate ionotropic glutamate receptor antagonist 6-cyano-7-nitroquinoxaline-2,3-dione disodium (CNQX, 10 μ M) and the NMDA receptor antagonist D-(-)-2-amino-5-phosphonopentanoic acid (D-AP5, 50 μ M). The GABA_B receptor antagonist (2S)-3-[[[(1S)-1-(3,4-dichlorophenyl)ethyl]amino-2-hydroxypropyl](phenylmethyl) phosphinic acid (CGP 55845, 1–2 μ M; gift from Ciba-Geigy Ltd., Basel, Switzerland or purchased from Tocris Cookson, Ellisville, MO) was added only when noted. The glutamate antagonists were purchased from Tocris Cookson. Other chemicals were purchased from Sigma-Aldrich (St. Louis, MO).

Cell-attached recording

Slices were submerged during recording in solution perfused with 95% O₂, 5% CO₂ gas at 31° C. Cell-attached recordings were made on pyramidal cells and interneurons using an EPC-7 patch-clamp amplifier (List Electronic) and pClamp software. All interneuron recordings and some pyramidal cell recordings were made using a visualized-cell set-up. The recording chamber for visualized-cell recordings was a modified RC-29 chamber purchased from Harvard Apparatus (Holliston, MA). Cells were visualized using a Nikon upright compound microscope equipped with a 40 $\times$ water-immersion objective and infrared/differential interference contrast optics. Some of the pyramidal cell recordings were made using “blind” recording (Blanton et al. 1989). The recording chamber for “blind” recordings was purchased from Fine Science Tools (Foster City, CA).

Cell-attached recording electrodes were pulled from thin-walled borosilicate glass capillaries, were filled with 150 mM NaCl, and had resistances of 3–7 M Ω . The liquid junction potential (E_{lj}) between the electrode solution and the bath solution was approximately zero because the concentration of the major ions was nearly the same in the electrode solution as in the bath solution. While approaching the cell, positive pressure was applied to the patch electrode. One advantage of using a sodium-based solution in the electrode rather than a potassium-based solution is that it allows the experimenter to clean the cell membrane by blowing solution out of the electrode tip before a seal is attempted, without depolarizing the cell and possibly weakening it. The seal (10 M Ω – > 5 G Ω) between the recording pipette and the cell membrane was obtained by applying suction to the electrode. Action potential currents were recorded in voltage-clamp mode or alternatively in “search” mode, which maintains an average 0 pA holding current. Resting membrane potential and synaptic potentials were recorded in current-clamp mode as described in the RESULTS.

Extracellular field recording

In some experiments, simultaneous DC field recordings were made with glass electrodes placed in CA3 *stratum lacunosum-moleculare* or at the border of *stratum radiatum* and *stratum lacunosum-moleculare*. Field electrodes were filled with 150 mM NaCl and had resistances of 1–2 M Ω . Voltage was recorded with a second EPC-7 amplifier (List Electronic) or a Warner IE-210 amplifier (Harvard Apparatus), and filtered and further amplified with a Warner LPF-100B (Harvard Apparatus).

Body

Part I: Cell-attached current-clamp recording

Is a cell-attached current-clamp recording capable of recording the resting membrane potential of the attached cell? In a recent paper, using both an equivalent circuit and dual recordings from a non-excitable cell, Mason et al. (2005) demonstrated that the voltage measured using a cell-attached recording gets closer and closer to the actual membrane potential of the cell as

the seal resistance gets larger and larger. I will describe the theory behind this experimental finding below. I will demonstrate that if seal resistance (R_{seal}) is $100 \times$ larger than $R_{\text{patch} + \text{cell}}$, the amplifier will accurately measure the cell's resting membrane potential to within 1 mV. In addition, if seal resistance were not this high, but the patch resistance and seal resistance were known, the experimenter could calculate the resting membrane potential from the measured value. However, as I will also explain below, it is impossible to measure separate values for seal resistance and patch resistance in the cell-attached configuration because the two resistances are in parallel. Therefore, knowing the exact resting membrane potential from a cell-attached measurement is not possible. As explained below, we can only know that the resting membrane potential is at least as negative as the measured voltage.

Recording resting membrane potential in current-clamp mode—First of all, how can it be that an electrode on the outside of the cell can record the potential on the inside of the cell? Fig. 1A is a drawing of the simple voltage divider circuit which helps to explain this phenomenon. The battery is the cell's resting membrane potential, in this case, -70 mV. The current is the same across the 3 resistors because they are in series. According to Ohm's law, most of the voltage drop will occur across the highest resistance. If $R_{\text{seal}} = 0 \Omega$, as it would if the electrode were not sealed on the cell, then the -70 mV drop will occur across $R_{\text{patch} + \text{cell}}$, and the voltage at the point labeled V_x on the drawing in Fig. 1A will be 0 mV. If the electrode is sealed on the cell and R_{seal} is infinitely large, then all of the -70 mV drop will occur across R_{seal} . In that case, no voltage drop will have occurred across R_{cell} or R_{patch} , and V_x will equal -70 mV. On the other hand, if $R_{\text{seal}} = R_{\text{patch} + \text{cell}}$, then the voltage at the point labeled V_0 will equal -35 mV, because half of the voltage will drop across $R_{\text{patch} + \text{cell}}$ and half will drop across R_{seal} . Adding an electrode and amplifier to the circuit allows measurement of V_x (Fig. 1C). Because the impedance of the amplifier is so great, no current flows through the electrode to the amplifier, and therefore no voltage drop occurs in that path; the voltage measured by the amplifier is V_x . Thus when $R_{\text{seal}} \gg R_{\text{patch} + \text{cell}}$, the electrode is insulated from the bath potential and accurately measures the cell resting membrane potential (E_m).

An alternative way of looking at the situation, which results in identical equations, is that the voltage at V_x will be a proportional average of the potentials on the two sides of the circuit. For example, if the seal conductance (g_{seal}) is equal to $g_{\text{patch} + \text{cell}}$, the amplifier will measure -35 mV, which is the average of 0 and -70 mV. If $g_{\text{patch} + \text{cell}}$ is larger than g_{seal} , the amplifier will sense the cell membrane potential better than the ground potential, and will measure a value that is closer to -70 mV than it is to 0 mV.

An alternate treatment that gives essentially the same results can be found in Mason et al. (2005). The only differences between the equations presented here and those of Mason et al. (2005) are the inclusion of the cell membrane resistance (R_{cell}) and the liquid junction potential (E_{lj}) between the electrode solution and the bath solution. R_{cell} is included here because Tyzio et al. (2003) and Chavas and Marty (2003) have convincingly described how R_{cell} affects the accuracy of the measured membrane potential in perforated patch and whole-cell recordings when there is a finite R_{seal} . The same reasoning applies to cell-attached recordings. E_{lj} is included in the equations because Barry and Lynch (1991) explain that there is always a liquid junction potential to be considered, even in cell-attached recordings, unless the pipette solution and the bath solution are the same. Before the electrode is sealed onto the cell, this E_{lj} is balanced by an equal and opposite "backoff potential" E_{lj}^* so that the amplifier reads 0 mV (Fig. 1D). The problem is that as the electrode seals onto the cell, E_{lj} remains, but the amplifier is insulated more and more from E_{lj} , so that the two no longer balance out to 0 .

Following are the equations for V_0 , the voltage that would be measured by the amplifier when it is putting out 0 current. The equations are in large part from Tyzio et al. (2003) and Chavas and Marty (2003), except with the addition of R_{patch} and E_{lj}^* .

$$V_0 = E_{ij}^* + \frac{(g_{\text{seal}} \times E_{ij}) + (g_{\text{patch+cell}} \times E_m)}{g_{\text{seal}} + g_{\text{patch+cell}}} \quad \text{equation 1}$$

which is equivalent to

$$V_0 = E_{ij}^* + \frac{(R_{\text{seal}} \times E_m) + (R_{\text{patch+cell}} \times E_{ij})}{R_{\text{seal}} + R_{\text{patch+cell}}} \quad \text{equation 2}$$

which is equivalent to

$$V_0 = \frac{E_m \times R_{\text{seal}}}{R_{\text{seal}} + R_{\text{patch+cell}}} \quad \text{equation 3}$$

, when $E_{ij} = 0$

which is equivalent to

$$V_0 = \frac{(\text{ratio} \times E_m)}{1 + \text{ratio}} \quad \text{equation 4}$$

, when $E_{ij} = 0$, and where $\text{ratio} = R_{\text{seal}}/R_{\text{patch+cell}}$

And thus

$$V_0/E_m = \text{ratio}/(1 + \text{ratio}) \quad \text{equation 5}$$

, when $E_{ij} = 0$ This is the form found in Mason et al (2005), except for the inclusion of R_{cell} in the ratio.

Thus, V_0 will equal 0 mV with a very loose seal, and V_0 will approach E_m with a very tight seal (if $E_{ij}^* = 0$). Note that equations 3, 4 and 5 are valid only when E_{ij} (and thus E_{ij}^*) is zero; E_{ij} would not be 0 when using a typical whole-cell electrode solution.

Fig. 2A was generated using equation 4. It shows the voltage, V_0 , that would be recorded by the amplifier in current-clamp mode for different ratios of $R_{\text{seal}}/R_{\text{patch+cell}}$ if E_m is -70 mV. Fig. 2B is a graph of V_0/E_m vs. $R_{\text{seal}}/R_{\text{patch+cell}}$, which was generated using equation 5. The graphs demonstrate that either increasing R_{seal} or decreasing R_{patch} would give a measured V closer to the actual E_m . As shown on the graph (Fig. 2B), an R_{seal} which is $10 \times R_{\text{patch+cell}}$ gives a measured V which is 91% of actual E_m . An R_{seal} which is $5 \times R_{\text{patch+cell}}$ gives a measured V which is 83% of actual E_m .

In conclusion, we can estimate cell resting membrane potential by measuring voltage in cell-attached current clamp mode. The measurement will always be an underestimate of the actual magnitude of the resting membrane potential, i.e., a measurement of -70 mV means that the resting membrane potential is -70 mV or more negative (as long as E_{ij} is 0). The degree of underestimation depends upon the resistance ratio $R_{\text{seal}}/R_{\text{patch+cell}}$; a larger resistance ratio is associated with a more accurate measurement. In practice, measuring voltage is a quick and easy way to determine the approximate resistance ratio. We know from experience with other recording methods that the resting membrane potential of hippocampal neurons tends to be around -65 or -70 mV. With that knowledge we can use the measured baseline voltage to estimate the resistance ratio $R_{\text{seal}}/R_{\text{patch+cell}}$. For example, the graph in Figure 2A was made assuming an actual resting membrane potential of -70 mV. Using that graph, we can see that if we record a membrane potential more negative than -60 mV, the resistance ratio is likely

greater than 6. Likewise, a measurement of 0 – –1 mV indicates a resistance ratio less than 0.02, and a voltage more negative than –35 mV indicates a likely resistance ratio greater than 1. As will be described below, there are certain experiments (i.e., stimulating the attached cell, recording synaptic potentials that stand out from baseline noise) that can be accomplished only with a resistance ratio greater than 1; therefore, this quick estimate of resistance ratio can be very useful.

Determining the values of R_{seal} and R_{patch} —Why is it that we cannot directly measure R_{seal} and R_{patch} ? Traditionally, the value of R_{seal} has been determined by commanding a step of membrane potential in cell-attached mode and using the equation $\Delta V/\Delta I = R_{\text{seal}}$. This equation assumes that all the current is passing across the seal and none across the patch. In actuality, the ΔI recorded is a combination of the current moving across the seal plus that moving across the patch.

The equation should be $\Delta V/\Delta I = R_{\text{tot}}$, where

$$R_{\text{tot}} = R_{\text{elec}} + (1/R_{\text{patch+cell}} + 1/R_{\text{seal}})^{-1} \quad \text{equation 6}$$

If R_{seal} and $R_{\text{patch+cell}}$, are $\gg R_{\text{elec}}$, then,

$$R_{\text{tot}} = (1/R_{\text{patch+cell}} + 1/R_{\text{seal}})^{-1} \quad \text{equation 7}$$

R_{tot} will be dominated by the *smaller* of $R_{\text{patch+cell}}$ and R_{seal} , because the resistances are in parallel.

If $R_{\text{seal}} \gg R_{\text{patch+cell}}$, and $R_{\text{patch+cell}} \gg R_{\text{elec}}$ then R_{tot} will be roughly equal to $R_{\text{patch+cell}}$, not R_{seal} .

If actual cell resting membrane potential were known, then the exact values of R_{seal} and $R_{\text{patch+cell}}$ could be calculated from R_{tot} and the measured voltage. As an alternative, we can compare the measured voltage to the expected E_m in order to estimate the resistance ratio, as discussed above. For example, consider interneuron #1 in table 1. We recorded a V_0 of –70 mV for this cell. Since the recorded membrane potential is very close to expected E_m , the R_{seal} is many times greater than $R_{\text{patch+cell}}$. Here we estimate R_{seal} is $20 \times R_{\text{patch+cell}}$. In this cell a 70 mV step gave 34 pA of current; therefore,

$$70 \text{ mV}/34 \text{ pA} = R_{\text{tot}}$$

$$R_{\text{tot}} = 2.06 \text{ G}\Omega$$

Using equation 7, $1/R_{\text{tot}} = 1/R_{\text{patch+cell}} + 1/(20 \times R_{\text{patch+cell}})$.

$$R_{\text{patch+cell}} = 2.2 \text{ G}\Omega, \text{ with } R_{\text{seal}} = 43.3 \text{ G}\Omega.$$

Table 1 shows a list of the 18 different neurons recorded with a tight seal. It lists R_{tot} and V_0 for each cell along with a resistance ratio ($R_{\text{seal}}/R_{\text{patch+cell}}$) estimated using the expected E_m of –70 mV and the graph in Fig. 2A. Estimated $R_{\text{patch+cell}}$ values were calculated from R_{tot} and the resistance ratio using equation 7 as above.

What is the effect of the reversal potential of channels in the patch and their open/closed state on measured voltage?— V_0 , the voltage recorded by the amplifier in current-clamp mode, is determined by the membrane potential of the cell, the liquid junction potential between pipette solution and bath solution (0 mV in our case) and the ratio of $R_{\text{seal}}/R_{\text{patch+cell}}$ (see equations 1–4). V_0 depends upon actual voltages, not on the driving force

across channels in the patch. Just as the reversal potential of gramicidin channels or nystatin channels does not need to be taken into account in perforated patch recordings when recording the cell's membrane potential, neither does the reversal potential for the native channels in the membrane patch need to be taken into account when recording membrane potential with tight-seal cell-attached recording. Furthermore, in a current-clamp recording (in contrast to voltage clamp, see Part II), the current is clamped at 0 pA, so that an opening channel will not result in current going from the amplifier through the patch to depolarize the cell.

However, if more channels open in the patch, V_0 will change by moving closer to the cell's actual membrane potential because R_{patch} has decreased. The degree to which V_0 will change depends upon the resistance ratio $R_{\text{seal}}/R_{\text{patch} + \text{cell}}$. Consult Fig. 2A: if the resistance ratio is near 1, we are in the steep part of the curve, and halving the value of the denominator by opening channels in the patch would have a large effect on measured voltage; whereas if the resistance ratio is large, we are in the flat part of the curve, and halving the value of the denominator would not have much effect on the measured voltage. If, for example, the resistance ratio were originally equal to 1, doubling the patch conductance would change measured voltage by 11 mV; whereas, if the resistance ratio were originally equal to 50, doubling the patch conductance would change measured voltage by less than 1 mV (Fig. 3A). The maximal change in recorded voltage with a doubling of patch conductance is found at a resistance ratio of approximately 0.72 (Fig. 3A). Thus, consulting Fig. 2A, maximal instability of measured baseline potential due to channels opening and closing in the patch is expected for recordings with a V_0 around -30 mV.

This effect of channels opening and closing on the stability of measured voltage has been observed in our recordings. When the measured resting voltage is in the -20 to -45 mV range, the measured baseline potential is often unstable. However, when the seal improves during the same recording, as evidenced by the measurement of a more negative resting membrane potential, the baseline potential is often quite stable (Fig. 3B), even when channel openings and closings can be observed in that patch in voltage-clamp mode.

Synaptic potentials can be recorded in tight-seal cell-attached current-clamp mode—Synaptic potentials can be recorded in tight-seal cell-attached current clamp mode (Fig. 4). For these experiments, 4-aminopyridine (4-AP) was used to elicit synchronous activity in the hippocampal slice. A cell-attached recording and a field recording were used simultaneously in order to record the activity of the attached cell during the population activity revealed by the field electrode. Fig. 4 shows that the CA1 pyramidal cell received a depolarizing synaptic potential during the glutamate-mediated population event and a hyperpolarizing synaptic potential during the GABA-mediated population event. Further discussion of the recording of synaptic events can be found in Part III.

Part II: Cell-attached voltage-clamp mode

This paper began with a discussion of cell-attached current-clamp recording. What about the more popular cell-attached voltage-clamp recording? Cell-attached voltage-clamp recording can be used to record the firing activity of the cell without changing that activity. Cell firing activity is recorded in the form of action potential currents, with the amplifier in voltage-clamp mode (Fig. 5). Cell-attached recording of action potential currents is an easy type of recording to do because no breaking of the patch is involved, and the seal can be loose (< 1 G Ω ; (Kondo and Marty, 1998); see explanation in Part III). The recordings are usually quite stable and can last for hours. It is important to realize that cell-attached voltage-clamp mode is not designed to, and indeed does not, voltage-clamp the cell. Another very important point is that you cannot simply assume that the recording is not affecting the activity of the cell – using the correct command voltage is imperative.

What is the correct command voltage to use when you want to record spontaneous firing activity in cell-attached voltage-clamp mode?—Using the wrong command potential for a cell-attached recording of firing activity can change the very activity you are attempting to record. The key to this issue is that the amplifier can generate current in voltage-clamp mode, and some of this current will pass across the patch. Current that passes from the amplifier across the patch of membrane and into the cell must then leave the cell by passing across the cell membrane resistance (Fig. 6). This current passing across the cell membrane resistance will depolarize the cell. This phenomenon has long been recognized by researchers who record single channel currents in cell-attached mode (Barry and Lynch, 1991; Sherman-Gold, 1993), but has been largely ignored by researchers doing cell-attached recordings of cell firing activity.

For recording spontaneous firing activity in cell-attached voltage-clamp mode, the cell membrane potential should be unaffected by the recording itself, and thus the command potential should be the potential at which no current is flowing from the amplifier through the patch. Although a command potential of 0 mV does not depolarize the patch itself, it is not the correct potential to use for tight-seal cell-attached recordings when you do not want to depolarize the cell. Instead, the correct command potential is the command potential at which the amplifier current, I_{amp} , is at 0 pA. The command potential which gives an I_{amp} of 0 pA is V_0 . The voltage, V_0 , which gives 0 pA of current is the same potential the amplifier would measure in a 0-pA current-clamp recording (Fig. 7). Thus, the correct command potential, V_0 , depends upon the ratio of $R_{seal}/R_{patch + cell}$, as already demonstrated in Fig. 2. For example, as shown in Fig. 2A, the correct command potential would be essentially equal to E_m when $R_{seal} \gg R_{patch + cell}$, and would be equal to -35 mV for a recording in which $R_{seal} = R_{patch + cell}$.

When recording spontaneous firing activity in cell-attached mode with a tight seal, the command potential is very important; it must be set to V_0 lest you change the membrane potential of the cell and thus cell firing rate. V_0 is simple to determine: it is simply the command potential at which the amplifier reads zero current. With very loose seals, the command potential is less important, because even if the amplifier generates current, most of the current will leak across the seal rather than passing across the patch (discussed below).

Stimulation of attached cell in voltage-clamp mode—When recording cell-attached from a neuron in the hippocampal slice with the amplifier in voltage-clamp mode, the command potential can affect the firing rate of the attached cell (Fig. 8). When recording with a tight seal, depolarization of the attached cell can be achieved by commanding a depolarizing voltage step, (and hyperpolarization of the attached cell can be achieved by commanding a hyperpolarizing voltage step). Because stimulation of the attached cell is achieved in voltage-clamp mode, the resulting action potential current can be easily recorded.

How does commanding a pipette voltage (V_p) more depolarized than V_0 depolarize the attached cell? Clearly, the cell does not reach the commanded voltage. The answer is that the amplifier measures V_0 (as defined above), and commands the necessary current to change the pipette potential from V_0 to the command potential V_p . Current which passes from the amplifier through the patch into the cell exits the cell across the cell's membrane resistance and thus depolarizes the cell's membrane potential. For example, if the cell's membrane potential is -70 mV and the seal resistance is infinitely large, the amplifier will measure the -70 mV. If the command potential is -70 mV, then the amplifier does not pass any current, and the cell will not be depolarized. However, with that same tight seal, the amplifier would need to pass current to reach a command potential of 0 mV, and the cell would be depolarized.

By how much was the interneuron in Fig. 8A depolarized at $V_p = 0$ mV? Fig. 6 shows the circuit that must be considered. The patch resistance and the seal resistance are in parallel, in this case. I_{amp} is the current produced (and measured) by the amplifier. I_{amp} will split, and part of the current (I_{seal}) will travel across R_{seal} to ground, and part of the current (I_{patch}) will flow across the patch into the cell and out of the cell across the cell's membrane resistance to ground. $I_{amp} = I_{seal} + I_{patch}$ and $I_{patch} = I_{cell}$. For the recording shown in Fig. 8A, 34 pA of current was recorded at a command pipette potential of 0 mV. $34 \text{ pA} = I_{amp} = I_{patch} + I_{seal}$. In order to determine how much the cell was depolarized, we first need to know what portion of I_{amp} went across the patch. If $R_{seal} \gg R_{patch} + R_{cell}$, then $I_{patch} \approx I_{amp}$ because virtually no current would leak across the seal. The V_0 for this recording was -70 mV. Recording such a negative V_0 indicates that the $R_{seal}/R_{patch+cell}$ ratio was very high for this cell. Thus, at steady-state (after capacitances were fully charged): 34 pA of current passed through the patch and 34 pA of current passed through R_{cell} . If $R_{cell} = 200 \text{ M}\Omega$, then cell membrane potential was depolarized by $34 \text{ pA} \times 200 \text{ M}\Omega = 6.8 \text{ mV}$.

Commanding a depolarizing voltage step can be used to stimulate a “quiet” cell to make it fire action potentials, which are recorded as action potential currents (Fig. 8). The technique has been very successful with CA1 and CA3 interneurons: 9/9 interneurons recorded in tight-seal cell-attached voltage-clamp mode could be stimulated by commanding a depolarizing voltage step (Table 1).

Determining the values of I_{patch} and I_{seal} —How do we determine the value of I_{patch} ? We know that $I_{amp} = I_{patch} + I_{seal}$. If $R_{seal} \gg R_{patch+cell}$, then $I_{patch} \approx I_{amp}$. However, what if R_{seal} is not $\gg R_{patch+cell}$?

The equations are derived as follows:

We can begin with Ohm's law:

$$\Delta V_p = \Delta I_{amp} \times R_{tot}$$

(R_{tot} is defined in equation 6).

We can replace ΔV_p with $V_{p1} - V_{p2}$ and ΔI_{amp} with $I @ V_{p1} - I @ V_{p2}$

Then we can set V_{p2} at V_0 , which is the pipette voltage at which $I_{amp} = 0$.

Now we have

$$V_p - V_0 = (I_{amp} - 0) \times R_{tot}$$

$$V_p - V_0 = I_{amp} \times R_{tot}$$

$$I_{amp} = (V_p - V_0) / R_{tot} \quad \text{equation 8}$$

Note that $I_{amp} = 0$ when $V_p = V_0$.

If I_{seal} and I_{patch} both equal 0 when I_{amp} is 0, and given that the potential difference across parallel branches of a circuit are equal:

$$(V_p - V_0) - (I_{amp} \times R_{elec}) = (I_{patch} \times R_{patch+cell}) \text{ and}$$

$$(V_p - V_0) - (I_{amp} \times R_{elec}) = (I_{seal} \times R_{seal}), \text{ therefore}$$

$$I_{\text{patch}} = \frac{(V_p - V_0) - (I_{\text{amp}} \times R_{\text{elec}})}{R_{\text{patch} + \text{cell}}} \quad \text{equation 9}$$

and

$$I_{\text{seal}} = \frac{(V_p - V_0) - (I_{\text{amp}} \times R_{\text{elec}})}{R_{\text{seal}}} \quad \text{equation 10}$$

If we look at the voltage-clamp amplifier as a current generator generating I_{amp} , the current will take the path of least resistance:

$$I_{\text{patch}} = I_{\text{amp}} \times g_{\text{patch} + \text{cell}} / (g_{\text{patch} + \text{cell}} + g_{\text{seal}}) \quad \text{equation 11}$$

$$I_{\text{seal}} = I_{\text{amp}} \times g_{\text{seal}} / (g_{\text{patch} + \text{cell}} + g_{\text{seal}}) \quad \text{equation 12}$$

(Equations 11 and 12 give identical values of I_{patch} and I_{seal} as equations 9 and 10.) Also note that equation 11 converts to

$$I_{\text{patch}} / I_{\text{amp}} = g_{\text{patch} + \text{cell}} / (g_{\text{patch} + \text{cell}} + g_{\text{seal}}) \quad \text{equation 13}$$

, which is equivalent to

$$I_{\text{patch}} / I_{\text{amp}} = \text{ratio} / (1 + \text{ratio}), \quad \text{equation 14}$$

, where $\text{ratio} = R_{\text{seal}} / R_{\text{patch} + \text{cell}}$

Therefore, a greater proportion of I_{amp} will go through the patch rather than the seal as $R_{\text{seal}} / R_{\text{patch} + \text{cell}}$ increases (Fig. 9). Note the similarity between equation 14 and equation 5. $I_{\text{patch}} / I_{\text{amp}}$ depends upon the resistance ratio in exactly the way that V_0 / E_m depends upon the resistance ratio; therefore, the plots in Fig. 9 and Fig. 2B are identical.

What factors affect the ability to depolarize the cell in cell-attached voltage-clamp mode?—The keys to depolarizing the cell in cell-attached voltage-clamp mode are 1) the amount of current passed across the patch and 2) the cell's input resistance, R_{cell} . The current which travels across the patch into the cell must exit the cell across the cell membrane resistance in order to complete the circuit. Current passing out across the cell membrane resistance will depolarize the cell: the change in cell membrane potential (ΔV_m) equals $I_{\text{patch}} \times R_{\text{cell}}$.

First of all, in order to depolarize the cell, current has to cross the patch. The amount of current passed across the patch is dependent upon the magnitude of I_{amp} and the resistance ratio (equation 14). Thus, I_{patch} depends upon V_p , R_{seal} , and $R_{\text{patch} + \text{cell}}$. Fig. 10 shows plots of I_{patch} vs. V_p for 3 different values of R_{seal} . If 20 pA of I_{patch} were required in order to make the cell fire an action potential, then V_p would have to be depolarized to -24 mV for $R_{\text{seal}} = 20 \text{ G}\Omega$, +5 mV for $R_{\text{seal}} = 2 \text{ G}\Omega$, and over +160 mV for $R_{\text{seal}} = 0.2 \text{ G}\Omega$.

Not only do seal resistance and V_p affect the amount of current passed across the patch, R_{patch} will also affect the amount of current passed across the patch – a lower R_{patch} gives a larger I_{patch} . Recordings with a higher R_{patch} will require a higher R_{seal} or a more depolarized V_p in order to pass the same amount of current across the patch.

Note in Fig. 10 that the R_{patch} is not constant with decreasing R_{seal} . A constant R_{patch} of 2 $\text{G}\Omega$ would predict that with a seal of 0.2 $\text{G}\Omega$, a depolarization to +35 mV would be sufficient to pass 20 pA across the patch and stimulate action potentials. In contrast, in our experiments,

we were unable to pass enough current across the patch to excite cells if R_{seal} was less than 1–2 G Ω . In addition, the size of action potential currents did not correspond to the theoretical if a stable R_{patch} was assumed (see further discussion in Part III). Instead, the data are better fit if R_{patch} decreases as R_{seal} increases from approximately 200 M Ω to approximately 2 G Ω . A logical explanation for the changing R_{patch} is that the surface area of the patch of membrane increases as R_{seal} increases. When the electrode is merely touching the cell, the area of the patch of membrane within the electrode tip will be well-approximated by the area of a circle, πr^2 . However, as the seal increases, membrane is pulled into the electrode tip to form a three-dimensional omega-shaped patch of membrane whose area can be roughly approximated using the surface area of a sphere, $4\pi r^2$. It would not be unreasonable, then, to expect R_{patch} to decrease by four-fold as a tight seal is formed.

Fig. 11A illustrates that a positive I_{amp} depolarizes the cell, and that a greater R_{seal} results in a greater depolarization. The depolarization will be bigger with a larger R_{seal} because more of I_{amp} will travel across the patch. The degree to which the cell is depolarized depends also upon the cell's input resistance, R_{cell} . Fig. 11B shows the graph of change in cell membrane potential vs. R_{cell} for $V_p = +30$ mV, $R_{\text{seal}} = 10$ G Ω , and $R_{\text{patch}} = 2$ G Ω . As R_{cell} increases, the ΔV_m rises quickly but peaks at $R_{\text{cell}} = 3.4$ G Ω . The ΔV_m initially rises as R_{cell} increases because $\Delta V_m = I_{\text{patch}} \times R_{\text{cell}}$. The ΔV_m does not continue to rise because increasing R_{cell} decreases I_{patch} (see equation 9).

Over the course of this study, it was easier to evoke action potentials in hippocampal interneurons (9/9 tight-seal recordings) than in cells in the pyramidal cell layer (1/9 tight-seal recordings, Table 1). This could be because the resistance ratio is larger in interneuron recordings, because interneurons have a larger R_{cell} , because the interneurons fire more easily in response to a given tonic depolarization, or a combination thereof. Table 1 shows that the estimated resistance ratios of the interneuron and pyramidal cell recordings were comparable. In fact, several of the pyramidal cell recordings had very high resistance ratios, and yet the cell could not be stimulated. These data suggest that R_{cell} and other intrinsic membrane properties play a large role in the difference between interneurons' and pyramidal cells' responses to a depolarization of V_p .

In summary, the major factors which affect the ability to depolarize the cell are R_{patch} (the lower the better), R_{seal} (the higher the better), and R_{cell} (the higher the better, up to a point).

Single channel openings can depolarize the attached cell in voltage-clamp mode

Fig. 8 illustrates that commanding a depolarization of V_p will depolarize the attached cell. However, the experimenter does not necessarily have to command a depolarizing step in order to pass current across the patch and depolarize the cell. For example, when Fenwick et al. (1982) included acetylcholine (ACh) in the pipette solution, single ACh channel openings were able to trigger action potentials: current flowed out of the amplifier across the channel into the cell and out across the cell membrane, depolarizing the cell. As another example, Vereheugen et al. (1999) triggered action potentials by actually commanding a hyperpolarizing step of V_p : when they used a high K^+ solution in the recording pipette so that $[K^+]_{\text{in pipette}} = [K^+]_{\text{in cell}}$, a hyperpolarizing step of V_p from 0 to -40 mV depolarized the channels in the patch (channel would see a depolarizing step of $+40$ mV), opened voltage-gated K^+ channels, and K^+ current flowed across the patch into the cell and out across R_{cell} , depolarizing the cell and causing an action potential. The important thing to realize is that when I_{amp} is positive (i.e. passing out of the pipette and into the cell), the current going through the patch will depolarize the cell, and when I_{amp} is negative, the current going through the patch will hyperpolarize the cell (Fig. 11A).

Part III: Comparison of cell-attached voltage-clamp recording to cell-attached current clamp recording and the differential effect of the membrane patch in the two modes

Current clamp mode for synaptic potentials and voltage-clamp mode for action potentials—We have demonstrated the recording of synaptic potentials and action potential currents using cell-attached recording. It is notable that the synaptic potentials were recorded using current-clamp mode, and the action potential currents were recorded using voltage-clamp mode. Fig. 12 demonstrates the combined use of tight-seal cell-attached current-clamp and voltage-clamp recordings in a single cell. Note that the synaptic event is evident only in current-clamp mode, not voltage-clamp mode, and that the action potentials, which are tiny in current-clamp mode, are easily seen in voltage-clamp mode.

In Fig. 12, the tight-seal current-clamp recording shows the synaptic potential. In this recording, the CA3 pyramidal cell experienced a hyperpolarization followed by a depolarization during the GABA-mediated population event. Tiny-looking action potentials appeared on the rising phase and at the peak of the depolarization. They were tiny because the amplitude and kinetics of action potentials are highly filtered by the membrane patch in current-clamp mode (see section below). Changing to voltage-clamp mode revealed large action potential currents but no synaptic event. The action potential currents are not all of the same magnitude. From looking at the current-clamp recording and the simultaneous field recordings, we can deduce that the smaller action potentials were occurring during the cellular depolarization. The sections below will explain the theory behind these observations.

Why is cell-attached voltage-clamp mode best-suited for recording action potentials and cell-attached current-clamp mode best-suited for recording synaptic events?—Figure 12 demonstrates that cell-attached voltage-clamp mode is best-suited for recording action potentials and cell-attached current-clamp mode is best-suited for recording synaptic events. What is the explanation for this experimental finding? When the potential is not at steady-state, the patch of membrane under the electrode is represented by a resistor and capacitor in parallel (Fig. 13). In cell-attached voltage-clamp mode, the capacitor aspect of the membrane patch provides a low impedance pathway through the patch for fast events, but not for slow events. Conversely, in cell-attached current-clamp mode, this membrane patch acts as a low-pass filter, filtering fast events such as action potentials, and allowing slow synaptic potentials to pass through with largely-unaffected kinetics. Expanded explanations follow.

Voltage clamp with an infinite seal – comparison of fast and slow events—In cell-attached voltage-clamp a bigger current will be recorded for fast events than for slow events of the same ΔV_m . This is because the patch impedance (Z_{patch}) is smaller for fast events. Appendix 2 shows the calculation of Z_{patch} for an action potential with a rise time of 0.5 ms and for a slow synaptic potential with a rise time of 20 ms. Much of the action potential current recorded using cell-attached voltage clamp is actually capacitive current, since the impedance of the capacitive pathway across the patch is lower than the impedance of the resistive pathway across the patch for fast events (see Appendix 2). The current recorded by the amplifier assuming an infinite R_{seal} can be calculated as:

$$\Delta I = \frac{\Delta V_m}{Z_{\text{patch+elec}}}$$

$\frac{\text{action potential}}{80\text{mV}} = \frac{488\text{pA}}{1.64 \times 10^8 \Omega}$	$\frac{\text{slow synaptic potential}}{10\text{mV}} = \frac{5\text{pA}}{1.91 \times 10^9 \Omega}$
--	---

Note that at steady-state, this same ΔV_m of 80 mV would be recorded as a ΔI of 40 pA, rather than 488 pA, because the current would have to flow across R_{patch} rather than C_{patch} .

Voltage clamp recording of action potential currents with a less than infinite seal—Above we calculated the magnitude of the action potential current that would be recorded by the amplifier if the seal between the electrode and the cell were of infinite resistance and the rise time of the action potential was 0.5 ms. However, there is no need to achieve a seal with a $> 1 \text{ G}\Omega$ resistance in order to record action potential currents in voltage-clamp mode. Even with a seal $< 1 \text{ G}\Omega$, we can still measure the current associated with the action potential.

What percentage of the current passing through the patch (capacitive + resistive) will be recorded by the amplifier with a less than infinite seal? The current coming from the cell through the patch has two possible pathways to ground (Fig. 13). It can go through the electrode to the amplifier or through the seal to ground. As long as R_{seal} is $> R_{\text{elec}}$, more than 50% of the current will go through the electrode. For example, if $R_{\text{seal}} = 100 \text{ M}\Omega$ and $R_{\text{elec}} = 5 \text{ M}\Omega$, the % of current reaching the amplifier = $g_{\text{elec}}/(g_{\text{elec}} + g_{\text{seal}}) = 2 \times 10^{-7} \text{ S}/(2 \times 10^{-7} \text{ S} + 1 \times 10^{-8} \text{ S}) = 95\%$. Of course, if the electrode has gotten clogged in the course of approaching or sealing on the cell, the working electrode resistance will not be the 3–7 $\text{M}\Omega$ of resistance with which the electrode began, and the amplitude of the current measured by the amplifier will be lower.

An additional issue to be considered is the area of the patch of membrane. In Appendix 1, we estimate the area of the membrane patch using the area of a sphere, $4\pi r^2$. However, when the electrode is merely touching the cell, before a tight seal has formed, the area of the patch of membrane within the electrode tip will be better-approximated by the area of a circle, πr^2 . For a loose seal, the capacitance of that membrane would therefore be approximately one-fourth the capacitance estimated in Appendix 1. If the seal were 11 $\text{M}\Omega$, then, B_c would be one-fourth what we estimated in Appendix 2, and $Z_{\text{patch+elec}}$ would be $6.1 \times 10^8 \Omega$. The total current would then be $80 \text{ mV}/(6.1 \times 10^8 \Omega) = 131 \text{ pA}$, rather than 488 pA. The current reaching the amplifier would be $69\% \times 131 \text{ pA} = 90 \text{ pA}$.

Fig 14 demonstrates that action potential currents can be recorded in cell-attached voltage-clamp with a loose seal. The 5 mV step gave 302 pA, giving an R_{tot} of 16.6 $\text{M}\Omega$, and thus an R_{seal} of roughly 11 $\text{M}\Omega$, the value used for the calculation directly above. The action potential current was 74 pA, which is similar to the theoretical amplitude we just calculated.

In summary, the factors most important for recording action potential currents which stand out from baseline noise are the magnitude of the ΔV_m (action potential currents recorded from depolarized cells will be smaller), the rise time of the action potential (faster rise gives bigger current), the working electrode resistance as compared to the seal resistance (R_{elec} should be smaller than R_{seal}), and the capacitance of the patch (bigger capacitance gives bigger current).

Current clamp with an infinite R_{seal} —Assuming an infinite R_{seal} , in steady-state, $V_p = V_m$. When V_m changes, current will flow through the patch until new $V_p = \text{new } V_m$. In current clamp assuming an infinite R_{seal} , $\Delta V_p = \Delta V_m (1 - e^{-t/\tau})$, where $\tau = R_{\text{patch}} \times C_{\text{patch}}$. V_p cannot reach the new value of V_m until the patch capacitance (C_{patch}) is fully charged. If the change in V_m is of a short duration, V_p will never fully reach the new V_m . Thus the patch attenuates the amplitude of fast events like action potentials much more than slow synaptic potentials (Fig. 12).

Current-clamp with a less than infinite R_{seal} : How accurately does the measured ΔV reflect the actual ΔV_m ?—In order to accurately record the resting membrane potential

of the cell to within 1 mV, the R_{seal} needs to be at least $100 \times$ larger than $R_{\text{patch+cell}}$ (Fig. 2). On the other hand, much information can still be gained from a recording with a smaller R_{seal} . For example, as long as the synaptic potentials stand out from baseline noise, a cell-attached current-clamp recording accurately depicts whether a synaptic potential is hyperpolarizing or depolarizing. The deviation of the recorded change in potential from the actual change in membrane potential is in the magnitude and kinetics of the potential change, not its polarity.

Fig. 15 shows the timecourse and magnitude of the changing V_p resulting from a theoretical 80-mV step change in V_m for three different values of R_{seal} . The plots in Fig. 15 were generated using the equation:

$$V_p(t) = V_0 \text{ recorded at rest} + \Delta V_p(t) \quad \text{equation 15}$$

where

$$\Delta V_p(t) = \Delta V_0 \times (1 - e^{-t/\tau}) \quad \text{equation 16}$$

V_0 is determined as in equation 4 and

$\Delta V_0 = V_0 \text{ recorded at new potential after capacitance fully charged} - V_0 \text{ recorded at rest before the step in potential}$

The equation for calculating τ is taken from Mason et al. (2005):

$$\tau = R_{\text{patch}} \times C_{\text{patch}} \times \frac{(R_{\text{patch}} + R_{\text{seal}})}{R_{\text{seal}}} \quad \text{equation 17}$$

With an infinite R_{seal} , this equation reduces to $\tau = R_{\text{patch}} \times C_{\text{patch}}$. C_{patch} is calculated in Appendix 1.

As Fig. 15 illustrates, a smaller R_{seal} results in the measurement of a less negative beginning V_0 , a less positive ending V_0 , and a smaller ΔV . With a greater and greater R_{seal} , the measured magnitude approaches the actual magnitude of the change in potential. For a good seal, for example, $R_{\text{seal}} = 5 \times R_{\text{patch}}$ or $10 \text{ G}\Omega$, a resting E_m of -70 mV would give a resting V_0 of -58 mV , and an 80 mV depolarization of E_m to $+10 \text{ mV}$ would be recorded as a 66 mV depolarization to $+8 \text{ mV}$. For a mediocre seal, for example, $R_{\text{seal}} = 0.5 \times R_{\text{patch}}$ or $1 \text{ G}\Omega$, a resting E_m of -70 mV would give a resting V_0 of -23 mV , and an 80 mV depolarization of E_m to $+10 \text{ mV}$ would be recorded as a 26 mV depolarization to $+3 \text{ mV}$.

As discussed above, the membrane patch slows the kinetics of the measured voltage change. Because the example shown (Fig. 15) is a theoretical instant step in membrane potential, the effects are quite large. V_p would more faithfully depict the kinetics of a slower change in V_m . Note that in this example, V_p takes several ms to reach its new steady-state level even with an infinite R_{seal} (Fig. 15). A smaller R_{seal} results in a longer time for V_p to reach its new steady-state level (Fig. 15).

Importantly, the cell-attached current-clamp recording accurately measures the polarity of the change in potential, i.e. hyperpolarizing vs. depolarizing. The magnitude of the seal resistance does not affect the recorded polarity of the change in potential (Fig. 15). Accordingly, the magnitude of R_{seal} does not affect the recorded polarity of synaptic potentials; however, it can affect the ability to record synaptic potentials clearly. With a low R_{seal} , the synaptic potential can fail to stand out from baseline because of 1) the effect of R_{seal} on the size of the recorded change in potential (Fig. 15) and 2) the effect of R_{seal} on the stability of the measured baseline potential (recall Fig. 3B).

Part IV: Discussion of the advantages of cell-attached recording and stimulation compared to other methods

Advantages of cell-attached recording over other recording methods—I will preface this discussion of the relative advantages of cell-attached recording with a cautionary note. When considering the relative merits of different recording techniques, it is very important to understand the distinction between inaccuracies in measuring a parameter, such as membrane potential, and inaccuracies caused because the recording itself is actually changing the real value of that parameter. These two are very often confused in electrophysiology literature. For example, just because a technique causes you to measure a depolarized resting potential, it does not necessarily mean that the technique caused a depolarization of the cell. It is important to understand whether a technique causes inaccuracies in measurement or actual changes of real parameters, or both.

Cell-attached recording in voltage-clamp mode is an excellent technique to use for recording the firing activity of the attached cell. This technique can be particularly useful when determining the role of a particular cell type in a stereotypic network activity (e.g. Dzhala and Staley, 2004; Kantrowitz et al., 2005) or when determining the effect of an exogenous agonist on cell firing activity (e.g. Hirono and Obata, 2005). Cell-attached recording has advantages in certain respects over whole-cell, perforated patch, and conventional “sharp-electrode” intracellular recording for recording cell firing activity. First of all, compared to whole-cell recording, cell-attached recording is typically easier and more stable. An additional advantage of cell-attached mode over whole-cell mode is that the intracellular contents are not disturbed. Because it disrupts intracellular contents and can thereby change cell membrane potential, a whole-cell recording can actually change cell firing rate. In contrast, done properly (see Part II), cell-attached recording does not. The primary advantage of cell-attached over perforated patch recording is that it is easier and faster to achieve, allowing more successful recordings in a given period of time. Cell-attached recording has several advantages over conventional “sharp electrode” intracellular recording as well: cell-attached recording can be easier to achieve from small cells; cell-attached recordings can be easier to obtain when the electrode must come in at a shallow angle to clear the microscope objective in a visualized-cell set-up; and patch electrodes have a smaller noise problem when recording from submerged preparations than do sharp electrodes. In addition, cell-attached recording may detect the excitatory nature of depolarizing synaptic potentials better than sharp-electrode recording. Sharp-electrode recording is at a disadvantage in this respect because the leak around the sharp electrode can reduce cell input resistance and make a depolarizing potential less likely to cause action potentials (Spruston and Johnston, 1992).

As described in Parts I and III, cell-attached recording can also be used to record membrane potential in current-clamp mode. It should be realized that the measured membrane potential change will tend to be of a smaller magnitude than the actual potential change, but the polarity will be accurately depicted. In contrast to cell-attached, a whole-cell recording can change intracellular ionic composition and actually change the resting membrane potential and change the polarity of synaptic events. Perforated-patch recording leaves the intracellular milieu relatively intact (Horn and Marty, 1988), and depending on the pore-forming antibiotic used, perforated patch recording may not change the reversal potential of synaptic events (Kyrozis and Reichling, 1995). However, cell-attached has the advantage over perforated-patch recording of having even less effect on the intracellular contents.

The question of whether a synaptic potential is hyperpolarizing or depolarizing is fundamental to understanding its effect on cell activity. Accurately discerning the polarity of GABA-mediated synaptic potentials using conventional recording techniques has been particularly difficult because the reversal potential of GABA-mediated events is near the resting membrane potential of the cell. Consequently, neurophysiologists have gone to elaborate measures in

order to determine whether GABA-mediated synaptic potentials are hyperpolarizing or depolarizing at rest (e.g. Verheugen et al., 1999; Chavas and Marty, 2003). Although tight-seal cell-attached recording cannot provide the numerical value of the reversal potential of a synaptic event, it does accurately depict the direction of the synaptic potential (i.e. hyperpolarizing or depolarizing) without perturbing the resting membrane potential or the reversal potential of the synaptic event. Cell-attached current-clamp recording of synaptic potentials may allow distinctions between the effect of synaptically-released GABA on different cell types. For example, the giant GABA-mediated postsynaptic potential (GPSP) in the CA1 pyramidal cell shown in Fig. 4B is a hyperpolarizing potential. In contrast, the GPSP in the CA3 pyramidal cell shown in Fig. 12 (in the presence of a GABA_B antagonist) is a biphasic hyperpolarizing-depolarizing potential. Another contentious issue is whether depolarizing GABA-mediated synaptic events are excitatory. Fig. 12 provides an example of how cell-attached recording can be used to determine whether a depolarizing synaptic potential is excitatory (as it was in that case).

Advantages of tight-seal cell-attached stimulation over other stimulation

methods—This paper has demonstrated that tight-seal cell-attached mode can be used to evoke action potentials in the attached cell. This technique opens up the possibility of doing paired recordings between a presynaptic interneuron and a postsynaptic interneuron or pyramidal cell. The presynaptic cell can be stimulated using cell-attached voltage-clamp mode, and because the action potential current is recorded, the researcher will know when the stimulation is successful.

Stimulation of the presynaptic cell of a pair using tight-seal cell-attached mode has advantages over other paired recording techniques in some respects. For example, cell-attached stimulation allows paired recordings from a normally silent presynaptic cell, offering an advantage over waiting for the presynaptic cell to fire, which you would normally have to do with a loose cell-attached recording (e.g. Kondo and Marty, 1998). (Stimulating the attached cell in loose cell-attached mode requires large voltages and currents, which are not possible with most amplifiers, and which are associated with membrane breakdown (Barbour and Isope, 2000)). An advantage that cell-attached stimulation has over extracellular minimal stimulation (e.g. Chapman and Lacaille, 1999) is that using cell-attached easily and reliably insures that only a single, identified presynaptic cell is stimulated. Cell-attached mode has two advantages over stimulating the cell in whole-cell mode: first, achieving a cell-attached recording is easier than achieving a whole-cell recording, and second, it avoids the decline in transmitter release with time that occurs when stimulating the presynaptic cell in whole-cell mode (Kondo and Marty, 1998). Cell-attached stimulation also has advantages over sharp-electrode stimulation: a stable sharp-electrode recording can be harder to maintain while establishing a recording from a second cell, can be difficult to achieve from small cells, and can be difficult to use in a visualized-cell set-up, as mentioned above.

Conclusions

Cell-attached recording can be used to measure cell firing activity, to record resting membrane potential and synaptic potentials, and to evoke action potentials in the attached cell. The magnitude of the seal resistance determines what types of experiments can be accomplished with a cell-attached recording: a loose seal is adequate for recording action potential currents, and a tight seal is required for evoking action potentials in the attached cell and for recording resting potential and synaptic potentials.

Cell-attached voltage-clamp mode, rather than current-clamp mode, is best-suited for recording spontaneous firing activity in the attached cell. When recording spontaneous firing activity, it is essential to set the command potential at the voltage which gives an I_{amp} of 0 pA, so that

you do not change the membrane potential of the attached cell and thus cell firing rate. The factors most important for recording action potential currents which stand out from baseline noise are the magnitude of the ΔV_m (bigger action potentials give bigger action potential currents; thus a depolarized cell will have smaller action potential currents), the rise time of the action potential (faster rise gives bigger current), the working electrode resistance as compared to the seal resistance (R_{elec} should be smaller than R_{seal}), and the capacitance of the patch (bigger capacitance gives bigger current).

Tight-seal cell-attached voltage clamp mode can be used to evoke action potentials in the attached cell. The attached cell can be depolarized by commanding a depolarizing voltage step. The change in cell membrane potential accomplished by the depolarizing step equals $I_{patch} \times R_{cell}$. Thus, the major factors which affect the ability to depolarize the cell are R_{patch} (the lower the better), R_{seal} (the higher the better), and R_{cell} (the higher the better, up to a point).

Cell-attached current-clamp mode, rather than voltage-clamp mode, is best-suited for recording cell resting potential and synaptic potentials. The tighter the seal, the closer the measured voltage will be to the cell's actual membrane potential. When recording changes in membrane potential, the patch acts as a low-pass filter, reducing the apparent amplitude and slowing the apparent kinetics of fast events. Importantly, tight-seal cell-attached current-clamp recording accurately depicts the direction (depolarizing or hyperpolarizing) of changes in membrane potential and can thus correctly identify depolarizing vs. hyperpolarizing postsynaptic potentials. Because the intracellular contents are left intact, cell-attached recording has an advantage over whole-cell recording, in that it does not change the very parameter it is trying to measure.

Acknowledgements

Qizong Yang participated in some of the experiments involving cell-attached interneuron recordings. The author thanks S. Young, M. Stewart, S. Fox, and A. Salah for helpful discussions, and T. Kunitake for early discussions of cell stimulation in cell-attached voltage-clamp mode. Grants: This project was sponsored by National Institutes of Health grants NS047435 to K. Perkins and K07AG00959 to S. Mirra.

References

- Barbour B, Isope P. Combining loose cell-attached stimulation and recording. *J Neurosci Methods* 2000;103:199–208. [PubMed: 11084213]
- Barry PH, Lynch JW. Liquid junction potentials and small cell effects in patch-clamp analysis. *J Membrane Biol* 1991;121:101–17. [PubMed: 1715403]
- Blanton MG, Lo Turco JJ, Kriegstein AR. Whole cell recording from neurons in slices of reptilian and mammalian cerebral cortex. *J Neurosci Methods* 1989;30:203–10. [PubMed: 2607782]
- Chapman CA, Lacaille J-C. Cholinergic induction of theta-frequency oscillations in hippocampal inhibitory interneurons and pacing of pyramidal cell firing. *J Neurosci* 1999;19:8637–45. [PubMed: 10493764]
- Chavas J, Marty A. Coexistence of excitatory and inhibitory GABA synapses in the cerebellar interneuron network. *J Neurosci* 2003;23:2019–31. [PubMed: 12657660]
- Costantin JL, Charles AC. Spontaneous action potentials initiate rhythmic intercellular calcium waves in immortalized hypothalamic (GT1-1) neurons. *J Neurophysiol* 1999;82:429–35. [PubMed: 10400969]
- Dzhala VI, Staley KJ. Mechanism of fast ripples in the hippocampus. *J Neurosci* 2004;24:8896–8906. [PubMed: 15470156]
- Fenwick EM, Marty A, Neher E. A patch-clamp study of bovine chromaffin cells and of their sensitivity to acetylcholine. *J Physiol* 1982;331:577–97. [PubMed: 6296371]
- Gibb, AJ.; Edwards, FA. *The Plymouth workshop handbook*. Cambridge: The Company of Biologists Limited; 1987. Patch-clamp recording from cells in sliced tissues. Microelectrode techniques; p. 255-74.

- Hayar A, Karnup S, Shipley MT, Ennis M. Olfactory bulb glomeruli: external tufted cells intrinsically burst at theta frequency and are entrained by patterned olfactory input. *J Neurosci* 2004;24:1190–9. [PubMed: 14762137]
- Hirono M, Obata K. Alpha-adrenoceptive dual modulation of inhibitory GABAergic inputs to Purkinje cells in the mouse cerebellum. *J Neurophysiol* 2005;95:700–708. [PubMed: 16251261]
- Horn R, Marty A. Muscarinic activation of ionic currents measured by a new whole-cell recording method. *J Gen Physiol* 1988;92:145–59. [PubMed: 2459299]
- Kantrowitz JT, Francis NN, Salah A, Perkins KL. Synaptic depolarizing GABA response in adults is excitatory and proconvulsive when GABA_B receptors are blocked. *J Neurophysiol* 2005;93:2656–67. [PubMed: 15590725]
- Kondo S, Marty A. Synaptic currents at individual connections among stellate cells in rat cerebellar slices. *J Physiol* 1998;509.1:221–32. [PubMed: 9547395]
- Kyrozis A, Reichling DB. Perforated-patch recording with gramicidin avoids artifactual changes in intracellular chloride concentration. *J Neurosci Methods* 1995;57:27–35. [PubMed: 7540702]
- Mason MJ, Simpson AK, Mahaut-Smith MP, Robinson HPC. The interpretation of current clamp recordings in the cell-attached patch-clamp configuration. *Biophys J* 2005;88:739–50. [PubMed: 15516522]
- Michelson HB, Wong RKS. Excitatory synaptic responses mediated by GABA_A receptors in the hippocampus. *Science* 1991;253:1420–3. [PubMed: 1654594]
- Perkins, KL. 2005 Abstract Viewer/Itinerary Planner. Washington, DC: Society for Neuroscience; 2005. Cell-attached voltage-clamp and current-clamp recording and stimulation techniques in brain slices – when is a tight seal necessary?; p. # 569.18
- Perkins, KL. 2004 Abstract Viewer/Itinerary Planner. Washington, DC: Society for Neuroscience; 2004. Tight-seal cell-attached stimulation and recording techniques in hippocampal slice; p. # 920.11
- Perkins KL, Wong RKS. Ionic basis of the postsynaptic depolarizing GABA response in hippocampal pyramidal cells. *J Neurophysiol* 1996;76:3886–94. [PubMed: 8985886]
- Sherman-Gold, R., editor. *The Axon Guide*. Axon Instruments, Inc; 1993. Chapter 5: Advanced Methods in Electrophysiology; p. 103
- Spruston N, Johnston D. Perforated patch-clamp analysis of the passive membrane properties of three classes of hippocampal neurons. *J Neurophysiol* 1992;67:508–529. [PubMed: 1578242]
- Tyzio R, Ivanov A, Bernard C, Holmes GL, Ben-Ari Y, Khazipov R. Membrane potential of CA3 hippocampal pyramidal cells during postnatal development. *J Neurophysiol* 2003;90:2964–2972. [PubMed: 12867526]
- Verheugen JAH, Fricker D, Miles R. Noninvasive measurements of the membrane potential and GABAergic action in hippocampal interneurons. *J Neurosci* 1999;19:2546–2555. [PubMed: 10087068]

Appendix 1 – Estimate of patch capacitance

If we assume the patch is an omega-shaped membrane that is pulled into the electrode, we can calculate an estimated surface area (SA) of the patch by using the equation for SA of a sphere, $SA = 4\pi r^2$. Using an estimated radius, r , of 2 μm , gives a SA of $5.027 \times 10^{-7} \text{ cm}^2$. Multiplying SA by a capacitance per unit area of $1 \mu\text{F}/\text{cm}^2$ gives a patch capacitance (C_{patch}) of 0.5 pF.

Appendix 2 – Cell-attached voltage-clamp when V_m is changing

When the cell membrane potential is not at steady-state, the membrane patch is represented by a resistor and capacitor in parallel (Fig. 13). When a ΔV_m occurs, current flows from the cell across the patch to the amplifier. Below we will calculate the impedance of the pathway the current takes to the amplifier. We will initially use conductance, susceptance, and admittance for the calculations rather than their reciprocals resistance, reactance, and impedance since the resistor and capacitor are in parallel.

Assuming an infinite R_{seal} for now:

resistance of patch = $R_{\text{patch}} = 2 \text{ G}\Omega$

conductance of patch = $g_{\text{patch}} = 1/R_{\text{patch}} = 5 \times 10^{-10} \text{ S}$

susceptance of patch capacitance = $B_C = 2 \pi f C_{\text{patch}} = (3.14 \times 10^{-12} \text{ F}) \times f$, where f is frequency

admittance of patch, Y_{patch} = vector sum of the conductance and susceptance

$$Y_{\text{patch}} = \sqrt{g^2 + B_C^2}$$

At the end we will convert back to impedance, $Z_{\text{patch}} = 1/Y_{\text{patch}}$, and add R_{elec} .

If frequency is fast, Z_{patch} is smaller. For example,

At $f = 2 \text{ kHz}$ (0.5 ms rise time):

$$B_C = 6.28 \times 10^{-9} \text{ S}$$

$$Y_{\text{patch}} = \sqrt{g^2 + B_C^2}$$

$$Y_{\text{patch}} = 6.3 \times 10^{-9} \text{ S}$$

$$Z_{\text{patch}} = 1.59 \times 10^8 \Omega$$

$$Z_{\text{patch+elec}} = 1.64 \times 10^8 \Omega$$

At $f = 50 \text{ Hz}$: (20 ms rise time):

$$B_C = 1.57 \times 10^{-10} \text{ S}$$

$$Y_{\text{patch}} = 5.24 \times 10^{-10} \text{ S}$$

$$Z_{\text{patch}} = 1.91 \times 10^9 \Omega$$

$$Z_{\text{patch+elec}} = 1.91 \times 10^9 \Omega$$

At 2 kHz, the B_C dominates Y_{patch} because it has the higher admittance at that frequency. In contrast, at 50 Hz, the g_{patch} dominates Y_{patch} because it has the higher admittance.

How much of the current we record is capacitive current (I_C) and how much is resistive current (I_R)?

Using the total currents of 488 pA for action potential current and 5.2 pA for synaptic potential current (see Part III):

Action potential (0.5 ms rise time):

$$I_C = (80 \text{ mV} - \text{voltage drop across } R_{\text{elec}}) \times B_C$$

$$I_C = ((80 \text{ mV} - (488 \text{ pA} \times 5 \text{ M}\Omega)) \times B_C$$

$$I_C = (80 \text{ mV} - 2.4 \text{ mV}) \times (6.28 \times 10^{-9} \text{ S}) = 487 \text{ pA}$$

$$I_R = (80 \text{ mV} - \text{voltage drop across } R_{\text{elec}}) \times g_{\text{patch}} = 39 \text{ pA}$$

(Total current is vector sum of current through capacitor and current through resistor.)

Slow synaptic potential (20 ms rise time):

$$I_C = (10 \text{ mV} - \text{voltage drop across } R_{\text{elec}}) \times (B_C)$$

$$I_C = (10 \text{ mV} - 0.026 \text{ mV}) \times (1.57 \times 10^{-10} \text{ S}) = 1.6 \text{ pA}$$

$$I_R = (10 \text{ mV} - \text{voltage drop across } R_{\text{elec}}) \times g_{\text{patch}} = 5 \text{ pA}$$

Therefore, for action potentials, most of the recorded current is capacitive current and for slow synaptic potentials, most of the recorded current is resistive current.

Fig. 1. Circuit involved in cell-attached current clamp recording

(A) Arrow indicates direction of current flow. The voltage is measured at point V_x . The battery represents the resting membrane potential of the cell. The current flows through the three resistors in series. The largest voltage drop will occur across the largest resistor. If R_{seal} is infinitely large, then all of the voltage drop will occur across R_{seal} , and the voltage at V_x will be equal to -70 mV . If $R_{\text{seal}} \ll R_{\text{patch}}$, then all of the voltage drop will occur before the point labeled V_x , and V_x will be 0 mV . (B) Schematic showing the cell, the patch electrode, and the placement of the different resistances. (C) Adding an electrode and an amplifier to the circuit shown in A does not change the voltage at V_x . The impedance of the amplifier is so great that no current flows through the electrode to the amplifier, and no voltage drop occurs between

the point labeled V_x and the amplifier. The voltage measured by the amplifier is equal to V_x . **(D)** When the electrode solution and bath solution are not the same, the liquid junction potential (E_{lj}) between the electrode solution and the bath solution must be considered. When the electrode is in solution, before a seal is attempted, E_{lj} is offset by applying an equal and opposite voltage at the amplifier E^*_{lj} . As long as $R_{seal} \ll R_{patch+cell}$, E_{lj} and E^*_{lj} cancel each other out, and the amplifier measures 0 mV. As R_{seal} increases, the amplifier senses less of E_{lj} but all of E^*_{lj} , so that they no longer cancel each other out. In all conditions, the voltage measured by the amplifier = E^*_{lj} + the weighted average of E_{lj} and E_m (see equation 2). (R_{elec} is left out of D for simplicity, since it does not affect measured voltage.)

Fig. 2. The relative resistances of R_{seal} and $R_{\text{patch + cell}}$ determine the voltage measured by the amplifier in cell-attached current-clamp mode

(A) Graph of measured voltage (V_0) vs. resistance ratio for a theoretical recording. Plot was generated using equation 4, with a resting membrane potential (E_m) of -70 mV. As the ratio of R_{seal} to $R_{\text{patch + cell}}$ increases, the measured voltage approaches -70 mV. Note the log scale of the x-axis. (B) Graph of V_0/E_m vs. resistance ratio for a theoretical recording. V_0/E_m approaches 1 at large ratios of R_{seal} to $R_{\text{patch + cell}}$. Plot was generated using equation 5. Note the log scale of the x-axis.

Fig. 3. Channels opening and closing in the membrane patch will change the voltage measured by the amplifier. The effect is much smaller with a large resistance ratio

(A) Channels opening in the membrane patch will change the voltage measured by the amplifier to a value closer to actual membrane potential. Plot of mV change in V_0 with a doubling of g_{patch} . Peak change in V_0 (in mV) with a doubling of patch conductance occurs with an original resistance ratio near 0.72. Values used to generate graphs were a constant R_{cell} of 100 M Ω , constant E_m of -70 mV, $g_{\text{patch}} = 500$ pS ($R_{\text{patch}} = 2$ G Ω) doubling to $g_{\text{patch}} = 1$ nS ($R_{\text{patch}} = 1$ G Ω). Equation 4 was used to calculate V_0 before and after a theoretical doubling of g_{patch} .

(B) Resistance ratio affects stability of measured voltage. Recorded from a CA3 pyramidal cell in cell-attached current-clamp mode (1st pyramidal cell listed in Table 1). Resistance ratio

increased as the recording progressed. Top trace is earlier in the recording when measured resting potential (V_0) varied widely from -20 – -40 mV. Bottom trace was recorded several minutes later after R_{seal} had increased; note the more stable V_0 . (Single channel openings and closings, which would cause a varying R_{patch} , were apparent in voltage-clamp mode.)

Fig. 4. Synaptic potentials can be recorded in tight-seal cell-attached current clamp mode CA1 pyramidal cell (2nd pyramidal cell listed in Table 1) recording. **(A)** Synaptic potentials recorded in 4-aminopyridine (4-AP) with both glutamatergic and GABAergic transmission intact. Top row is cell-attached current-clamp. Bottom row is a simultaneous field recording. **(B)** Same recording after the addition of ionotropic glutamate antagonists CNQX and D-AP5. The large hyperpolarizing synaptic potential in the cell-attached current-clamp recording is a giant GABA-mediated postsynaptic potential (GPSP). The depolarizing potentials present in the 4-AP-alone condition shown in A were blocked by the glutamate antagonists, indicating that they were glutamate-mediated synaptic potentials.

Fig. 5. Action potential currents recorded using cell-attached voltage-clamp

(A) Cell-attached voltage-clamp recording from a neuron in the CA1 pyramidal cell layer (3rd pyramidal cell listed in Table 1). Recording pipette is voltage-clamped at 0 mV; baseline I_{amp} is +15 pA (therefore cell is depolarized – see Fig. 8). (B) One action potential current from A shown on an expanded time scale, illustrating the characteristic negative-then-positive shape. Extracellular saline included 4-AP, CNQX, and D-AP5.

Fig. 6. Circuit involved in cell-attached voltage clamp recording

In this case, R_{seal} is parallel to R_{patch} and R_{cell} , and R_{patch} and R_{cell} are in series. The current I_{amp} will split between the two available pathways to ground. The pathway with least resistance will have the greater current; therefore if R_{seal} is larger than $R_{\text{patch}} + R_{\text{cell}}$, a greater proportion of I_{amp} will travel across R_{patch} and R_{cell} than across R_{seal} .

Fig. 7. The voltage measured in cell-attached current-clamp mode is equal to the V_p associated with zero current in voltage clamp mode

Amplifier was switched from current clamp (CC) mode to voltage clamp (VC) mode by flipping the switch on the amplifier. I_{amp} and V_p were recorded simultaneously. Note that the amplifier measures -60 mV in CC mode and that clamping at -60 mV in voltage-clamp mode gives 0 current; whereas, clamping at 0 mV in VC mode gives +10 pA. (Current transients caused by flipping between modes and current transient at beginning of voltage steps have been clipped.) Recording is from a cell in the CA1 pyramidal cell layer (6th pyramidal cell in Table 1). No drugs were in the extracellular saline.

Fig. 8. Command potential affects firing rate of the attached cell. Cells can be stimulated to fire action potentials by commanding a depolarizing step with a tight-seal cell-attached recording (A) Tight-seal cell-attached voltage-clamp recording from interneuron in CA1 *str. oriens* (1st interneuron listed in Table 1). Current measured by the amplifier (I_{amp}) is shown in the upper panel. Commanded pipette voltage (V_p) is shown below. Cell did not fire at rest (-70 mV). Commanding increasingly depolarized potentials caused the amplifier to pass positive current (seen as a positive shift in baseline current). Current passed across the patch into the cell and depolarized the cell. The resulting action potentials were recorded as action potential currents. Recorded in the presence of 4-AP, CNQX, and D-AP5. (B) Tight-seal cell-attached recording from an interneuron in CA1 *str. lacunosum-moleculare* (2nd interneuron listed in Table 1). A

commanded voltage step from the zero-current potential of -60 mV to $+30$ mV passed current into the cell and caused it to fire action potentials. Recorded in the presence of 4-AP, CNQX, and D-AP5. (C) Tight-seal cell-attached recording from an interneuron in CA3 *str. lacunosum-moleculare* (5th interneuron listed in Table 1). Firing frequency increased as V_p was made more positive. No drugs were in the extracellular saline. (Current transients at beginning and end of voltage steps in A, B, and C have been clipped.)

Fig. 9. Increasing the ratio $R_{\text{seal}}/R_{\text{patch+cell}}$ increases the proportion of I_{amp} that travels across the patch

Graph of $I_{\text{patch}}/I_{\text{amp}}$ vs. resistance ratio for a theoretical recording. Plot was generated using equation 13. Note the log scale of the x-axis.

Fig. 10. Magnitude of I_{patch} depends upon V_p , R_{seal} , and $R_{patch+cell}$

Graph of I_{patch} vs. V_p for 3 different values of R_{seal} . Larger R_{seal} and more positive V_p give a larger I_{patch} . Larger $R_{patch+cell}$ gives a smaller I_{patch} . The equation used to generate the plot is $I_{patch} = [(V_p - V_0) - (I_{amp} \times R_{elec})]/R_{patch+cell}$, which is equation 9. Equation 8 was used to calculate I_{amp} . R_{elec} value used was 5 M Ω . R_{seal} and $R_{patch+cell}$ values for the different plots are listed in the box. A larger value of $R_{patch+cell}$ was used when $R_{seal} < 1\text{ G}\Omega$ in order to reflect the actual experimental situation (see Part II).

Fig. 11. A positive I_{amp} depolarizes the cell. The magnitude of the change in membrane potential depends upon R_{seal} and R_{cell}

(A) Theoretical graph of change in membrane potential vs. I_{amp} . The change in membrane potential is larger with a larger R_{seal} because a greater proportion of I_{amp} travels across the patch. Note that a positive I_{amp} causes a depolarization and a negative I_{amp} causes a hyperpolarization. Equation 11 was used to calculate I_{patch} . R_{patch} was constant at $2 \text{ G}\Omega$, and R_{cell} was $200 \text{ M}\Omega$. (B) Theoretical graph of change in membrane potential vs. R_{cell} . The change in membrane potential for a given V_p is greater for a larger R_{cell} , up to a point. The change in membrane potential peaks at $R_{cell} = 3.4 \text{ G}\Omega$. I_{amp} was calculated using equation 8 with $V_p = +30 \text{ mV}$. I_{patch} was calculated using equation 11. Change in membrane potential = $I_{patch} \times R_{cell}$.

Fig. 12. Tight-seal cell-attached current-clamp recording is best-suited for recording synaptic events whereas voltage-clamp recording is best-suited for recording action potentials

Tight-seal cell-attached recording from CA3 pyramidal cell (5th pyramidal cell listed in Table 1). Extracellular saline includes 4-AP, CNQX, D-AP5, and the GABA_B antagonist CGP 55845. Top row is cell-attached. Bottom row is a simultaneous field recording. Left panel is current clamp (CC). Right panel is voltage clamp (VC). Two successive GPSPs were recorded, one in current clamp and one in voltage clamp. Slash marks in field recording indicate a time gap of approximately 65 s. Recording alternately in CC and VC modes along with a simultaneous field recording allows us to see that the action potential currents recorded in voltage-clamp mode are caused by a large depolarization like the one measured in current-clamp mode. Notice that in the current-clamp recording, the action potentials have been greatly filtered by the patch capacitance and that in the voltage-clamp recording, the synaptic event is not evident. (A recording similar to the right panel but from a different cell is shown in Kantrowitz et al. 2005).

Fig. 13. The circuit involved when the cell membrane potential is changing

The membrane patch is represented by a resistor and capacitor in parallel. In cell-attached current-clamp mode, the charging of the capacitor slows down the apparent kinetics of fast membrane potential changes such as action potentials. In addition, the apparent magnitude of fast changes in membrane potential is reduced; for example, apparent action potential magnitude is profoundly reduced due to the filtering effect of the patch of membrane. In cell-attached voltage-clamp mode, the capacitor provides a low impedance pathway through the patch for fast events such as action potentials, resulting in the measurement of a current with an approximately 10-fold larger magnitude than would be measured at steady state for the same magnitude change in membrane potential.

Fig. 14. Loose seal is adequate for recording action potential currents in cell-attached voltage-clamp mode

Recording is from an interneuron in CA1 *str. oriens*. The left side of the trace shows the current response to a 5 mV step. The action potential current (negative deflection of 74 pA followed by smaller positive deflection) appears on the right side of the trace. The 5 mV step caused a ΔI of 302 pA. Using Ohm's law gives an R_{tot} of 16.6 M Ω . With an electrode resistance of approximately 5 M Ω , R_{seal} calculates to roughly 11 M Ω , which is a loose seal. No drugs were added to the extracellular saline.

Fig. 15. The magnitude and kinetics of the measured change in potential are affected by R_{seal} and the membrane patch, but the polarity of the ΔV_m is accurately depicted

Response to a theoretical 80 mV square step of V_m from -70 mV to $+10$ mV. Curved black lines show the voltage measured by the amplifier for three different theoretical R_{seal} values. Time 0 is the moment of the immediate 80 mV step in cell membrane potential. A smaller R_{seal} results in a less negative beginning V_0 , a less positive ending V_0 and a smaller ΔV_0 . A smaller R_{seal} also results in a longer time for V_p to reach its new steady-state level. Note that V_p takes several ms to reach its new steady-state level even with an infinite R_{seal} . Importantly, the magnitude of R_{seal} does not affect the measurement of the direction of the $-V_m$, i.e. hyperpolarizing v. depolarizing. Equations 15–17 were used to generate the plots. Values used were $R_{\text{patch}} = 2$ G Ω and $R_{\text{cell}} = 100$ M Ω .

Table 1**Summary of tight-seal cell-attached recordings from neurons in hippocampal slices**

A “yes” in the column headed “stimulated by depol?” means that commanding a depolarizing voltage step to $V_p = 0$ mV (or a smaller ΔV in some cells) in cell-attached voltage-clamp mode was able to make the cell fire action potentials or to increase the firing rate of the cell if it was already firing at rest. 6/8 of the “no” cells were tested with larger steps (to at least $V_p = +20$ mV; also ineffective) when a step to 0 mV did not evoke any action potentials. “R ratio” refers to the resistance ratio, which is defined as $R_{\text{seal}}/R_{\text{patch + cell}}$. R ratio was estimated assuming an E_m of -70 mV. For recordings with an estimated R ratio >20 , the listed $R_{\text{patch + cell}}$ is the value calculated using an R ratio of 20.

R_{tot} (G Ω)	V_0 (mV)	stimulated by depol?	estimated R ratio	estimated $R_{\text{patch + cell}}$
Interneurons				
2.1	-70	yes	>20	2.2
2.2	-61	yes	7	2.5
3.4	-70	yes	>20	3.6
4.2	-70	yes	>20	4.4
4.2	-50	yes	2.5	5.9
4.9	-65	yes	15	5.2
6.6	-65	yes	15	7.0
6.6	-57	yes	4.7	8.0
6.7	-50	yes	2.5	9.4
Pyramidal cells				
1.1 (0.6 – 4.1)*	-69	no	>20	1.2 (0.6 – 4.3)**
1.8 (0.7 – 2.6)*	-70	no	>20	1.9 (0.7 – 2.7)**
2.3	-50	yes	2.5	3.2
5.6	-70	no	>20	5.9
5.6	-67	no	20	5.9
5.7	-57	no	4.7	6.9
6.1	-60	no	6	7.1
6.8	-55	no	3.7	8.6
7.8	-48	no	2.2	11.3

* Single channel openings and closings apparent; average R_{tot} listed first; range given in parentheses.

** Average $R_{\text{patch + cell}}$ listed first, range given in parentheses. The cells included in the “pyramidal cells” list are cells found in the pyramidal cell layer; they were not confirmed to be pyramidal cells.